

Pia Ricco 15171

Pia Ricco Outdoor Pendant Light Instruction Manual

Model: 15171

IMPORTANT SAFETY INFORMATION

Please read these instructions carefully before installation and retain them for future reference. All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). If you are unfamiliar with proper electrical wiring connections, consult a qualified electrician.

- **WARNING:** To avoid the risk of electric shock, always turn off the main power supply at the circuit breaker or fuse box before beginning installation or performing any maintenance.
- This fixture is ETL Listed, ensuring compliance with North American safety standards.
- Do not exceed the maximum wattage specified for the bulb.
- Handle glass components with care.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Light Fixture Body with Glass Shade
- Mounting Canopy
- Adjustable Chain
- Mounting Hardware (screws, wire nuts, crossbar)
- Instruction Manual

Note: Bulb is not included.

SPECIFICATIONS

Feature	Specification
---------	---------------

Model Number	15171
Dimensions (L x W x H)	5.91" x 5.91" x 57.92" (max height with chain)
Item Weight	5.5 Pounds
Material	Metal, Glass
Finish Type	Matte Black
Shade Material	Clear Glass
Bulb Base	E26 Medium Base
Max Wattage	60W
Voltage	120V (AC)
Indoor/Outdoor Usage	Indoor, Outdoor
Water Resistance Level	Water Resistant (IP65)
Installation Type	Ceiling Mount

SETUP & INSTALLATION

1. Before You Begin

Tools Required (Not Included): Screwdriver, Wire Strippers, Electrical Tape, Pliers, Safety Glasses, Ladder.

1. Turn off power at the circuit breaker or fuse box.
2. Ensure the mounting surface can support the weight of the fixture.
3. Unpack all components and inspect for any damage.

2. Mounting the Fixture

This fixture is designed for both flat and sloped ceilings.

Flat/Sloped Ceiling Available



Figure 1: Ceiling Mount Adaptability. The fixture's canopy allows for installation on both flat and angled ceilings, ensuring a secure and level hang.

1. Attach the mounting crossbar to the junction box using the provided screws.
2. Determine the desired hanging height. The chain is adjustable up to 36 inches. Use pliers to open and remove excess chain links if necessary.
3. Thread the fixture wires through the chain and canopy.
4. Secure the chain to the canopy and the fixture body.

DETAIL



Figure 2: Product Dimensions and Adjustable Chain. This image illustrates the overall dimensions of the pendant light, including the maximum adjustable chain length of 36 inches (91.4 cm) and a total height of 57.92 inches (147 cm).

3. Wiring Instructions

1. Connect the fixture's black wire to the house's black (Live) wire using a wire nut.
2. Connect the fixture's white wire to the house's white (Neutral) wire using a wire nut.
3. Connect the fixture's ground wire to the house's ground wire (bare copper or green) and to the mounting crossbar using a wire nut or ground screw.
4. Carefully tuck all wires into the junction box.

4. Installing the Bulb and Glass Shade

1. Align the canopy with the mounting crossbar and secure it with the provided screws.
2. Insert one E26 medium base bulb (not included) into the socket. Do not exceed 60W.
3. Carefully attach the clear glass shade to the fixture body according to the design.



Figure 3: Key Features. This image details the ETL certification, IP65 weather resistance, the E26 bulb base for various compatible bulbs, and the elegant, sturdy tempered clear glass shade.



Figure 4: Compatible Bulbs. The fixture supports standard base bulbs under 60W, including LED, Incandescent,

Halogen, and CFL types (bulb not included).

Once installation is complete, restore power at the circuit breaker.

OPERATING INSTRUCTIONS

The Pia Ricco Outdoor Pendant Light operates via a standard wall switch (not included). Once installed and wired correctly, simply toggle the wall switch to turn the light on or off.

- **Bulb Compatibility:** This fixture is compatible with E26 medium base LED, Incandescent, and Halogen bulbs up to 60 watts.
- For optimal energy efficiency and longevity, LED bulbs are recommended.

MAINTENANCE

Regular maintenance ensures the longevity and appearance of your pendant light.

- **Cleaning:** To clean the fixture, turn off the power and wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents as they may damage the finish or glass.
- **Bulb Replacement:** Ensure power is off before replacing the bulb. Allow the old bulb to cool completely before removal. Screw in the new E26 bulb firmly.
- **Weather Resistance:** The fixture is designed to be weather-resistant (IP65 rated), offering protection against UV, water, wind, and snow exposure. Periodically inspect for any debris accumulation.



Figure 5: Weather Resistance. The Pia Ricco Outdoor Pendant Light is built to withstand various outdoor elements, including UV radiation, water (IP65 rated), wind, and snow.

TROUBLESHOOTING

If you encounter issues with your pendant light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture Loose wiring connection Faulty bulb	Check circuit breaker/fuse Ensure all wire connections are secure (power off first) Replace bulb with a new, working one
Light flickers	Loose bulb Incorrect bulb type/wattage Loose wiring	Tighten bulb Ensure bulb is E26 base and max 60W Check wiring connections (power off first)
Glass shade is loose	Securing mechanism not tightened	Gently tighten the screws or rings holding the glass shade in place

WARRANTY & SUPPORT

The Pia Ricco Outdoor Pendant Light (Model 15171) comes with a **full 1-year warranty** from the date of purchase, covering defects in materials and workmanship.

If you experience any issues or have questions regarding installation, operation, or maintenance, please contact Pia Ricco customer support. Refer to your purchase documentation or the Pia Ricco brand store on Amazon for contact details.

Pia Ricco Brand Store: [Visit the Pia Ricco Store on Amazon](#)