

[Manuals.plus](#) /

› [Darkaway](#) /

› Darkaway Flush Mount Ceiling Light Fixture User Manual (Model: Indoor Outdoor Ceiling Light)

Darkaway Indoor Outdoor Ceiling Light

Darkaway Flush Mount Ceiling Light Fixture User Manual

Model: Indoor Outdoor Ceiling Light

IMPORTANT SAFETY INFORMATION

Please read and understand this entire manual before attempting to assemble, operate, or install the product. Failure to do so could lead to electric shock, fire, or other injuries that could be fatal or cause serious damage.

- Always disconnect power before installation or maintenance.
- Consult a qualified electrician if you are unsure about the installation process.
- Ensure all electrical connections comply with local codes and ordinances.
- Do not exceed the recommended wattage for bulbs (Max 60W per socket).
- This fixture is UL listed for safety.

PACKAGE CONTENTS

Verify that all parts are present before beginning installation.

- Mounting Hardware
- Fixture Base with Sockets
- Glass Shade
- Metal Cage
- Center Pole/Nut



Image: All components of the Darkaway Flush Mount Ceiling Light Fixture laid out on a grey mat, including the fixture base, glass shade, metal cage, mounting hardware, and instructions.

SPECIFICATIONS

Brand	Darkaway
Model Number	Indoor Outdoor Ceiling Light
Dimensions (L x W x H)	10.43"L x 10.43"W x 4.98"H
Material	Metal, Glass
Color	Black Clear Glass
Number of Light Sources	2
Bulb Base	E26

Max Wattage	60 watts per socket
Voltage	110 Volts (AC)
Indoor/Outdoor Usage	Indoor
Certification	UL Listed



Image: Diagram showing the dimensions of the Darkaway Flush Mount Ceiling Light Fixture, with a diameter of 10.43 inches and a height of 4.98 inches.

SETUP AND INSTALLATION

1. Prepare for Installation:

- Turn off power at the circuit breaker or fuse box.
- Ensure the mounting surface is clean, dry, and flat.

- Unpack all components and inspect for damage.

2. Mounting Bracket Installation:

- Attach the mounting bracket to the junction box using the provided screws.
- Ensure the bracket is securely fastened.

3. Wiring Connections:

- Connect the fixture's black wire to the house's black (live) wire.
- Connect the fixture's white wire to the house's white (neutral) wire.
- Connect the fixture's ground wire to the house's ground wire.
- Secure all connections with wire nuts and electrical tape.

4. Fixture Base Attachment:

- Align the fixture base with the mounting bracket and secure it with the provided screws.

5. Bulb Installation:

- Screw E26 base bulbs (not included, max 60W) into the sockets.

6. Glass Shade and Metal Cage Assembly:

- Place the glass shade over the bulbs.
- Position the metal cage over the glass shade.
- Secure the glass shade and metal cage using the center pole and decorative nut.

7. Final Test:

- Restore power at the circuit breaker and test the light fixture.

Your browser does not support the video tag.

Video: This video demonstrates the assembly and bulb installation process for the Darkaway Flush Mount Ceiling Light Fixture, showing how to secure the bulbs and attach the glass shade and metal cage.

Your browser does not support the video tag.

Video: This video provides a visual guide to the installation of the Darkaway Flush Mount Ceiling Light Fixture, including unboxing, component identification, and the final installed appearance.

OPERATING INSTRUCTIONS

This fixture operates with standard wall switches. Ensure compatible E26 bulbs are installed for proper function.

- **Power On/Off:** Use your existing wall switch to turn the light fixture on or off.
- **Bulb Compatibility:** Compatible with Halogen, LED, Fluorescent, and Incandescent E26 base bulbs.
- **Dimming:** If using dimmable bulbs and a compatible dimmer switch, the light output can be adjusted.



Image: A split image showing the Darkaway Flush Mount Ceiling Light Fixture in both the off state (top) and on state (bottom), demonstrating the light output.

MAINTENANCE

- **Cleaning:** To clean the fixture, turn off the power and wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool before handling.
- **Inspection:** Periodically check all connections and mounting hardware for tightness.

TROUBLESHOOTING

Problem	Possible Cause	Solution
---------	----------------	----------

Light does not turn on.	◦ Power is off. ◦ Loose wiring connections. ◦ Faulty bulb. ◦ Faulty switch.	◦ Check circuit breaker/fuse. ◦ Verify all wiring connections are secure (power off). ◦ Replace bulb. ◦ Test or replace switch.
Light flickers.	◦ Loose bulb. ◦ Incompatible dimmer switch/bulb.	◦ Tighten bulb. ◦ Ensure dimmer and bulbs are compatible.
Glass shade is loose.	◦ Decorative nut not tightened.	◦ Tighten the decorative nut on the center pole.

WARRANTY AND SUPPORT

This Darkaway product comes with a 1-year manufacturer's warranty from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For warranty claims or technical support, please contact Darkaway customer service through the retailer where the product was purchased or visit the official Darkaway website.

Contact Information:

- Manufacturer: Darkaway
- For support, please refer to your purchase platform or the Darkaway official website.

