

## Capresso 570.02

# Capresso Infinity Plus Conical Burr Grinder

**MODEL: 570.02**

User Instruction Manual

## 1. Introduction

The Capresso Infinity Plus Conical Burr Grinder is designed to provide a precise and consistent grind for various brewing methods. Grinding fresh whole beans immediately before brewing is essential for achieving optimal coffee flavor and aroma. This manual provides detailed instructions for the safe and effective use, maintenance, and troubleshooting of your grinder.

The Infinity Plus model features commercial-grade, solid steel conical burrs and an innovative gear reduction motor to minimize friction and heat, preserving the coffee's delicate flavors. It offers 16 fineness settings, from extra fine for Turkish coffee to very coarse for percolators and cold brew.

## 2. Important Safeguards

- Read all instructions before operating the appliance.
- To protect against electrical hazards, do not immerse the power cord, plug, or the appliance body in water or other liquids.
- Close supervision is necessary when any appliance is used by or near children.
- Unplug from outlet when not in use, before assembling or disassembling parts, and before cleaning.
- Avoid contact with moving parts.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- Do not use outdoors.
- Do not let cord hang over edge of table or counter, or touch hot surfaces.
- Do not use the appliance for other than intended use.

### 3. Parts Identification

Familiarize yourself with the components of your Capresso Infinity Plus grinder:

1. Bean Hopper with Lid: Holds whole coffee beans.
2. Upper Conical Burr: Removable for cleaning.
3. Grind Selector Dial: Adjusts grind fineness (16 settings).
4. Timer Dial: Sets grinding duration.
5. Ground Coffee Container: Collects ground coffee.
6. Lower Conical Burr: Fixed component.
7. Main Unit Base: Houses the motor and controls.
8. Power Cord: Connects to electrical outlet.





Figure 1: Overview of the Capresso Infinity Plus Conical Burr Grinder in White.





Figure 2: Close-up view of the grind selector dial, showing various fineness settings.







Figure 3: Illustration of removing the upper conical burr for cleaning.

#### 4. Setup

1. **Unpack:** Carefully remove all components from the packaging.
2. **Clean:** Wash the bean hopper, bean hopper lid, and ground coffee container with mild soap and water. Ensure all parts are completely dry before assembly.
3. **Assemble:** Place the ground coffee container into its designated slot in the main unit. Ensure the upper conical burr is securely in place. Attach the bean hopper to the top of the unit and secure its lid.
4. **Placement:** Position the grinder on a clean, dry, and stable surface.
5. **Power:** Plug the power cord into a suitable electrical outlet (120 Volts).

## 5. Operating Instructions

---

1. **Fill Bean Hopper:** Open the bean hopper lid and pour whole coffee beans into the hopper. The hopper has an 11-ounce capacity. Replace the lid securely.
2. **Select Grind Fineness:** Rotate the grind selector dial to choose your desired fineness setting. Refer to the 'Grind Settings Guide' below for recommendations based on your brewing method.
3. **Set Grinding Time:** Rotate the timer dial to select the desired grinding duration. The grinder will automatically stop once the set time has elapsed.
4. **Start Grinding:** Press the power button to begin grinding. The grinder will operate until the timer runs out or until you press the power button again to stop it manually.
5. **Collect Ground Coffee:** Once grinding is complete, carefully remove the ground coffee container from the unit.
6. **Pulse Grinding:** For additional control, you can use the pulse grinding feature by repeatedly pressing and releasing the power button.

## 6. Grind Settings Guide

---

The Capresso Infinity Plus offers 16 grind settings. Use the table below as a general guide for various brewing methods:






Brewing Method					
					
	Espresso Machines	Drip Coffee	Pour Over	Percolators	French Press
Grind Size	Extra Fine to fine	Medium	Medium	Coarse	Coarse
Recommended Grinder Type	Conical Burr Disk Burr	Conical Burr Disk Burr Blade	Conical Burr Disk Burr	Conical Burr Disk Burr Blade	Conical Burr Disk Burr Blade

Figure 4: Recommended grind settings for various coffee brewing methods.

Brewing Method	Recommended Grind Setting
Turkish	Extra Fine
Espresso	Fine
Drip Coffee	Medium
Pour-Over Brewers	Medium
French Press	Coarse
Percolators	Coarse
Cold Brew	Coarse

## 7. Maintenance and Cleaning

Regular cleaning ensures optimal performance and extends the life of your grinder.

1. **Unplug:** Always unplug the grinder from the power outlet before cleaning.
2. **Remove Bean Hopper:** Remove the bean hopper and empty any remaining whole beans.
3. **Remove Upper Burr:** Twist and lift the upper conical burr out of the unit (refer to Figure 3).
4. **Clean Burrs:** Use a brush (not included) to clean both the upper and lower conical burrs. Remove any trapped coffee particles.
5. **Clean Ground Coffee Container:** Empty and wash the ground coffee container and its lid with warm, soapy water. Rinse thoroughly and dry completely.
6. **Clean Exterior:** Wipe the exterior of the grinder with a soft, damp cloth. Do not use abrasive

cleaners or immerse the main unit in water.

7. **Reassemble:** Once all parts are dry, reassemble the grinder by placing the upper burr back into position, followed by the bean hopper and its lid. Insert the clean ground coffee container.

The innovative gear reduction motor and anti-static design help minimize static cling of coffee grounds, making cleanup easier.

## 8. Troubleshooting

---

- **Grinder does not start:**
  - Ensure the power cord is securely plugged into a working outlet.
  - Check that the bean hopper and ground coffee container are correctly assembled and locked into place.
  - Verify the timer dial is set to a desired grinding duration.
- **Inconsistent grind:**
  - Ensure the burrs are clean and free of obstructions.
  - Adjust the grind selector dial to a different setting and test.
- **Grinder is clogged:**
  - Unplug the unit. Remove the bean hopper and upper burr. Carefully clear any blockages from the burrs and the grinding chamber using a brush.
- **Excessive static cling of grounds:**
  - The Infinity Plus features anti-static technology. If static persists, ensure the ground coffee container is completely dry before use.

## 9. Specifications

---




- **Brand:** Capresso
- **Model:** 570.02
- **Color:** White
- **Dimensions:** 5 x 7.75 x 11.25 inches
- **Item Weight:** 4 pounds
- **Voltage:** 120 Volts
- **Bean Container Capacity:** 11 ounces
- **Ground Coffee Container Capacity:** Up to 4 ounces
- **Grind Settings:** 16 (Extra Fine to Coarse)
- **Burr Type:** Commercial-grade solid steel conical burrs
- **Special Features:** Innovative gear reduction motor, safety lock, auto-off, removable upper burr, pulse grinding.



## 10. Warranty and Support

For warranty information, product registration, or technical support, please refer to the official Capresso website or contact their customer service department. Keep your purchase receipt as proof of purchase for any warranty claims.

### Related Documents - 570.02

 <p>infinity Plus Conical Burr Grinder</p> <p>Model #575 #570</p> <p>• Instructions • Warranty • Product Registration</p> <p>100W / 120V / 60 Hz</p>	<p><a href="#">Capresso Infinity Plus Conical Burr Grinder: User Manual &amp; Instructions</a></p> <p>Detailed instructions, safety guidelines, cleaning tips, and warranty information for the Capresso Infinity Plus Conical Burr Grinder (Models #570 and #575). Learn how to achieve the perfect grind for your coffee.</p>
 <p>Capresso infinity CONICAL Burr Grinder</p> <p>Model #565 #560</p> <p>• Instructions • Warranty • Product Registration</p> <p>100W / 120V / 60 Hz</p>	<p><a href="#">Capresso Infinity Conical Burr Grinder User Manual &amp; Instructions</a></p> <p>Comprehensive user manual and operating instructions for the Capresso Infinity Conical Burr Grinder (Models #560, #565), detailing safety precautions, setup, grinding settings, cleaning, and warranty information.</p>
 <p>Capresso grind SELECT Coffee Burr Grinder</p> <p>Model #597.04 1100W / 120V / 60 Hz</p> <p>• Operating Instructions • Warranty</p> <p>Read all instructions before operating the appliance.</p>	<p><a href="#">Capresso Grind Select Coffee Burr Grinder - Model 597.04 - Operating Instructions &amp; Warranty</a></p> <p>Comprehensive guide to the Capresso Grind Select Coffee Burr Grinder (Model 597.04), covering important safeguards, operating instructions, cleaning, troubleshooting, and warranty information.</p>




[Capresso Stainless Steel Burr Grinder \(Models 580 & 585\) - User Manual & Warranty](#)

User manual and warranty information for Capresso 580 and 585 Stainless Steel Burr Grinders, covering setup, operation, cleaning, and safety guidelines.



[Capresso Infinity Burr Grinder Limited Warranty](#)

Details the one-year limited warranty for the Capresso Infinity Burr Grinder (Models #560 and #565) in the United States, covering defects in materials and workmanship, and outlining exclusions and limitations.



[Capresso 559 Coffee Burr Grinder: Instructions, Settings, and Warranty Guide](#)

A comprehensive guide for the Capresso 559 Coffee Burr Grinder, covering important safety precautions, initial use, grinding instructions, fineness selector settings, cleaning procedures, and warranty information.