

SHALL SH112002AE

SHALL Pink Electric Staple Gun User Manual

Model: SH112002AE | Brand: SHALL

1. INTRODUCTION

This manual provides detailed instructions for the safe and effective use of your SHALL Pink Electric Staple Gun. This versatile 2-in-1 tool functions as both an upholstery stapler and a brad nailer, suitable for various crafting, DIY, and decoration projects.

Package Contents:

- 4V Pink Electric Staple Gun
- Staple Remover
- 2000 counts JT21 staples (1000 x 5/16", 1000 x 3/8")
- 500 counts 18 gauge brad nails (500 x 5/8")
- Fast Charger with Cable



Image: The SHALL Pink Electric Staple Gun shown with its complete set of accessories, including staples, brad nails, staple remover, and charger.

2. SAFETY INFORMATION

Important: Always read and understand all instructions before operating the tool. Failure to follow these safety guidelines may result in injury or damage to the tool.

General Safety Precautions:

- Keep hands and body parts clear of the firing area.
- Always wear appropriate personal protective equipment, such as safety glasses.
- Ensure the workpiece is stable and secure before operation.

- Do not point the tool at yourself or others.
- Turn off the power switch (position "0") when the tool is not in use, when loading/unloading fasteners, or when performing maintenance.
- Do not attempt to operate the tool while it is charging.

Safe Boot Mechanism:

The electric staple gun features a 3-step activation mechanism designed for user safety:

1. Turn on the power button.
2. Ensure the contact striker is pressed against the workpiece.
3. Press the trigger simultaneously.



Image: Visual representation of the LED power indicator and the three-step safety activation process for the staple gun.

3. SETUP

Charging the Battery:

The staple gun is equipped with a 2000 mAh lithium-ion battery. Before first use, or when the LED indicator shows red, charge the battery using the provided fast charger.

- Connect the charger cable to the charging port on the tool.
- Plug the charger into a standard electrical outlet.
- A full charge typically takes approximately 2 hours.
- Do not operate the tool while it is charging.

**Drives up to
1400+ SHOTS
on a full charge**

**2H Fast
Charger**

2000mAh

* Compatible with any phone or computer USB plug

Image: Illustration of the staple gun's 2000mAh battery capacity, capable of over 1400 shots per charge, and the included 2-hour fast charger.

Loading Staples/Nails:

This tool is compatible with JT21 staples (1/4" to 9/16") and 18 gauge brad nails (9/16" to 5/8").

1. Ensure the power switch is in the "0" (off) position.
2. Squeeze the magazine release and slide the magazine out from the bottom of the tool.
3. Place the staples or nails upside down into the left track of the magazine. Ensure they are seated correctly.
4. Slide the magazine back into the tool until it clicks securely into place.



Image: Step-by-step guide showing how to open the magazine and correctly insert staples or nails into the tool.

4. OPERATING INSTRUCTIONS

Powering On and Operation:

1. Ensure the battery is charged and fasteners are loaded.
2. Turn the power switch to the "I" (on) position.

3. Place the nose of the tool (contact striker) firmly against the workpiece where you wish to drive a fastener.
4. Press the trigger to fire the fastener.
5. Release the trigger and lift the tool from the workpiece.

LED Power Indicator:

- **Green Light:** Indicates normal operation or full charge. The LED will light up green once for each shot.
- **Red Light:** Indicates low power state or charging.

Fastener Compatibility:

The SHALL Electric Staple Gun is designed for two types of fasteners:

- **JT21 Staples:** Compatible with sizes from 1/4" (6mm) to 9/16" (14mm).
- **18 Gauge Brad Nails:** Compatible with sizes from 9/16" (14mm) to 5/8" (15mm).



Image: Diagram illustrating the compatible sizes and types of JT21 staples and 18GA brad nails for the tool.

5. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your staple gun.

- **Cleaning:** Periodically wipe down the tool with a clean, dry cloth. Do not use harsh chemicals or abrasive cleaners.
- **Storage:** Store the tool in a dry place, away from direct sunlight and extreme temperatures. Ensure the power switch is off before storing.
- **Fastener Management:** Always remove any remaining fasteners from the magazine before long-term storage.
- **Staple Remover:** Use the included staple remover to safely extract any misfired or bent fasteners from your workpiece.

6. TROUBLESHOOTING

If you encounter issues with your staple gun, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Tool does not fire.	Battery is low or depleted. Power switch is off. Contact striker not fully depressed. Magazine is empty or jammed.	Charge the battery. Turn the power switch to "I". Press the tool firmly against the workpiece. Check and reload fasteners; clear any jams.
Fasteners are bent or not fully driven.	Incorrect fastener size. Tool not pressed firmly against workpiece. Fasteners are low or jammed in magazine. Workpiece material is too hard.	Ensure correct fastener type and size. Apply more pressure to the tool. Reload magazine; clear any jams. The tool may not be suitable for extremely dense materials.
Tool jams frequently.	Incorrect fastener type/size. Magazine not properly loaded. Damaged fasteners.	Use only recommended JT21 staples or 18GA brad nails. Ensure fasteners are loaded correctly and magazine is secure. Discard bent or damaged fasteners.
Battery not charging.	Charger not properly connected. Faulty outlet. Battery issue.	Ensure charger is securely plugged into tool and outlet. Try a different outlet. Contact customer support if issue persists.

If the problem persists after attempting these solutions, please contact SHALL customer support.

7. SPECIFICATIONS

Feature	Detail
Model Number	SH112002AE
Brand	SHALL
Item Weight	1.7 pounds
Product Dimensions	7.87 x 6.69 x 0.04 inches
Battery Type	1 Lithium Ion battery (required)
Color	Pink
Material Type	Wood (for application)
Number of Fasteners (Included)	2500 (JT21 staples & 18 gauge brad nails)
Staple Compatibility	JT21 staples (1/4" to 9/16")
Nail Compatibility	18 gauge brad nails (9/16" to 5/8")
First Available Date	July 5, 2022

8. APPLICATIONS

The SHALL Pink Electric Staple Gun is designed for a wide range of fastening applications, making it ideal for both hobbyists and professionals. Its lightweight and ergonomic design ensures comfortable use for extended periods.

Common Uses Include:

- Upholstery projects
- Material repair
- Decoration tasks
- Carpentry work
- Furniture DIY
- Crafts
- Insulation fastening
- Working with cork, cloth, and leather



Image: Collage showing the electric staple gun being used for crafts, general repairs, upholstery, and decorating.

9. WARRANTY & SUPPORT

For any questions, technical assistance, or warranty inquiries regarding your SHALL Pink Electric Staple Gun, please contact SHALL customer support. You can find more information and contact details on the official SHALL brand store.

Visit the [SHALL Store](#) for additional products and support resources.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question