**Saved from manuals.plus.**
**Open the live page for links to other documents and user manuals.**



**Aipsun 8461**

# Aipsun Model 8461 23-inch Black 3-Light Crystal Vanity Light

Instruction Manual

## 1. Introduction

Thank you for purchasing the Aipsun Model 8461 23-inch Black 3-Light Crystal Vanity Light. This manual provides essential information for the safe installation, operation, and maintenance of your new lighting fixture. Please read these instructions thoroughly before beginning installation and retain them for future reference.



*Figure 1: Front view of the Aipsun 23-inch Black 3-Light Crystal Vanity Light.*

## 2. Safety Information

**WARNING:** To avoid electric shock, always turn off the power at the main circuit breaker or fuse box before beginning installation or performing any maintenance. Ensure all electrical connections are made in accordance with local codes, ordinances, and the National Electric Code (NEC).

- Consult a qualified electrician if you are unsure about the installation process.
- Wear safety glasses and gloves during installation.
- Handle crystal components with care to prevent breakage.

- Do not exceed the maximum wattage specified for the bulbs.
- This fixture is designed for indoor use only and is not water resistant.

## 3. Package Contents

Verify that all components are present before discarding packaging materials.

- Vanity Light Fixture (Model 8461)
- Mounting Hardware (screws, wire nuts, mounting plate)
- Instruction Manual

**Note:** Bulbs are not included and must be purchased separately.

## 4. Specifications

| Feature | Detail |
|---|---|
| Brand | Aipsun |
| Model Number | 8461 |
| Color | Black |
| Dimensions (L x W x Extension) | 23.6 inch x 7.2 inch x 7.3 inch |
| Backplate Dimensions (L x W) | 23.6 inch x 4.3 inch |
| Material | Iron, Aluminum, Crystal |
| Finish Type | Powder Coated |
| Bulb Base | E26 |
| Number of Light Sources | 3 |
| Max Wattage (per bulb) | 60W (Total 180W) |
| Voltage | 110 Volts (AC) |
| Dimmable | Yes (with dimmable bulbs and dimmer switch, not included) |
| Installation Type | Wall-mounted |
| Water Resistance Level | Not Water Resistant |
| Item Weight | 8.8 Pounds |




*Figure 2: Product dimensions for planning installation.*

## 5. Installation

**Required Tools (not included):** Screwdriver, wire strippers, electrical tape, ladder, level.

1. **Turn Off Power:** Before starting, ensure the power to the circuit is turned off at the circuit breaker or fuse box.
2. **Mounting Plate Installation:** Attach the mounting plate to the junction box using the provided screws. Ensure the plate is level.
3. **Wiring:** Connect the fixture wires to the house wires. Connect the bare copper ground wire from the fixture to the ground wire from the junction box (usually bare copper or green). Connect the white wire from the fixture to the white (neutral) wire from the junction box. Connect the black wire from the fixture to the black (hot) wire from the junction box. Secure connections with wire nuts and electrical tape.
4. **Fixture Attachment:** Carefully align the fixture with the mounting plate and secure it using the provided screws.
5. **Install Bulbs:** Screw E26 base bulbs (not included) into the sockets. Ensure bulb length is less than 4.7 inches.
6. **Crystal Shade Installation:** The crystal lampshades are designed to be easily attached. Carefully slide them into place or secure them as per the design.
7. **Restore Power:** Once installation is complete, turn the power back on at the circuit breaker.

*Figure 3: Example of the vanity light installed in a bathroom setting.*

*Video 1: Official product video showcasing the Aipsun Crystal Modern Bathroom Vanity Light Fixtures, highlighting design and features.*

## 6. Operating Instructions

This vanity light fixture operates via a standard wall switch (not included). To utilize dimming functionality, ensure you have installed dimmable E26 bulbs and a compatible dimmer switch.



*Figure 4: The fixture supports E26 bulbs and is dimmable with compatible components.*




*Figure 5: The fixture can be installed for either uplight or downlight orientation.*

## 7. Maintenance

- **Cleaning:** To clean the fixture, turn off the power and wipe with a soft, dry cloth. Do not use abrasive cleaners or

solvents as they may damage the finish or crystal. The crystal lampshades can be removed for thorough cleaning.

- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool completely before touching. Replace with E26 base bulbs of the same type and wattage (max 60W per bulb).




*Figure 6: Close-up of the crystal shade, which can be removed for cleaning.*

## 8. Troubleshooting

| Problem | Possible Cause | Solution |
|---|---|---|
| Light does not turn on | 1. Power is off<br>2. Loose wiring connection<br>3. Faulty bulb | 1. Check circuit breaker/fuse<br>2. Verify all wire connections are secure<br>3. Replace bulb(s) |

| | | |
|---|---|---|
| Light flickers | 1. Loose bulb<br>2. Incorrect bulb type for dimmer<br>3. Loose wiring | 1. Tighten bulb(s)<br>2. Ensure dimmable bulbs are used with dimmer<br>3. Check wiring connections |
| Dimmable function not working | 1. Non-dimmable bulbs<br>2. Non-dimmable switch | 1. Install dimmable E26 bulbs<br>2. Install a compatible dimmer switch |

## 9. Warranty and Support

Aipsun is committed to providing high-quality products. If you encounter any issues with your Aipsun Crystal Vanity Light, please contact our customer support team through the retailer where the product was purchased. We aim to resolve any concerns within 24 hours.

© 2026 Aipsun. All rights reserved.


### Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

**Name**

Anonymous

**Email**

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

**Question**

Example: How do I reset this device or fix this error?

**Details**

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

**Open the live page**

**https://manuals.plus/asin/B0B73ZW1ZV**

More documents and user manuals: **https://manuals.plus/**