

WAYXIN R9

WAYXIN R9 Motorcycle Bluetooth Headset Instruction Manual

Model: R9 | Brand: WAYXIN

1. INTRODUCTION

Thank you for choosing the WAYXIN R9 Motorcycle Bluetooth Headset. This device is designed to enhance your riding experience by providing seamless communication, entertainment, and navigation capabilities. Featuring advanced Bluetooth 5.0 technology, noise reduction, and a robust waterproof design, the R9 ensures clear audio and reliable performance in various conditions. Please read this manual thoroughly to understand the product's features and ensure proper usage and maintenance.



Overview of WAYXIN R9 features including Bluetooth 5.0, universal pairing, FM radio, 6-person intercom, waterproof design, and voice assistant.

2. WHAT'S IN THE BOX

The WAYXIN R9 package includes the following components:

- 1 × R9 Host Unit
- 1 × Speaker Set
- 1 × Hardcore Microphone
- 1 × Button Microphone
- 1 × Charging Cable
- 1 × Metal Sheet
- 2 × Mounting Screws
- 1 × Allen Wrench
- 1 × User Manual (this document)



The R9 headset unit shown with both the hardcore (boom) and button (soft wire) microphones.

WAYXIN R9 1 Pack List



1* R9 hosts

1* Hardcore and
button microphone

1* Speakers

1* Allen key

1* Metal sheets

1* User manual

2x mounting screws



Speakers and
Installation tools

Mounted

Mounted on the
edge of the

Tighten the screws
to secure the

mounting
downwards

Completely

Visual representation of all included accessories and a simplified installation guide.

3. SETUP AND INSTALLATION

3.1 Choosing Your Microphone

The WAYXIN R9 comes with two types of microphones to suit different helmet styles:

- **Hardcore (Boom) Microphone:** Ideal for open-face or modular helmets where the microphone needs to extend closer to your mouth.
- **Button (Soft Wire) Microphone:** Suitable for full-face helmets where the microphone can be discreetly placed inside the helmet near the mouth area.

Select the microphone that best fits your helmet type and attach it to the R9 host unit.

2 Microphones

Fits your half and full helmet



The two microphone options are designed to fit both half and full-face helmets.

3.2 Mounting the R9 Unit

The R9 unit can be mounted using either Velcro or the metal splint method:

- **Velcro Method:** Attach the adhesive Velcro pad to the side of your helmet and the corresponding Velcro on the R9 unit. Press firmly to secure.
- **Metal Splint Method:** Slide the metal splint between the helmet shell and the inner padding. Secure the R9 unit to the splint using the provided screws and Allen wrench. Ensure it is firmly attached to prevent movement during riding.

Position the unit on the side of your helmet where it is easily accessible for controls but does not obstruct your vision or movement.

4. OPERATING INSTRUCTIONS

4.1 Power On/Off

- **Power On:** Press and hold the Power button (usually the central large button) until the indicator light illuminates and you hear a voice prompt.
- **Power Off:** Press and hold the Power button again until the indicator light turns off and you hear a voice prompt.

4.2 Intercom Pairing (Up to 6 Riders)

The R9 supports intercom communication for up to 6 riders within a 1500m range.

1. Ensure both R9 units are powered off.
2. Press and hold the Power button on both units simultaneously until they power on and enter pairing mode (indicated by flashing lights).
3. Once paired, the lights will change, and you will hear a confirmation.
4. To initiate intercom mode, press the 'B' button on either unit. The units will connect, allowing for two-way communication.
5. To add more riders (up to 6), repeat the pairing process with additional R9 units.

This video demonstrates the pairing process for two R9 intercom units and then pairing one unit with a mobile phone for music playback and FM radio functionality.



Reach 1500m Range

1500M

6 people at the same time
intercom distance up to 1500m

The R9 headset supports communication for up to 6 riders with a range of up to 1500 meters.



The R9 allows up to 6 riders to communicate simultaneously, with impressive battery life for calls, music, and FM radio.

4.3 Phone Pairing

To connect your R9 headset to your mobile phone:

1. Ensure the R9 unit is powered on and in pairing mode (flashing blue/red light). If not, press and hold the Power button until it enters pairing mode.
2. On your mobile phone, go to Bluetooth settings and search for available devices.
3. Select "WAYXIN R9" from the list of devices.
4. Accept any pairing requests on your phone. A voice prompt will confirm successful connection.

Bluetooth 5.0



Low Battery

Alert to Keep You in Control

Supports Connecting 2 Bluetooth Devices



The R9 features Bluetooth 5.0 and can connect to two Bluetooth devices simultaneously, such as a phone and a GPS.

Universal Pairing

Schließen Sie Intercom anderer Hersteller an



The R9 offers universal pairing, allowing connection with most motorcycle Bluetooth intercoms on the market.

4.4 Music Playback & FM Radio

- **Music Playback:** Once paired with your phone, you can play music directly through the R9 headset. Use your phone's media controls or the R9's control buttons (e.g., volume up/down, next/previous track) if supported.
- **FM Radio:** To activate the FM radio, press the 'A' button. The headset will scan for available stations. Use the volume buttons to adjust the station or volume.



The R9 features a full-band FM radio, covering frequencies from 76Mhz to 108Mhz.

4.5 Voice Assistant & Calls

- The R9 supports voice assistant activation (e.g.,