

Mpayel B7810

Mpayel Flush Mount Ceiling Fan with Lights and Remote Control User Manual

Model: B7810

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Mpayel Flush Mount Ceiling Fan with Lights and Remote Control. Please read this manual thoroughly before installation and keep it for future reference.

The Mpayel Low Profile Bladeless Ceiling Fan features a 110V 100% Pure Copper motor for quiet operation (35 dB). It includes stepless dimming LED lighting and a remote control with timing functions for convenience and energy saving. Its modern, enclosed design is suitable for various indoor spaces such as bedrooms, dining rooms, porches, offices, and cafes.

IMPORTANT SAFETY INFORMATION

- Always turn off the power at the circuit breaker before beginning installation or maintenance.
- Ensure all electrical connections comply with local codes and ordinances. If you are unsure, consult a qualified electrician.
- Mount the fan securely to a ceiling joist or a suitable support structure capable of holding the fan's weight.
- Do not bend the fan blades during installation or cleaning.
- Keep children away from the fan during operation.
- This product is designed for indoor use only and is not water resistant.

PACKAGE CONTENTS

Before installation, ensure all components are present and undamaged. Refer to the included English manual for a complete list.

- Flush Mount Ceiling Fan with Light
- Remote Control
- Installation Hardware (screws, wire nuts, mounting bracket)
- User Manual

Your browser does not support the video tag.

Video: 2023 Low Profile Ceiling Fan Installation Video. This video provides a visual guide for the installation process, including unboxing and mounting the bracket.

SETUP AND INSTALLATION

The components of the flush mount ceiling light with fan have been pre-assembled for quick installation. Follow these steps carefully.

Step 1: Prepare for Installation

- Turn off power at the circuit breaker.
- Remove any existing light fixture.
- Ensure the ceiling junction box is securely mounted and capable of supporting the fan.

Step 2: Install the Mounting Bracket

Attach the mounting bracket to the ceiling junction box using the provided screws. Ensure it is firmly secured.



Image: Close-up of the Mpayel Flush Mount Ceiling Fan, showing its compact design and integrated light ring. This image helps visualize the product during installation.

Step 3: Wiring the Fan

Connect the fan's wires to the household electrical wires according to the color codes (typically black to black, white

to white, and green/yellow to ground). Use wire nuts to secure connections and electrical tape for added safety.

Step 4: Secure the Fan to the Mounting Bracket

Carefully lift the fan assembly and attach it to the installed mounting bracket. Secure it with the screws provided, ensuring all wires are tucked safely inside the junction box.

Step 5: Final Checks

- Verify all connections are secure.
- Ensure the fan is stable and does not wobble.
- Restore power at the circuit breaker.

OPERATING INSTRUCTIONS

Your Mpayel ceiling fan is controlled by the included remote control. The fan and light can operate independently.

Remote Control Functions



Image: The remote control for the Mpayel Flush Mount Ceiling Fan, showing buttons for fan speed, light dimming, and timer settings.

- **ON/OFF Button:** Turns the fan and light on or off.
- **Fan Speed Control:** Adjusts the fan speed (Low, Medium, High).
- **Light ON/OFF:** Turns the light on or off independently.
- **Stepless Dimming:** Adjusts the brightness of the light.
- **Color Temperature Adjustment:** Cycles through different light color temperatures (Warm White, Natural Light, Cool White).
- **Timer Function:** Sets the fan to turn off automatically after 1 or 2 hours.

Your browser does not support the video tag.

Video: Flush Mount Ceiling Fans with Lights. This video demonstrates the remote control functions, including light color and brightness adjustments, and fan speed settings.

Light Memory Function

The fan's light features a memory function that remembers your last light setting (brightness and color temperature). When you turn it on again, it will resume the previously selected setting.

MAINTENANCE

- **Cleaning:** To clean the fan, wipe it with a soft, damp cloth. Do not use abrasive cleaners or solvents. Ensure the power is off before cleaning.
- **Blade Care:** The enclosed design protects the blades. If cleaning is necessary, ensure the fan is completely off and stationary.
- **Light Source:** The integrated LED light source is designed for long life and does not require bulb replacement.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Fan does not operate.	No power supply; loose wiring; remote control battery low.	Check circuit breaker; ensure all wires are securely connected; replace remote control batteries.
Light does not turn on.	No power supply; loose wiring; LED failure (rare).	Check circuit breaker; ensure all wires are securely connected; contact customer service if LED is faulty.
Fan makes excessive noise.	Loose mounting screws; internal motor issue.	Ensure mounting screws are tightened; contact customer service if noise persists.
Remote control not working.	Low battery; obstruction; remote not paired.	Replace batteries; ensure clear line of sight to fan; refer to remote pairing instructions in the full manual.

SPECIFICATIONS

Feature	Detail
Brand	Mpayel
Model Number	B7810
Color	Black
Size	15 inches

Feature	Detail
Material	Copper (motor), Crystal (shade)
Power Source	Corded Electric
Voltage	240 Volts (AC)
Light Source	LED
Brightness	> 800 lumens
Control Method	Remote Control
Special Features	Dimmable, Energy Efficient, Timer
Indoor/Outdoor Usage	Indoor
Item Weight	6.05 Pounds

For more energy efficiency information, please visit the EU EPREL database: <https://eprel.ec.europa.eu/qr/1420550>

WARRANTY AND SUPPORT

Mpayel offers a free replacement service for damaged parts. Our professional customer service team is available to assist you with product installation or quality issues.

If you have any questions or require assistance, please feel free to contact us. We aim to provide a satisfactory answer within 24 hours.