PAWPRO PP6-A

PAWPRO Dog Training Collar User Manual

Model: PP6-A

Introduction

Thank you for choosing the PAWPRO Dog Training Collar. This professional training system is designed to help you establish effective communication with your dog, promoting positive behavior and a harmonious relationship. Featuring three safe and effective training modes (Beep, Vibration, and Static), this waterproof and rechargeable collar is suitable for various dog breeds and sizes. Please read this manual thoroughly before use to ensure proper operation and the safety of your pet.



Image: The PAWPRO Dog Training Collar system, including the remote control, receiver collar, and product packaging.

Safety Information and Important Warnings

- This training collar is intended for dogs weighing over 3 kg (6 lbs) and puppies older than 4 months.
- Do not use this product on aggressive, sick, or injured dogs. Consult a veterinarian or professional trainer if you have concerns about your dog's health or temperament.
- Avoid leaving the collar on your dog for more than 12 hours per day to prevent skin irritation.
- Regularly check your dog's neck for any signs of irritation or sores. If irritation occurs, discontinue use until the skin heals.
- The static correction mode should be used responsibly and only when necessary, at the lowest effective level. It is an optional feature and can be disabled.
- Keep the device out of reach of children.

- Ensure the collar is properly fitted; it should be snug but not overly tight, allowing two fingers to fit comfortably under the strap.

Package Contents

The PAWPRO Dog Training Collar package includes the following items:

- 1 x Remote Transmitter
- 1 x Receiver Collar with adjustable strap
- 1 x USB-C Charging Cable
- 1 x Clicker/Whistle
- 1 x Remote Lanyard
- 2 x Sets of Contact Points (short and long)
- 2 x Silicone Conductive Caps for contact points
- 1 x Test Light Tool
- 1 x User Manual (in French, but this document serves as an English guide)



Image: Visual representation of the PAWPRO Dog Training Collar components, including the remote, collar, clicker, and whistle.

Product Overview

Remote Transmitter

- **LCD Display:** Shows battery level, mode, and static level.
- **Mode Button:** Cycles through Beep, Vibration, and Static modes.
- **Up/Down Buttons:** Adjust static correction levels (1-16).
- **Activation Button:** Delivers the selected correction.
- **Channel Button:** Switches between dog 1 and dog 2 (if using two collars).
- **Charging Port:** USB-C port for recharging.

Receiver Collar

- **Contact Points:** Deliver static correction. Can be covered with silicone caps for vibration/beep only.
- **Power Button:** Turns the receiver on/off.
- **Charging Port:** USB-C port for recharging.
- **LED Indicator Light:** Shows power status, charging status, and mode activation.
- **Adjustable Strap:** Fits various neck sizes.



Image: Detailed view of the remote control and receiver collar, highlighting the three training modes: Beep, Shock (Static), and Vibration, along with the built-in safety lock feature.

Setup

1. Charging the Devices

Before first use, fully charge both the remote transmitter and the receiver collar. Connect the USB-C charging cable to the charging ports on both devices and plug it into a standard USB power adapter (not included). The LED indicator on the receiver will turn solid red during charging and turn green when fully charged. The remote's display will show a charging icon. A full charge takes approximately 2 hours.



Image: Illustration showing the USB-C charging connection for both the remote and the receiver collar.

2. Attaching Contact Points (Optional for Static Mode)

If you intend to use the static correction mode, screw the appropriate length of contact points onto the receiver. Use shorter points for dogs with short coats and longer points for dogs with thicker coats. For vibration or beep-only training, you can attach the silicone conductive caps over the contact points or remove the contact points entirely to prevent accidental static correction.



Image: Diagram illustrating the contact points and optional silicone caps for double protection and comfort.

3. Pairing the Remote and Receiver

The devices are usually pre-paired from the factory. If pairing is needed:

1. Turn on the receiver collar by pressing and holding its power button until the LED flashes.
2. Press and hold the power button on the receiver collar again for 3 seconds until the LED flashes rapidly.
3. Within 10 seconds, press the Activation Button on the remote transmitter.
4. The receiver's LED will stop flashing rapidly, indicating successful pairing.

4. Fitting the Collar

Proper fit is crucial for effective and safe operation. The collar should be placed high on your dog's neck, just below the ears. The contact points must have direct contact with your dog's skin. You should be able to fit two fingers snugly between the collar strap and your dog's neck. A loose fit will reduce the effectiveness of the static correction and may cause skin irritation due to rubbing.



Image: Visual guide showing the PAWPRO collar's adjustability and suitability for dogs ranging from 6 lbs to 130 lbs, illustrating various dog breeds.

Operating Instructions

Training Modes

The PAWPRO training collar offers three distinct training modes:

- **Beep Mode:** Delivers an audible tone. Ideal for initial training and gaining your dog's attention.
- **Vibration Mode:** Provides a gentle vibration. Useful for reinforcing commands or as a warning before static correction.
- **Static Correction Mode:** Delivers a mild static pulse. This mode has 16 adjustable levels. Start at the lowest level and increase only if necessary to find the minimum effective level for your dog. This mode is optional and can be avoided if other modes are sufficient.



Image: Illustrates the benefits of using the PAWPRO collar, such as reducing excessive barking, pulling on leash, jumping up, and aggressive behavior, leading to improved safety and more enjoyable walks. Highlights IPX7 waterproofing.

Using the Remote Control

1. **Turn On/Off:** Press and hold the power button on both the remote and receiver to turn them on or off.
2. **Select Mode:** Press the Mode button on the remote to cycle through Beep, Vibration, and Static modes. The selected mode will be displayed on the LCD screen.
3. **Adjust Static Level:** If in Static mode, use the Up/Down buttons to adjust the intensity level from 1 to 16.
4. **Deliver Correction:** Press the Activation Button to deliver the selected correction.
5. **Switch Channels (for multiple dogs):** If you have a second PAWPRO collar, use the Channel button to switch between controlling Dog 1 and Dog 2.

Training Tips

- Always start with positive reinforcement and basic obedience commands before introducing the collar.
- Introduce the collar gradually. Let your dog wear it for short periods without activation so they associate it with normal wear, not punishment.

- Use the collar to interrupt unwanted behaviors, not to punish. The timing of the correction is critical.
- Always pair a correction with a verbal command. For example, if your dog barks excessively, say "Quiet" and then activate the beep or vibration.
- Keep training sessions short, positive, and consistent.
- The included clicker/whistle can be used for positive reinforcement training, marking desired behaviors.



Image: Close-up of the included 2-in-1 clicker and whistle, demonstrating its use for daily dog training.

Range and Waterproofing

The PAWPRO training collar offers a remote control range of up to 500 meters (approximately 1640 feet), allowing for effective training in various environments. The receiver collar is IPX7 waterproof, meaning it can withstand immersion in water up to 1 meter for 30 minutes. This makes it suitable for dogs who enjoy swimming or training in wet conditions. However, it is recommended to remove the collar before prolonged water activities to ensure longevity.



Image: Illustration depicting a dog running with the collar and the remote control, emphasizing the 500-meter range.



Image: Visual representation of the receiver collar being splashed with water, indicating its IPX7 waterproof rating.

Maintenance

- **Cleaning:** Regularly clean the receiver collar and contact points with a damp cloth. Ensure no dirt or debris

accumulates around the contact points, as this can affect performance and cause skin irritation.

- **Battery Care:** To prolong battery life, avoid fully discharging the devices frequently. Recharge them when the battery indicator is low. If storing for an extended period, charge them to about 50% every few months.
- **Storage:** Store the collar and remote in a cool, dry place away from extreme temperatures and direct sunlight.



Image: Highlights the exceptional battery life of the PAWPRO system, with 200 days for the remote and 15 days for the collar on a full 2-hour recharge.

Troubleshooting

Problem	Possible Cause	Solution

Problem	Possible Cause	Solution
Collar not working/no response	Low battery; Not paired; Collar off; Out of range.	Charge devices; Re-pair remote and receiver; Turn on collar; Move closer to dog.
Static correction not working	Poor contact with skin; Static level too low; Contact points too short; Silicone caps on.	Adjust collar fit; Increase static level gradually; Use longer contact points; Remove silicone caps.
Dog shows skin irritation	Collar worn too long; Collar too tight/loose; Allergic reaction; Dirty contact points.	Limit wear time; Adjust fit; Consult vet; Clean contact points.
Remote display is blank	Low battery; Remote off.	Charge remote; Turn on remote.

Specifications

Feature	Detail
Model Number	PP6-A
Recommended for Species	All dog breeds
Minimum Dog Weight	3 kg (6 lbs)
Minimum Dog Age	4 months
Training Modes	Beep, Vibration, Static (16 levels)
Remote Range	Up to 500 meters (1640 feet)
Waterproof Rating	IPX7 (Receiver Collar)
Battery Life (Collar)	Up to 15 days (typical use)
Battery Life (Remote)	Up to 200 days (standby)
Charging Time	Approximately 2 hours
Charging Port	USB-C
Included Accessories	Clicker/Whistle, Lanyard, USB-C Cable

Warranty and Support

The PAWPRO Dog Training Collar comes with a 2-year warranty, ensuring quality and reliability. For any questions, technical support, or warranty claims, please contact PAWPRO customer service. Our team is dedicated to providing

assistance and ensuring your satisfaction.
PAWPRO is a French company committed to providing high-quality pet training solutions. We prioritize the comfort and safety of your animal.



Image: Two dogs wearing PAWPRO collars in a natural setting, representing the brand's commitment to pet comfort and safety.

© 2023 PAWPRO. All rights reserved.

For more information, visit our product page.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question