

i Cafilas MINI Q MA2205

# i Cafilas MINI Q 2 IN 1 Coffee Machine User Manual

Model: MINI Q MA2205

|          |       |           |             |                     |                |                    |  |
|----------|-------|-----------|-------------|---------------------|----------------|--------------------|--|
|          |       |           |             | Safety Instructions | Product        |                    |  |
| Overview | Setup | Operation | Maintenance | Troubleshooting     | Specifications | Warranty & Support |  |

## 1. IMPORTANT SAFETY INSTRUCTIONS

Please read all instructions carefully before using the i Cafilas MINI Q 2 IN 1 Coffee Machine. Retain this manual for future reference.

- Do not immerse the appliance, power cord, or plug in water or other liquids.
- Ensure the power supply voltage matches the rating label on the appliance.
- Unplug the coffee machine from the outlet when not in use and before cleaning.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- Keep the appliance out of reach of children.
- Use only cold, fresh water in the water reservoir.
- Do not open the brewing chamber during the brewing cycle. Hot water may spray out.
- Place the coffee machine on a stable, level surface away from hot surfaces.

## 2. PRODUCT OVERVIEW

The i Cafilas MINI Q 2 IN 1 Coffee Machine is designed for quick and convenient brewing of single-serve coffee using either K-cup capsules or ground coffee. Its compact design makes it suitable for various spaces.

### Components:

- Main Unit
- Removable Water Reservoir (8oz / 240ml capacity)
- K-cup Capsule Holder
- Ground Coffee Filter Basket

- Power Cord
- Coffee Scoop (for ground coffee)

Key Features:

- **Fast Brewing:** Brews coffee in approximately 2 minutes.
- **Dual Compatibility:** Supports both K-cup capsules and ground coffee.
- **Compact Design:** Dimensions of 5.01"D x 10.2"W x 9.5"H, ideal for small spaces.
- **Intelligent Temperature Control:** Maintains 85°C for optimal extraction.
- **Auto Shut-off:** Automatically turns off after brewing for safety.
- **Fresh Water System:** Uses fresh water for each brew, no large water tank.

PRODUCT DESCRIPTION



Product Name:  
**Mini Q Coffee Maker**

Style:  
**Semi-automatic**

Product Weight:  
**1400g**

Material:  
**ABS/304/PA/PP/Silicone**

Voltage Electric Current:  
**110-120V**

Rate of Power:  
**1400W**

Image: i Cafilas MINI Q Coffee Machine showing its dimensions and key specifications.

## 3. SETUP

---

### 3.1 Unpacking and Initial Cleaning

1. Carefully remove all packaging materials and inspect the coffee machine for any damage.
2. Wipe the exterior of the machine with a damp cloth.
3. Wash the removable water reservoir, K-cup capsule holder, and ground coffee filter basket with warm, soapy water. Rinse thoroughly and dry.

### 3.2 First Use (Water Cycle)

Before brewing coffee for the first time, run a water-only cycle to clean the internal components.

1. Place an empty mug on the drip tray.
2. Open the water reservoir lid and fill the reservoir with fresh, cold water up to the MAX line (240ml).
3. Close the water reservoir lid securely.
4. Ensure no capsule or ground coffee is in the brewing chamber.
5. Press the power button to start the water cycle. The machine will heat the water and dispense it into the mug.
6. Once the cycle is complete, discard the hot water. The machine is now ready for use.

# MAKE COFFEE WITH FRESH WATER EVERY DAY

8oz (240ml) Removable water tank



Image: Filling the removable water tank with fresh water. The tank is designed for easy filling and cleaning.

## 4. OPERATING INSTRUCTIONS

---

### 4.1 Brewing with K-cup Capsules

1. Lift the top cover of the brewing chamber.
2. Insert a K-cup capsule into the capsule holder, ensuring it is seated correctly.
3. Close the top cover firmly until it clicks into place.
4. Fill the water reservoir with fresh, cold water (4-8oz / 120-240ml) according to your desired cup size.
5. Place your mug on the drip tray.
6. Press the power button to start brewing. The machine will heat the water and dispense coffee.
7. The machine will automatically turn off after brewing.

## 4.2 Brewing with Ground Coffee

1. Lift the top cover of the brewing chamber.
2. Place the ground coffee filter basket into the brewing chamber.
3. Use the provided scoop to add your desired amount of ground coffee (typically 1-2 scoops) into the filter basket. Do not overfill.
4. Close the top cover firmly until it clicks into place.
5. Fill the water reservoir with fresh, cold water (4-8oz / 120-240ml) according to your desired cup size.
6. Place your mug on the drip tray.
7. Press the power button to start brewing. The machine will heat the water and dispense coffee.
8. The machine will automatically turn off after brewing.

## TWO WAY TO BREW

### Ground Coffee



### K-Pod Capsule



Image: The coffee machine supports brewing with both ground coffee and K-pod capsules.

# SIMPLE TO USE



Image: Simple steps for operating the coffee machine: insert coffee, close lid, add water, press button.

# ONE TOUCH BREWING

Constant Temperature Extraction At 85°C



Image: The machine features one-touch brewing with constant temperature extraction at 85°C.

## 4.3 Official Product Videos

Video: Overview of the iCafilas MINI Q coffee maker, demonstrating its features and ease of use.

Video: Demonstrates how to use the Single Serve Coffee Maker for both K-Cup and ground coffee.

Video: Shows the rapid brewing capability of the single serve coffee maker, making coffee in 1-2 minutes.

## 5. MAINTENANCE AND CLEANING

Regular cleaning ensures optimal performance and extends the lifespan of your coffee machine.

### 5.1 Daily Cleaning

1. After each use, unplug the machine and allow it to cool down.
2. Remove and empty the K-cup capsule holder or ground coffee filter basket. Wash with warm, soapy water and rinse.
3. Empty any remaining water from the removable water reservoir. Wash and rinse.
4. Wipe the drip tray and the area around the brewing chamber with a damp cloth.

## **5.2 Descaling (Monthly or as needed)**

Mineral deposits can build up over time, affecting performance. Descale your machine monthly or if you notice slower brewing or reduced coffee temperature.

1. Fill the water reservoir with a mixture of 1 part white vinegar and 2 parts water.
2. Place a large empty mug on the drip tray.
3. Run a brewing cycle without any coffee.
4. Repeat the cycle with the vinegar solution until the reservoir is empty.
5. Rinse the reservoir thoroughly and run 2-3 cycles with fresh, clean water to remove any vinegar residue.

# MAKE COFFEE WITH FRESH WATER EVERY DAY

8oz (240ml) Removable water tank



Image: The removable water reservoir facilitates easy filling and thorough cleaning.

## 6. TROUBLESHOOTING

If you encounter issues with your coffee machine, refer to the following common problems and solutions:

| Problem                   | Possible Cause                       | Solution                                                         |
|---------------------------|--------------------------------------|------------------------------------------------------------------|
| Machine does not turn on. | No power supply.                     | Ensure the power cord is securely plugged into a working outlet. |
| Coffee is not brewing.    | Insufficient water in reservoir.     | Fill the water reservoir to the desired level.                   |
|                           | Brewing chamber not closed properly. | Ensure the top cover is firmly closed and clicked into place.    |

| Problem                       | Possible Cause                           | Solution                                                           |
|-------------------------------|------------------------------------------|--------------------------------------------------------------------|
| Coffee tastes weak or watery. | Too much water for the amount of coffee. | Use less water or more coffee (ground coffee) / a stronger K-cup.  |
|                               | Machine needs descaling.                 | Perform a descaling cycle as described in the Maintenance section. |
| Water leaks from the machine. | Water reservoir not seated correctly.    | Remove and re-seat the water reservoir firmly.                     |
|                               | Brewing chamber not closed properly.     | Ensure the top cover is firmly closed.                             |

If the problem persists after trying these solutions, please contact customer support.

## 7. PRODUCT SPECIFICATIONS

| Feature            | Detail                                                                 |
|--------------------|------------------------------------------------------------------------|
| Model Name         | MINI Q MA2205                                                          |
| Brand              | i Cafilas                                                              |
| Color              | Dark Grey                                                              |
| Product Dimensions | 5.01"D x 10.2"W x 9.5"H                                                |
| Item Weight        | 3.1 pounds                                                             |
| Power Source       | AC adapter                                                             |
| Voltage            | 110-120 Volts                                                          |
| Rate of Power      | 1400 Watts                                                             |
| Capacity           | 240 Milliliters (8 oz)                                                 |
| Coffee Input Type  | K-cup capsules & Ground Coffee                                         |
| Operation Mode     | Semi-Automatic                                                         |
| Special Feature    | Compact, Supports capsule and ground coffee, Single-Serve Coffee Maker |
| Is Dishwasher Safe | No                                                                     |

## 8. WARRANTY AND SUPPORT

The i Cafilas MINI Q 2 IN 1 Coffee Machine comes with a standard manufacturer's warranty. For specific warranty details, please refer to the documentation included with your purchase or contact i Cafilas customer support.

### Customer Support:

For technical assistance, troubleshooting, or warranty claims, please visit the official i Cafilas website or contact their customer service department. Contact information can typically be found on the product packaging or the brand's official online presence.

## ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

### Name

Anonymous

### Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

### Question

Example: How do I reset this device or fix this error?

### Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

---

Open the live page

<https://manuals.plus/asin/B0BF9Q9CZ3>

More documents and user manuals: <https://manuals.plus/>