**QLIFE Automatic Cat Feeder - 6L**

# QLIFE Automatic Pet Feeder - 6L Programmable Dry Food Dispenser User Manual

Model: Automatic Cat Feeder - 6L

## 1. Introduction

Thank you for choosing the QLIFE Automatic Pet Feeder. This device is designed to provide scheduled and portion-controlled meals for your pets, ensuring they are fed consistently even when you are away. This manual provides essential information for the safe and efficient operation of your new pet feeder.

## 2. Important Safety Instructions

- Read all instructions before using this appliance.
- **For dry pet food only:** Fill the feeder only with dry pet food. Kibble size should be between 2mm and 12mm in diameter.
- **Power Source:** Use the provided USB-C power adapter. For backup power, use 3 D-size alkaline batteries. Do not use rechargeable batteries.
- **Water Immersion:** Do not immerse the base of the feeder in water at any time. This will damage the control panel and electronic components.
- **Battery Maintenance:** Change batteries every 6 months if not in use for an extended period.
- **Placement:** Place the feeder on a stable, level surface.
- **Children and Pets:** Keep out of reach of small children and supervise pets during initial use to prevent tampering.
- **Cleaning:** Refer to the "Maintenance" section for proper cleaning procedures.

## 3. Package Contents

Please check the box for the following items:

- 1 x QLIFE Automatic Pet Feeder (6L capacity)

- 1 x USB-C Power Adapter and Cable
- 2 x Stainless Steel Bowls with Holder
- 2 x Feeding Lift Kits (for elevated bowls)
- 1 x Desiccant Bag
- 1 x User Guide (this manual)

## 4. Setup

### 4.1 Assembly

1. **Place the Feeder:** Position the feeder on a flat, stable surface.
2. **Install Bowls:** Attach the stainless steel bowls to the feeder base. If feeding two pets, ensure the food splitter is correctly inserted to divide food evenly. For a single pet, the splitter and one bowl can be removed.
3. **Add Desiccant:** Open the lid and place the desiccant bag in its designated compartment to maintain food freshness.
4. **Fill Food Tank:** Open the top lid and fill the 6-liter food tank with dry pet food. Ensure kibble size is appropriate (2-12mm). Close the lid securely to maintain freshness and prevent pets from accessing food.




*Image: The QLIFE Automatic Pet Feeder with two bowls, demonstrating its capacity and multi-pet feeding capability.*




*Image: Illustration of how to convert the feeder from a two-bowl setup to a single-bowl setup by removing the splitter.*

### 4.2 Power Supply

- **Primary Power:** Connect the USB-C cable to the feeder and plug the adapter into a wall outlet.
- **Battery Backup:** For uninterrupted operation during power outages, install 3 D-size alkaline batteries (not included) into the battery compartment located at the bottom of the feeder. The feeder will automatically switch to battery power if the main power is lost.




*Image: The dual power supply system, showing both USB-C input and the battery backup compartment.*

## 5. Operating Instructions

### 5.1 Setting Current Time

Upon first power-up or after a long power loss without battery backup, the display will show a default time. Use the control panel buttons (usually 'Set', '+', '-') to adjust the current hour and minute. Refer to the on-screen prompts for specific button presses.




*Image: The LCD digital screen and control buttons for programming the feeder.*

### 5.2 Programming Meal Times and Portions

The feeder allows for 1 to 6 meals per day, with up to 40 portions per meal. Each portion is approximately 7 grams.

1. Press the 'Set' button to enter programming mode.
2. Use the '+' and '-' buttons to navigate through meal settings (Meal 1, Meal 2, etc.).
3. For each meal, set the desired feeding time (hour and minute) and the number of portions.
4. Confirm each setting by pressing 'Set' again or as indicated by the display.
5. Exit programming mode once all desired meals are set.

The feeder will automatically dispense food at the programmed times. The schedule is retained even during power outages if battery backup is installed.

### 5.3 Manual Feeding

To dispense food manually, press and hold the manual feed button (refer to your feeder's specific button layout, often

indicated by a paw icon or similar). This will dispense one portion of food immediately. Release the button to stop dispensing.

### 5.4 Voice Recording

You can record a 10-second voice message to call your pet at meal times.

1. Locate the record button (often indicated by a microphone icon).
2. Press and hold the record button. Speak your message clearly into the microphone.
3. Release the button to save the recording. The recorded message will play automatically before each scheduled meal.




*Image: The voice recording feature, allowing you to call your pets to their meals.*

## 6. Maintenance

### 6.1 Cleaning

Regular cleaning ensures hygiene and proper functioning of the feeder.

- **Detachable Components:** The food tank, stainless steel bowls, and bowl holder are detachable for easy cleaning. Wash these components with mild soap and water, then rinse thoroughly and dry completely before reassembling.
- **Feeder Base:** Wipe the main feeder base with a damp cloth.**Do not immerse the base in water.**
- **Desiccant Bag:** Replace the desiccant bag periodically (e.g., every 1-2 months) to maintain food freshness.




*Image: Detachable components allow for thorough and hygienic cleaning.*

### 6.2 Battery Replacement

If using battery backup, replace the 3 D-size alkaline batteries every 6 months or when the low battery indicator appears on the display. Ensure the feeder is unplugged from main power before replacing batteries.

## 7. Troubleshooting

| Problem | Possible Cause | Solution |
|---|---|---|
| Feeder not dispensing food. | No power.<br>Food tank empty.<br>Kibble jammed.<br>Incorrect programming. | Check power adapter connection and/or battery status.<br>Refill food tank.<br>Clear any obstructions in the dispenser mechanism. Ensure kibble size is 2-12mm.<br>Verify meal times and portion settings. |
| Display is off or flickering. | Power issue.<br>Low batteries. | Check power adapter.<br>Replace D-size batteries. |
| Voice recording not playing. | No recording saved.<br>Volume too low. | Re-record your message.<br>Check if there's a volume setting (if applicable, otherwise assume fixed). |
| Food not evenly distributed (for two pets). | Splitter incorrectly installed.<br>Kibble size variation. | Ensure the food splitter is securely and correctly placed.<br>Ensure kibble is uniform and within recommended size. |

## 8. Specifications

| | |
|---|---|
| **Brand** | QLIFE |
| **Model Number** | Automatic Cat Feeder - 6L |
| **Capacity** | 6 Liters |
| **Dimensions (L x W x H)** | 33.78 x 19.3 x 36.32 cm (13.3 x 7.6 x 14.3 inches) |
| **Weight** | 3.2 Kilograms (7.05 lbs) |
| **Material** | Stainless Steel (bowls), Plastic (feeder body) |
| **Power Source** | USB-C Adapter (included), 3 x D-size Alkaline Batteries (not included) |
| **Kibble Size Compatibility** | 2mm - 12mm diameter |
| **Meals Per Day** | 1 - 6 meals |
| **Portions Per Meal** | Up to 40 portions (approx. 7g per portion) |
| **Special Features** | Programmable Feeding Schedule, Portion Control, 10-second Voice Recorder, Dual Power Supply, Desiccant Bag for Freshness, Detachable Components for Easy Cleaning |
| **Target Species** | Cats, Small/Medium/Large Dogs |

## 9. Warranty and Support

QLIFE products are manufactured to high-quality standards. For warranty information, technical support, or customer service inquiries, please refer to the contact information provided on the product packaging or visit the official QLIFE website. Please retain your proof of purchase for warranty claims.


### Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

**Name**

Anonymous

**Email**

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

**Question**

Example: How do I reset this device or fix this error?

**Details**

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question