Arcmira B0BPH31ZSC

Arcmira Automatic Nut Milk Maker Instruction Manual

Model: B0BPH31ZSC

1. Introduction

Thank you for choosing the Arcmira Automatic Nut Milk Maker. This appliance is designed to simplify the process of creating fresh, homemade plant-based milks from various nuts, seeds, grains, and beans. It offers multiple functions including milk making, boiling water, keeping warm, and a delay start feature, all controlled via an intuitive LED screen. Please read this manual thoroughly before first use to ensure safe and optimal operation.

2. Important Safety Instructions

- Read all instructions before using the appliance.
- Do not immerse the main unit (containing electrical components) in water or other liquids. The power cord is detachable for cleaning, but the main unit should only be wiped clean.
- Ensure the voltage indicated on the appliance corresponds to your local mains voltage before connecting.
- Keep the appliance out of reach of children. Close supervision is necessary when any appliance is used by or near children.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner. Contact customer service for assistance.
- Avoid contact with moving parts.
- Do not use attachments not recommended or sold by the manufacturer.
- Do not use outdoors.
- Always unplug from outlet when not in use, before putting on or taking off parts, and before cleaning.
- Do not let cord hang over edge of table or counter, or touch hot surfaces.
- Do not place on or near a hot gas or electric burner, or in a heated oven.
- Exercise extreme caution when moving an appliance containing hot liquid.
- The appliance has an overheating prevention and automatic shut-off function for safety.

3. Product Components

The Arcmira Automatic Nut Milk Maker comes with the following components:

- Main Unit (with stainless steel liner and integrated blades)
- Lid (with magnetic control induction)
- Power Cord
- Nut Milk Bag
- Cleaning Brush
- Measuring Spoon
- Recipe Book



Figure 1: Arcmira Nut Milk Maker and its accessories.

4. Setup

1. **Unpack:** Carefully remove all components from the packaging.
2. **Initial Cleaning:** Before first use, clean the stainless steel interior of the main unit and the lid with warm, soapy water. Use the provided cleaning brush for the blades. Rinse thoroughly and dry completely. Do not immerse the main unit in water.
3. **Connect Power:** Insert the detachable power cord into the port at the back of the main unit. Plug the other end into a standard 110V electrical outlet.
4. **Placement:** Place the appliance on a stable, flat, heat-resistant surface.



Figure 2: Basic steps for using the Arcmira Nut Milk Maker.

5. Operating Instructions

The Arcmira Nut Milk Maker features an intuitive LED screen and one-touch automatic programs for various functions.

5.1 Making Plant-Based Milk

1. **Add Ingredients:** Use the provided measuring spoon to add your desired nuts, seeds, grains, or beans into the stainless steel interior. Refer to the recipe book for recommended quantities.
2. **Add Water:** Pour water into the unit, ensuring it is between the 'MIN' and 'MAX' fill lines indicated inside the pitcher.
3. **Secure Lid:** Place the lid securely on the main unit. The magnetic control induction ensures proper closure for operation.
4. **Select Program:** Press the 'Menu/Cancel' button repeatedly to cycle through the available programs:
    - **Room Temp:** Ideal for almond milk and other chilled nut milks (suitable for 50-70°F).
    - **Warm (140°F):** For warm beverages.
    - **Hot (212°F):** For making soy and rice milk.
5. **Start:** Once the desired program is selected, the machine will automatically begin operation. The LED screen will display the remaining time.
6. **Completion:** The machine will beep approximately 10 times when the program is complete.



Figure 3: Overview of the three basic operating modes.

5.2 Additional Functions

- **Boil Water:** Select this function to simply boil water.
- **Keep Warm:** This function maintains the temperature of your beverage for up to 6 hours.
- **Delay Start:** Use the 'Delay Start' button to set a delayed start time for your program, up to 18 hours. This allows you to prepare ingredients in advance and have fresh milk ready when you need it.



Figure 4: Delay Start function for convenient scheduling.

5.3 Blade Technology

The Arcmira machine features 6-blade strong cross stainless steel blades, including 2 shark blades, designed for smooth blending and efficient nutrient extraction. The built-in quadrilateral stirring column ensures ingredients collide repeatedly for a smooth beverage texture.



Figure 5: Detailed view of the blending blades.

6. Recipes and Usage Examples

The included recipe book provides detailed instructions for making various plant-based milks. The Arcmira Nut Milk Maker can produce:

- Almond Milk
- Oat Milk
- Soy Milk
- Cashew Milk
- Rice Milk
- Coconut Milk
- Walnut Milk
- Hemp Milk

It can also be used to make smoothies and other hot or cold plant-based beverages. The machine is designed to

make approximately 20oz (600mL) of milk per cycle.



Figure 6: Examples of plant-based milks made with the Arcmira Nut Milk Maker.

6.1 Video Demonstrations

Video 1: A user demonstrates making oat milk with the Arcmira Nut Milk Maker, highlighting the process and the resulting milk. The video also shows the included cleaning brushes and measuring spoon.

Video 2: A user demonstrates the Arcmira Nut Milk Maker in operation, showing the blending process and the digital display.

Video 3: A short clip demonstrating the Arcmira Nut Milk Maker's blending action and digital display during operation.

Video 4: A brief demonstration of the Arcmira Nut Milk Maker's blending process.

Video 5: A user demonstrates pouring freshly made almond milk from the Arcmira Nut Milk Maker into a glass.

Video 6: A user demonstrates the Arcmira Nut Milk Maker's digital display and blending process.

7. Cleaning and Maintenance

Proper cleaning and maintenance will extend the life of your Arcmira Nut Milk Maker.

7.1 Self Clean Function

The appliance features a 'Self Clean' function for a quick 60-second rinse cycle. After use, add water up to the 'MIN' line and select the 'Self Clean' option. This helps to loosen any residue.

7.2 Manual Cleaning

- **Unplug:** Always unplug the appliance from the power outlet before cleaning.
- **Interior:** After the self-clean cycle or for a more thorough clean, carefully clean the stainless steel interior with warm, soapy water and the provided cleaning brush. Pay attention to the blades. Rinse thoroughly.
- **Exterior:** Wipe the exterior of the main unit with a damp cloth. Do not immerse the main unit in water.
- **Lid:** The lid can be hand-washed with warm, soapy water. Ensure it is completely dry before storing.
- **Nut Milk Bag:** Wash the nut milk bag with warm, soapy water and rinse thoroughly after each use. Allow it to air dry.
- **Drying:** Ensure all parts are completely dry before reassembling or storing the appliance.

8. Troubleshooting

If you encounter issues with your Arcmira Nut Milk Maker, please refer to the following common troubleshooting steps:

- **Appliance does not turn on:** Ensure the power cord is securely plugged into both the appliance and a working electrical outlet. Check if the lid is properly seated, as the magnetic induction requires correct placement for operation.
- **Milk is not smooth enough:** Ensure you are using the recommended amount of ingredients and water. For finer results, you may use the provided nut milk bag to strain the finished product.
- **Overheating/Automatic Shut-off:** The appliance has a built-in safety feature. If it overheats, it will automatically shut off. Allow the unit to cool down completely before attempting to use it again. Ensure proper ventilation around the unit.
- **Leaking:** Check that the lid is properly sealed and that the water level does not exceed the 'MAX' fill line.

If the issue persists, please contact Arcmira customer support.

9. Specifications

Feature	Detail
Brand	Arcmira
Model	B0BPH31ZSC
Color	Blue-green
Special Feature	Manual, Programmable
Capacity	591 Milliliters (approx. 20 oz)
Product Dimensions	7.4"D x 7.4"W x 11.8"H

Item Weight	20 Ounces
Power Source	Corded Electric
Wattage	600 watts
Voltage	110 Volts
Controls Type	Digital Touch
Material	Stainless Steel
Material Type Free	BPA Free, Chemical Free
Dishwasher Safe	No (Hand wash recommended for main unit, lid can be hand washed)
Blade Material	Stainless Steel
Style	Countertop Blenders

10. Warranty and Support

The Arcmira Automatic Nut Milk Maker comes with a**1-year manufacturer's limited warranty**. For any assistance, questions, or warranty claims, please contact Arcmira customer support through the retailer where the product was purchased or refer to the contact information provided in the product packaging.

© 2023 Arcmira. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question