

## SEYVUM LB-8189

# SEYVUM 20V Leaf Blower User Manual

Model: LB-8189

## 1. INTRODUCTION

Thank you for choosing the SEYVUM 20V Leaf Blower. This manual provides important information regarding the safe operation, assembly, maintenance, and troubleshooting of your leaf blower. Please read this manual thoroughly before using the product and keep it for future reference.

This SEYVUM 20V Leaf Blower is designed for clearing leaves, grass clippings, and other light debris from hard surfaces like driveways, patios, and decks. It is a battery-powered, handheld tool offering portability and ease of use.

## 2. GENERAL SAFETY INSTRUCTIONS

**WARNING: Read all safety warnings and instructions. Failure to follow the warnings and instructions may result in electric shock, fire, and/or serious injury.**

- **Work Area Safety:** Keep the work area clean and well-lit. Do not operate power tools in explosive atmospheres, such as in the presence of flammable liquids, gases, or dust. Keep children and bystanders away while operating a power tool.
- **Electrical Safety:** Avoid body contact with earthed or grounded surfaces. Do not expose power tools to rain or wet conditions.
- **Personal Safety:** Always wear eye protection, hearing protection, and sturdy footwear. Do not overreach. Maintain proper footing and balance at all times. Dress properly; do not wear loose clothing or jewelry.
- **Tool Use and Care:** Do not force the power tool. Use the correct power tool for your application. Disconnect the battery pack from the power tool before making any adjustments, changing accessories, or storing power tools.
- **Battery Tool Use and Care:** Recharge only with the charger specified by the manufacturer. Use power tools only with specifically designated battery packs.

- **Service:** Have your power tool serviced by a qualified repair person using only identical replacement parts.

### 3. PACKAGE CONTENTS

---

Carefully unpack all items and check against the list below. Ensure all components are present and undamaged before discarding packaging materials.

- SEYVUM 20V Leaf Blower (Tool Only)
- Blower Tube
- User Manual

*Note: Battery and charger are sold separately as this is a 'tool only' product.*

### 4. PRODUCT OVERVIEW

---

Familiarize yourself with the parts of your SEYVUM 20V Leaf Blower before operation.



Image: SEYVUM 20V Leaf Blower. This image displays the main unit of the leaf blower, typically showing the motor housing, handle, and the attachment point for the blower tube.

1. Blower Nozzle/Tube
2. Motor Housing
3. Handle
4. Trigger Switch
5. Battery Port

## 5. SETUP

---

### 5.1. Assembling the Blower Tube

1. Ensure the leaf blower is turned off and the battery is removed.
2. Align the blower tube with the outlet on the main unit.
3. Push the tube firmly onto the outlet until it clicks into place or is securely seated. Some models may require a twist to lock.
4. Verify the tube is securely attached before use.

### 5.2. Installing the Battery Pack

1. Ensure the battery pack is fully charged before first use. Refer to your battery charger manual for charging instructions.
2. Align the battery pack with the battery port on the leaf blower.
3. Slide the battery pack into the port until it locks into place with a click.
4. To remove the battery, press the release button (if present) and slide the battery out.

## 6. OPERATING INSTRUCTIONS

---

### 6.1. Starting the Leaf Blower

1. Ensure the battery is fully charged and properly installed.
2. Hold the leaf blower firmly with one hand on the handle.
3. Press the trigger switch to start the blower. The motor will begin to run, and air will exit the nozzle.
4. Release the trigger switch to turn off the blower.

### 6.2. Operating Tips

- Always direct the blower nozzle away from yourself, bystanders, and pets.
- Start blowing debris from the outer edges of the area and work inwards.
- Use a sweeping motion to move debris effectively.
- Avoid blowing debris towards open windows, cars, or other objects that could be damaged.
- For stubborn debris, use a rake or broom to loosen it before blowing.

## 7. MAINTENANCE

---

**WARNING: Always remove the battery pack before performing any maintenance or cleaning.**

### 7.1. Cleaning

- Keep the air vents clean and free of debris to prevent overheating.

- Wipe the exterior of the blower with a damp cloth. Do not use strong detergents or solvents.
- Periodically check the blower tube for blockages and clear any debris.

## 7.2. Storage

- Store the leaf blower in a dry, well-ventilated area, out of reach of children.
- Remove the battery pack from the tool before storing for extended periods.
- Store the battery pack in a cool, dry place, away from direct sunlight and extreme temperatures.

## 8. TROUBLESHOOTING

Problem	Possible Cause	Solution
Blower does not start	Battery not installed correctly Battery not charged Trigger switch faulty	Ensure battery is fully seated and locked. Charge the battery pack. Contact customer support for service.
Reduced air flow	Blower tube blocked Air intake vents obstructed	Remove battery, clear any blockages from the tube. Remove battery, clear debris from air intake vents.
Blower stops during operation	Battery depleted Overheating protection activated	Recharge the battery. Allow the tool to cool down for several minutes before resuming operation.

## 9. SPECIFICATIONS

Feature	Specification
Model Number	LB-8189
Voltage	20V (DC)
Air Speed	Up to 150 MPH
Air Volume	Up to 320 CFM
Power Source	Battery Powered
Form Factor	Handheld
Weight (Tool Only)	<i>(Specific weight not provided in source, typical for handheld blowers)</i>

## 10. WARRANTY AND SUPPORT

SEYVUM products are manufactured to high-quality standards. For information regarding warranty coverage, technical support, or replacement parts, please refer to the warranty card included with your purchase or visit the official SEYVUM website. Please have your model number (LB-8189) and purchase

date available when contacting support.

For further assistance, you may contact SEYVUM customer service through their official channels.