

Marg M3013001760

Marg AC Adapter User Manual

Model: M3013001760

1. INTRODUCTION

This manual provides essential information for the safe and efficient use of your Marg AC Adapter. This power supply unit is designed to provide reliable power to compatible Daewoo DVD Players, including models DPC-7100P, DPC-7200, DPC-7600PD, DPC-7209, and DPC-7900.

Please read this manual thoroughly before using the product and retain it for future reference.

2. SAFETY INFORMATION

Your Marg AC Adapter is equipped with advanced safety features to protect your devices and ensure safe operation. Adhere to the following guidelines:

- Do not expose the adapter to water or moisture.
- Do not disassemble or attempt to repair the adapter.
- Ensure the adapter is used within its specified voltage and current ratings.
- Avoid using the adapter in extremely hot or cold environments.
- Keep out of reach of children.

Intelligent Protection Chip



Figure 2.1: Intelligent Protection Chip. This image displays the internal intelligent protection chip of the AC adapter, detailing its various safety mechanisms including input overvoltage, overheat, overcurrent, short circuit, and output overvoltage protection.

BUILT-IN SAFETY PROTECTIONS

Designed with safety in mind



OVP (Over Voltage Protection)



OCP (Over Current Protection)



OTP (Over Temperature Protection)



SCP (Short Circuit Protection)



Figure 2.2: Built-in Safety Protections. This image illustrates the comprehensive safety features of the adapter, including Over Voltage Protection (OVP), Over Current Protection (OCP), Over Temperature Protection (OTP), and Short Circuit Protection (SCP), designed to safeguard your devices.

SAFE & RELIABLE



Short Circuit Protection



Over Voltage Protection



Over Temperature Protection



Over charge and over discharge protection



Figure 2.3: Safe & Reliable Design. This image highlights the adapter's safe and reliable design, featuring icons for Short Circuit Protection, Over Voltage Protection, Over Temperature Protection, and Over Charge and Discharge Protection.

3. SETUP

Follow these steps to set up your AC adapter:

1. **Verify Compatibility:** Ensure your Daewoo DVD Player model (DPC-7100P, DPC-7200, DPC-7600PD, DPC-7209, DPC-7900) is listed as compatible with this adapter.
2. **Connect to Device:** Insert the adapter's output connector firmly into the power input port of your Daewoo DVD Player.
3. **Connect to Power Outlet:** Plug the AC adapter into a standard wall power outlet. Ensure the outlet is easily accessible.
4. **Power On:** Once connected, your device should receive power. Refer to your DVD player's manual for specific power-on procedures.

4. OPERATING INSTRUCTIONS

The Marg AC Adapter is designed for straightforward operation:

- **Powering Your Device:** Once properly connected, the adapter will supply continuous power to your compatible Daewoo DVD Player.
- **Charging (if applicable):** If your device has a rechargeable battery, the adapter will charge it while providing power. The adapter features efficient charging capabilities.
- **Disconnection:** To disconnect, first power off your device (if applicable), then unplug the adapter from the wall outlet, and finally disconnect it from your device.

CHARGING SPEED

Huge Savings on Batteries

AC Adapter
Model: Input:100-240VAC/0.3A
50/60Hz
Output: [unintelligible]
MADE IN CHINA

50%

25%

Our Charger

Regular

Figure 4.1: Charging Efficiency. This image illustrates the efficient charging capability of the Marg AC Adapter, demonstrating faster charging compared to a regular charger.



Figure 4.2: Versatile Usage. This collage depicts the AC adapter being used in diverse settings such as an office, a home living room, during work, and while traveling, highlighting its adaptability for various environments.

5. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your AC adapter:

- **Cleaning:** Disconnect the adapter from both the power outlet and your device before cleaning. Use a soft, dry cloth to wipe the exterior. Do not use liquid cleaners or solvents.
- **Storage:** When not in use, store the adapter in a cool, dry place, away from direct sunlight and extreme temperatures. Avoid tightly coiling the cable.
- **Cable Care:** Regularly inspect the cable for any signs of damage, such as fraying or cuts. Do not use the adapter if the cable is damaged.



Figure 5.1: High Quality Cable. This image showcases the robust construction of the adapter's cable, emphasizing its quality and durability.

6. TROUBLESHOOTING

If you encounter issues with your AC adapter, refer to the following troubleshooting steps:

Problem	Possible Cause	Solution
Device not powering on/charging	Loose connection	Ensure all connections (adapter to device, adapter to wall outlet) are secure.
Device not powering on/charging	Faulty power outlet	Test the power outlet with another device or try a different outlet.
Device not powering on/charging	Incompatible device	Verify that your device model is listed as compatible.
Slow charging	Device drawing too much power	Ensure no other high-power accessories are connected to the device during charging.
Adapter feels hot	Normal operation or poor ventilation	A slight warmth is normal. Ensure the adapter is in a well-ventilated area and not covered. If it's excessively hot, discontinue use and contact support.

If the problem persists after trying these solutions, please contact customer support.

7. SPECIFICATIONS

Feature	Specification
Brand	Marg
Model Number	M3013001760
Connector Type	ACC
Compatible Devices	Daewoo DPC-7100P, DPC-7200, DPC-7600PD, DPC-7209, DPC-7900 DVD Players
Color	Black
Power Source	Corded Electric
Connectivity Technology	Powerline
Safety Features	Overcharging, Overheating, Overvoltage, Overcurrent, Short Circuit Protection

8. WARRANTY

This Marg AC Adapter comes with a **3-year warranty** from the date of purchase. This warranty covers manufacturing defects and ensures the product performs as described under normal use. Please retain your proof of purchase for warranty claims.

The warranty does not cover damage caused by misuse, accidents, unauthorized modifications, or improper installation.

9. SUPPORT

For further assistance, technical support, or warranty inquiries, please contact Marg customer service. Refer to the product packaging or the retailer's website for the most current contact information.

When contacting support, please have your product model number (M3013001760) and proof of purchase readily available.