GODOX SL60IID

Godox SL60IID 70W LED Video Light User Manual

Model: SL60IID
Brand: GODOX

1. Introduction

This manual provides detailed instructions for the safe and effective use of your Godox SL60IID 70W LED Video Light. Please read this manual thoroughly before operation to ensure proper functionality and to prevent damage to the product or injury to yourself or others. Keep this manual for future reference.



Image: The Godox SL60IID LED Video Light, showing the main unit, reflector, power cord, and remote control.

2. Product Features

- **High Output:** 70W LED light with up to 18,600 Lux at 1 meter (with standard reflector).
- **Accurate Color:** CRI 96+ and TLCI 97+ for natural and faithful color reproduction.
- **Daylight Balanced:** Fixed color temperature of 5600K ± 200K.
- **Special Effects:** 8 built-in FX effects including Flash (1, 2, 3), Storm (1, 2, 3), TV, and Broken Bulb.
- **Multiple Control Methods:** On-device controls, 2.4G wireless remote control (RC-A6 included), and Bluetooth APP control via "Godox Light" application.
- **Silent Fan:** Upgraded fan design for a quieter operating environment.
- **Bowens Mount:** Standard Bowens-mount for compatibility with a wide range of light modifiers.
- **Compact and Portable:** Lightweight design for easy transport and flexible positioning.



Image: The Godox SL60IID Compact COB Video Light emitting bright light, mounted on a stand.

3. Setup Instructions

3.1 Unpacking and Components

Carefully unpack the contents and ensure all items are present:

- Light Body (SL60IID) x1
- LED Bowens-mount Reflector x1
- Power Cord x1
- Protection Cover x1
- LETWING Cloth x1
- RC-A6 Remote Control x1 (if included in package)

3.2 Assembly

1. **Attach Reflector:** Align the standard Bowens-mount reflector with the front of the light body. Rotate clockwise until it locks securely.
2. **Mounting:** Attach the light body to a light stand using the integrated U-shaped holder. Adjust the angle as needed and tighten the locking knob.
3. **Power Connection:** Connect the power cord to the light's power input and then to a suitable AC power outlet.



Image: The Godox SL60IID demonstrating its flexible angle adjustment and compatibility with various Bowens mount modifiers like softboxes and beauty dishes.

4. Operating Instructions

4.1 Power On/Off

Flip the power switch located on the back of the light body to turn the unit on or off.

4.2 Brightness Adjustment

Use the 'DIM' dial on the control panel to adjust the brightness from 0% to 100%. The current brightness level will be displayed on the LCD screen.



Image: Visual representation of the Godox SL60IID's dimmable brightness from 0% to 100% output.

4.3 FX Special Effects

Press the 'FX' button on the control panel to cycle through the 8 special effects. Use the 'CCT/FX' dial to select the desired effect:

- Flash 1, Flash 2, Flash 3
- Storm 1, Storm 2, Storm 3
- TV
- Broken Bulb



Image: Icons representing the 8 built-in FX effects available on the SL60IID, including various flash and storm simulations, TV, and broken bulb.

4.4 Control Methods

The SL60IID offers multiple ways to control its settings:

- **On-Device Control:** Use the dials and buttons directly on the light's control panel.
- **2.4G Wireless Remote Control:** Use the included RC-A6 remote to adjust settings wirelessly. Refer to the RC-A6 manual for specific instructions.
- **Bluetooth APP Control:** Download the "Godox Light" app on your smartphone. Enable Bluetooth on the light and your phone, then pair the devices to control the light remotely.



Image: A hand holding a smartphone displaying the Godox Light app interface, controlling the Godox SL60IID LED video light.

5. Maintenance

5.1 Cleaning

Regularly clean the light body and reflector with a soft, dry cloth. For stubborn dirt, use a slightly damp cloth and then dry thoroughly. Avoid using harsh chemicals or abrasive materials that could damage the finish or optical components.

5.2 Storage

When not in use, store the Godox SL60IID in a cool, dry place, away from direct sunlight and excessive humidity. Ensure the protection cover is in place to protect the LED COB.

5.3 Fan Operation

The SL60IID features an ultra-silent fan for heat dissipation. Ensure the fan vents are not obstructed during operation to maintain optimal performance and prevent overheating.



Image: An illustration highlighting the silent fan system within the Godox SL60IID, emphasizing its quiet operation.

6. Troubleshooting

Problem	Possible Cause	Solution
Light does not turn on.	No power supply; loose connection; power switch off.	Check power cord connection; ensure power outlet is functional; turn power switch to ON position.
Remote control not working.	Batteries low/dead; incorrect channel/group setting; out of range.	Replace remote batteries; ensure light and remote are on the same channel/group; operate within effective range.

Problem	Possible Cause	Solution
APP control not connecting.	Bluetooth not enabled on light/phone; app not updated; interference.	Ensure Bluetooth is active on both devices; update "Godox Light" app; try reconnecting in a different location.
Light flickers or output is inconsistent.	Unstable power supply; overheating.	Ensure stable power source; check for obstructed fan vents; allow light to cool down if operating for extended periods.

7. Specifications

Feature	Detail
Model	SL60IID
Power Output	70W
Color Temperature	5600K ± 200K
CRI	96+
TLCI	97+
Illuminance (1m, with standard reflector)	18,600 Lux
Dimming Range	0% - 100%
FX Effects	8 types
Control Methods	On-device, 2.4G Wireless (RC-A6), Bluetooth APP
Mount Type	Bowens Mount
Product Dimensions (unfolded without reflector)	5.51 x 9.29 x 8.46 inches (14 x 23.6 x 21.5 cm)
Net Weight	3.15 lbs (1.43 kg)
Connectivity Technology	Bluetooth



Image: A graphic illustrating the high CRI (96+) and TLCI (97+) ratings of the Godox SL60IID, indicating accurate color fidelity.

8. Warranty Information

For detailed warranty information, please refer to the warranty card included with your product or visit the official Godox website. Warranty terms and conditions may vary by region and retailer. Please retain your proof of purchase for any warranty claims.

9. Customer Support

If you encounter any issues or have questions regarding your Godox SL60IID LED Video Light that are not covered in this manual, please contact Godox customer support or your authorized dealer. You can find contact information on the official Godox website: www.godox.com.

© 2023 GODOX. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question