Monte Carlo 3ALMSM52BS

Monte Carlo Generation Lighting Alma Smart Ceiling Fan (Model 3ALMSM52BS) Instruction Manual

Model: 3ALMSM52BS

1. Introduction

Thank you for purchasing the Monte Carlo Generation Lighting Alma Smart Ceiling Fan. This 52-inch indoor/outdoor damp-rated ceiling fan features three light grey weathered oak carved wood blades and a brushed steel finish, designed to provide efficient air circulation and enhance your living space. This manual provides essential information for safe installation, operation, and maintenance of your new ceiling fan. Please read all instructions carefully before beginning installation and retain this manual for future reference.



Image 1.1: Monte Carlo Alma Smart Ceiling Fan (Model 3ALMSM52BS)

2. Safety Information

WARNING: To reduce the risk of fire, electric shock, or personal injury, always follow these instructions:

- Read all instructions and safety information before installing your fan and save these instructions.
- All wiring must be in accordance with national and local electrical codes. Installation should be performed by a qualified licensed electrician.
- The fan must be mounted to an outlet box marked "Acceptable for Fan Support of 35 lbs (15.9 kg) or less" and use mounting screws

provided with the outlet box.

- Do not operate the fan with damaged blades or housing.
- Ensure the fan is turned off and power is disconnected at the circuit breaker before servicing or cleaning.
- Avoid placing objects in the path of the blades.
- This fan is damp-rated for indoor and outdoor covered use. Do not expose to direct water spray.

3. Package Contents

Carefully unpack your fan and inspect the contents. You should have the following items:

- Fan Motor Assembly
- Fan Blades (3)
- Downrod (6 inches)
- Mounting Bracket
- Canopy
- Remote Control with Wall Mount
- Hardware Pack (screws, washers, wire nuts)
- Instruction Manual

4. Setup and Installation

Important: Before installation, ensure the power is turned off at the circuit breaker and the wall switch.

4.1 Mounting the Fan

1. Attach the mounting bracket to the ceiling outlet box using the screws provided with the outlet box. Ensure the bracket is securely fastened and can support the fan's weight.
2. Feed the electrical wires from the outlet box through the center hole of the mounting bracket.

4.2 Assembling the Fan

1. Insert the downrod through the canopy and then through the fan motor assembly. Secure the downrod to the motor housing with the provided pin and screw.
2. Carefully lift the fan assembly and hang it from the mounting bracket using the ball joint in the downrod. Ensure the ball joint is seated correctly in the bracket's opening.

4.3 Electrical Connections

Connect the fan's electrical wires to the household wiring according to the following:

- Connect the green/bare copper wire from the fan to the household ground wire (green or bare copper).
- Connect the white wire from the fan to the household neutral wire (white).
- Connect the black wire from the fan to the household hot wire (black).
- Secure all connections with wire nuts and ensure no loose strands of wire are exposed.

4.4 Attaching Blades

1. Attach each blade to the fan motor housing using the screws and washers provided. Ensure all screws are tightened securely.

4.5 Securing the Canopy

1. Slide the canopy up against the ceiling and secure it to the mounting bracket with the provided screws.

5. Operating Instructions

Your Alma Smart Ceiling Fan is operated via the included remote control and can also be controlled via a smart app.

5.1 Remote Control Functions

The remote control allows you to adjust fan speed, turn the fan on/off, change fan direction, and control the optional light kit.

- **Power Button:** Turns the fan on or off.
- **Fan Speed Buttons:** Adjusts fan speed (typically 6 speeds).
- **Fan Direction Button:** Reverses blade rotation for summer (downward airflow) or winter (upward airflow) operation.
- **Light On/Off Button:** Controls the optional light kit.
- **Light Dimming Buttons:** Adjusts the brightness of the optional light kit.

5.2 Smart App Control

For smart control features, download the compatible Monte Carlo smart app from your device's app store. Follow the in-app instructions to pair your fan with your smart device. This allows for advanced control, scheduling, and integration with smart home systems.

6. Maintenance

Regular maintenance ensures optimal performance and extends the life of your ceiling fan.

- **Cleaning:** Clean the fan periodically with a soft, damp cloth. Do not use abrasive cleaners or solvents, as these can damage the finish or blades.
- **Blade Care:** The light grey weathered oak carved wood blades should be cleaned gently. Avoid excessive moisture.
- **Tighten Fasteners:** Periodically check all screws and fasteners on the fan and mounting hardware to ensure they are secure.
- **Lubrication:** The fan motor is permanently lubricated and does not require additional oiling.

Caution: Always turn off the power at the circuit breaker before cleaning or performing any maintenance.

7. Troubleshooting

If you experience issues with your fan, refer to the following troubleshooting guide:

Problem	Possible Cause	Solution
Fan does not start	No power to the fan Loose wire connections Remote control not paired	Check circuit breaker and wall switch Verify all wire connections are secure (power off first) Refer to remote pairing instructions in the smart app or separate remote manual.
Fan wobbles	Loose blade screws Improperly balanced blades Loose mounting bracket	Ensure all blade screws are tight Use a blade balancing kit (sold separately) to balance blades Tighten mounting bracket screws
Noisy operation	Loose screws Motor housing rubbing Incorrect installation	Check and tighten all screws Ensure canopy is not touching the ceiling Re-check installation steps
Remote control not working	Dead batteries Remote not paired Obstruction between remote and receiver	Replace batteries Re-pair remote with fan Ensure clear line of sight

8. Specifications

Feature	Detail
Model Number	3ALMSM52BS

Feature	Detail
Brand	Monte Carlo
Product Dimensions	52"D x 52"W x 13.1"H
Blade Span	52 inches
Number of Blades	3
Blade Material	Wood (Light Grey Weathered Oak Carved)
Finish	Brushed Steel
Indoor/Outdoor Usage	Outdoor (Damp Rated)
Power Source	Corded Electric
Motor Type	DC
Number of Speeds	6
Air Flow Capacity	5955 cfm
Wattage	60 watts
Controller Type	Remote Control
Control Method	App
Downrod Length	6 inches
Special Feature	Heavy Duty
Certifications	cETL Approved, Energy Star

9. Warranty Information

This Monte Carlo Generation Lighting Alma Smart Ceiling Fan (Model 3ALMSM52BS) comes with a **1 Year Manufacturer Warranty**. Please retain your proof of purchase for warranty claims. The warranty covers defects in materials and workmanship under normal use. For specific terms and conditions, please refer to the warranty card included with your product or contact Monte Carlo customer support.

10. Customer Support

For technical assistance, troubleshooting, or warranty inquiries, please contact Monte Carlo customer support. You can find contact information on the official Monte Carlo website or on the packaging of your product. Please have your model number (3ALMSM52BS) and proof of purchase ready when contacting support.

Online Resources: For additional information, FAQs, and product registration, visit the official Monte Carlo website: www.montecarlofans.com

© 2026 Monte Carlo Generation Lighting. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question

and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question