

Yodoit PTM15

Yodoit Portable Monitor 15.6" User Manual

Model: PTM15

1. PRODUCT OVERVIEW

The Yodoit 15.6-inch Portable Monitor is a versatile and lightweight display designed to enhance your productivity and entertainment experience. Featuring a 1080p Full HD IPS panel, it delivers vibrant colors and wide viewing angles. Its slim profile and integrated smart cover make it an ideal companion for on-the-go use.



The Yodoit 15.6" Portable Monitor, showcasing its vibrant display and smart cover acting as a stand.

Lightweight & Portable

Size
15.6"

Thickness
0.2 Inch

Weight
0.7 KG



This diagram highlights the monitor's lightweight design (0.7 kg) and slim thickness (0.2 inches), emphasizing its portability.

Key Features:

- **15.6-inch Full HD (1920x1080) IPS Display:** Offers crisp visuals and wide viewing angles.
- **Anti-Glare Screen:** Reduces reflections for comfortable viewing in various lighting conditions.
- **Dual USB-C Ports:** For power and video signal transmission with compatible devices.
- **Mini HDMI Port:** Provides broad compatibility with a variety of devices.

- **Built-in Dual Speakers:** Delivers audio without the need for external speakers.
- **Smart Cover:** Protects the screen and functions as an adjustable stand.
- **Plug-and-Play Functionality:** No drivers or complex setup required for most devices.
- **Lightweight and Ultra-Slim Design:** Weighs only 0.7 kg and is 0.9 cm thin for easy transport.

2. SETUP

Setting up your Yodoit Portable Monitor is straightforward. Follow these steps to connect it to your device.

Connecting the Monitor:

1. **Identify Ports:** Locate the USB-C and Mini HDMI ports on your Yodoit monitor and your source device (laptop, PC, phone, gaming console).
2. **Power Supply:** The monitor can draw power directly from a compatible USB-C port on your device. If your device's USB-C port does not provide sufficient power, or if you are using the Mini HDMI connection, you will need to connect the monitor to an external power source using the provided USB-C power adapter.
3. **Connection Options:**
 - **USB-C to USB-C (Full-Featured):** If your device has a full-featured USB-C port (supporting video output and power delivery), connect one end of the USB-C cable to the monitor and the other end to your device. This single cable can provide both power and video signal.
 - **Mini HDMI to HDMI:** Connect the Mini HDMI end of the cable to the monitor and the standard HDMI end to your device. In this setup, you will also need to connect a USB-C cable from the monitor to a power source (either your device's USB port or a wall adapter) for power.
 - **iPhone/Lightning Devices:** For iPhones, an adapter with an HDMI output port (e.g., Lightning to HDMI adapter) is required to connect via the Mini HDMI port. Power will still be needed via USB-C.
4. **Positioning:** Use the integrated smart cover to prop up the monitor at your desired viewing angle. The magnetic design allows for stable positioning.

Wide Compatibility



A detailed view of the monitor's connectivity options: dual USB-C ports, Mini HDMI port, and 3.5mm audio jack.

Superior Visual Experience



The monitor set up as a secondary display, demonstrating its use for increased work efficiency.

3. OPERATING

Once connected, the Yodoit Portable Monitor is designed for intuitive operation.

Basic Operation:

- **Power On/Off:** The monitor typically powers on automatically when a signal is detected and sufficient power is supplied. Use the Power/Return Button on the side to manually turn the monitor on or off.
- **Adjusting Settings:** Use the Turning Button (scroll wheel) on the side of the monitor to navigate the On-Screen Display (OSD) menu. Press the button to select an option, and scroll to adjust values or move through menus. The Power/Return Button can be used to go back in the menu.
- **Display Modes:** The monitor supports both landscape and portrait orientations. Your connected device should automatically detect and allow you to switch between these modes in its display settings.
- **Audio:** The monitor has built-in dual speakers. Audio will be routed through the monitor when connected via USB-C or HDMI. You can also connect external headphones or speakers via the 3.5mm audio jack.

Increase Work Efficiency



The monitor seamlessly extends a laptop's display, enhancing productivity for various tasks.

Vesa Mountable & Multiple Mode



The monitor supports VESA mounting (75x75mm) and can be used in both landscape and portrait orientations for flexible setups.

360° Surround Sound & Dual Speakers



The monitor features integrated dual speakers for 360-degree surround sound, providing audio without external devices.

4. MAINTENANCE

Proper care and maintenance will ensure the longevity and optimal performance of your Yodoit Portable Monitor.

Cleaning the Monitor:

- **Screen:** Gently wipe the screen with a soft, lint-free cloth. For stubborn smudges, slightly dampen the cloth with water or a screen-specific cleaning solution. Avoid using harsh chemicals, alcohol, or abrasive materials, as these can damage the screen surface.
- **Body:** Use a soft, dry cloth to clean the monitor's casing.

General Care:

- **Storage:** When not in use, always store the monitor in its smart cover to protect the screen from scratches and impacts.
- **Handling:** Avoid dropping the monitor or subjecting it to strong impacts. Do not place heavy objects on top of it.
- **Environment:** Keep the monitor away from extreme temperatures, direct sunlight, and high humidity. Ensure proper ventilation during use.
- **Cables:** Handle cables carefully. Avoid bending them sharply or pulling them forcefully from the ports.

5. TROUBLESHOOTING

If you encounter issues with your Yodoit Portable Monitor, refer to the following common troubleshooting steps.

Common Issues and Solutions:

- **"No Signal" Message:**
 - Ensure all cables (USB-C, HDMI) are securely connected to both the monitor and your source device.
 - Verify that your source device is powered on and configured to output video to an external display.
 - Try using different cables to rule out a faulty cable.
 - If using HDMI, ensure the monitor is also receiving power via a USB-C connection.
 - Restart both the monitor and your source device.
- **No Power / Monitor Not Turning On:**
 - Ensure the USB-C power cable is properly connected to a sufficient power source (wall adapter or powerful USB-C port).
 - Check if the power adapter and cable are working correctly by testing them with another device if possible.
 - Press the Power/Return Button to manually turn on the monitor.
- **Flickering Screen / Unstable Display:**
 - Ensure the monitor is receiving adequate power. Insufficient power can cause instability.
 - Try a different cable or port on your source device.
 - Reduce the display resolution or refresh rate on your source device's settings.
- **No Audio from Speakers:**
 - Check the volume settings on both the monitor (via OSD menu) and your source device.
 - Ensure the audio output on your source device is set to the Yodoit monitor.
 - If using HDMI, ensure the audio signal is being transmitted through the HDMI cable.
- **Image Quality Issues (Blurry, Incorrect Colors):**
 - Adjust the display settings (brightness, contrast, color temperature) via the monitor's OSD menu.
 - Ensure the display resolution on your source device matches the monitor's native resolution (1920x1080).
 - Check for any physical damage to the screen or cables.

If these steps do not resolve the issue, please contact Yodoit customer support for further assistance.

6. SPECIFICATIONS

Detailed technical specifications for the Yodoit Portable Monitor (Model PTM15).

Feature	Specification
Brand	Yodoit
Model Number	PTM15
Screen Size	15.6 Inches

Feature	Specification
Resolution	1920 x 1080 (Full HD)
Display Technology	IPS
Refresh Rate	60 Hz
Response Time	2 Milliseconds
Aspect Ratio	16:9
Screen Surface Description	Glossy (Anti-Glare)
Contrast Ratio	High
Connectivity	2x USB-C, 1x Mini HDMI, 1x 3.5mm Audio Jack
Product Dimensions	40.3 x 26.4 x 5.3 cm (15.87 x 10.39 x 2.09 inches)
Item Weight	700 g (1.54 lbs)
Color	Black
Special Features	Portable, Built-in Speakers, Smart Cover, VESA Mountable

7. WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the documentation included with your purchase or visit the official Yodoit website. Typically, warranty details, return policies, and contact information for technical assistance are provided by the seller or manufacturer.

If you require further assistance with setup, operation, or troubleshooting that is not covered in this manual, please reach out to Yodoit customer service through their official channels.

Online Resources:

- Check the product page on the retailer's website for FAQs or additional support links.
- Visit the Yodoit brand's official website for the latest drivers, firmware updates, and support contact details.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question