

Watyo LTV303-3SN

Watyo LTV303-3SN 3-Light Brushed Nickel Bathroom Vanity Light Fixture

Instruction Manual

INTRODUCTION

Thank you for choosing the Watyo LTV303-3SN 3-Light Brushed Nickel Bathroom Vanity Light Fixture. This manual provides detailed instructions for the safe installation, operation, and maintenance of your new lighting fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference.

This fixture features a sturdy metal lamp body with clear globe glass shades and a brushed nickel finish, designed for modern bathroom aesthetics. It accommodates three E26 base bulbs (not included).

IMPORTANT SAFETY INFORMATION

- Always turn off the power at the main circuit breaker before installation or maintenance.
- Consult a qualified electrician if you are unsure about the installation process.
- Use only E26 base bulbs, maximum 60 watts per socket.
- Ensure all electrical connections are secure and comply with local codes.
- Handle glass shades with care to prevent breakage.
- This fixture is designed for indoor use only and is not water resistant.

WHAT'S IN THE BOX

Carefully unpack your fixture and ensure all parts are present. The package should include:

- Vanity Light Fixture (Brushed Nickel)
- 3 Clear Glass Shades
- Instruction Manual
- Mounting Hardware (screws, wire nuts, mounting bracket)



Image: Components of the Watyo 3-Light Vanity Fixture, showing the main bar, glass shades, and various mounting hardware pieces.

SETUP AND INSTALLATION

This fixture is designed for semi-flush wall mount installation. Follow these steps for a safe and proper setup:

1. **Prepare for Installation:** Turn off power at the circuit breaker. Ensure the mounting surface is clean and dry.
2. **Attach Mounting Bracket:** Secure the mounting bracket to the junction box using the provided screws. Ensure it is firmly attached.
3. **Make Electrical Connections:** Connect the fixture's wires to the house wires according to standard electrical codes (black to black, white to white, ground to ground). Use the provided wire nuts and ensure connections are secure.
4. **Mount the Fixture:** Carefully align the fixture with the mounting bracket and secure it with the canopy screws.
5. **Install Glass Shades:** Gently screw the clear globe glass shades onto the fixture's sockets. Do not overtighten.
6. **Insert Bulbs:** Screw in three E26 base bulbs (not included) into the sockets. We recommend clear A19 or T45 bulbs for a modern look.
7. **Restore Power:** Turn the power back on at the circuit breaker.



Image: The Watyo 3-Light Brushed Nickel Vanity Light Fixture installed above a bathroom mirror, showcasing its modern design.



Image: A close-up view of the sturdy mounting bracket, highlighting its robust construction for secure installation.

OPERATING INSTRUCTIONS

Once installed and powered, your Watyo vanity light fixture is ready for use. It operates via a standard wall

switch (not included).

- **Turning On/Off:** Use the wall switch connected to the fixture to turn the lights on or off.
- **Dimmable Capability:** This fixture has full dimming capability if used with dimmable E26 bulbs and a compatible dimmer switch (both not included).



Image: A split image demonstrating the Watyo vanity light fixture in both its 'on' (illuminated) and 'off' states.

MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your light fixture.

- **Cleaning:** Before cleaning, ensure the power is off and the fixture is cool. Wipe the brushed nickel finish with a soft, dry cloth. For glass shades, use a mild glass cleaner and a soft cloth. Avoid abrasive cleaners or harsh chemicals.
- **Bulb Replacement:** Always turn off power before replacing bulbs. Allow bulbs to cool completely. Unscrew old bulbs and replace with new E26 base bulbs (max 60W).
- **Inspection:** Periodically check for any loose connections or signs of wear. If any issues are found, consult a qualified electrician.

TROUBLESHOOTING

If you encounter issues with your light fixture, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture, loose wiring, faulty bulb, faulty switch	Check circuit breaker. Ensure all wiring is secure. Replace bulb. Test switch.
Lights flicker	Loose bulb, incompatible dimmer switch/bulbs, loose wiring	Tighten bulbs. Ensure dimmer and bulbs are compatible. Check wiring connections.
Glass shade is loose	Shade not tightened properly	Gently tighten the glass shade onto the socket.

SPECIFICATIONS

Feature	Detail
Brand	Watyo
Model Name	LTV303-3SN
Color	Brushed Nickel
Material	Glass, Metal
Style	Modern
Light Fixture Form	Vanity
Room Type	Bathroom
Product Dimensions	19.69"L x 6.97"W x 9.11"H
Indoor/Outdoor Usage	Indoor
Power Source	Corded Electric
Installation Type	Semi Flush Mount
Number of Light Sources	3
Voltage	110 Volts
Wattage (Max)	60 watts per bulb
Bulb Base	E26
Assembly Required	Yes
Item Weight	3.5 Pounds



Size Display



E26 Base
RECOMMENDED BULBS
(Bulbs are not included)



Image: A diagram illustrating the dimensions of the Watyo 3-Light Vanity Light Fixture, including length, width, and height.

WARRANTY AND SUPPORT

This Watyo product comes with a Limited Warranty. For specific details regarding warranty coverage and claims, please refer to the documentation included with your purchase or contact Watyo customer support. For technical assistance, troubleshooting not covered in this manual, or to inquire about replacement parts, please contact Watyo customer service through the retailer where the product was purchased.