

[Manuals.plus](#) /

› [HOREVO](#) /

› HOREVO 24W LED Ceiling Lamp X003 Instruction Manual

HOREVO X003

HOREVO 24W LED Ceiling Lamp X003 Instruction Manual

Model: X003

1. PRODUCT OVERVIEW

The HOREVO 24W LED Ceiling Lamp X003 is a flush mount ceiling light fixture featuring a built-in Bluetooth speaker and remote control. It offers RGB color-changing capabilities and adjustable white light (6500K daylight bright). This energy-efficient LED light is designed for various indoor spaces.

Simple Design



**12W
LED**

Image 1.1: Front view of the HOREVO 24W LED Ceiling Lamp.

2. SAFETY INFORMATION

- **Electrical Installation:** Installation must be performed by a qualified electrician or in accordance with local electrical codes. Ensure power is turned off at the circuit breaker before installation.
- **Indoor Use Only:** This fixture is designed for indoor use.
- **Humidity Warning:** To ensure long-term durability and optimal performance, avoid installation in bathrooms or areas with sustained high humidity.
- **Voltage:** Operate only with 110 Volts AC power supply.
- **Cleaning:** Disconnect power before cleaning. Use a soft, dry cloth. Do not use abrasive cleaners or solvents.

3. WHAT'S IN THE BOX

Verify that all components are present before beginning installation.

- HOREVO 24W LED Ceiling Lamp Fixture
- Remote Control
- Mounting Hardware (screws, anchors)
- Instruction Manual (this document)



4. SETUP AND INSTALLATION

This ceiling lamp is designed for flush mount installation and requires wired electrical connection.

1. **Turn off Power:** Before starting, ensure the power supply to the installation area is completely turned off at the main circuit breaker.
2. **Prepare Mounting Surface:** Identify the electrical junction box in your ceiling. Ensure the surface is clean and stable.
3. **Attach Mounting Bracket:** Secure the mounting bracket (usually included with hardware) to the junction box using the provided screws.
4. **Electrical Wiring:** Connect the fixture's wires to your household wiring. Typically, this involves connecting live (black) to live, neutral (white) to neutral, and ground to ground. Use wire nuts to secure connections. **If you are unsure about wiring, consult a qualified electrician.**
5. **Mount the Fixture:** Carefully align the lamp fixture with the mounting bracket and secure it in place with the provided screws. Ensure it is flush against the ceiling.
6. **Restore Power:** Once the fixture is securely installed and wired, restore power at the circuit breaker.



Image 4.1: Underside of the lamp, illustrating the wiring connection points and integrated speaker.

5. OPERATING INSTRUCTIONS

5.1. Light Functions

The lamp offers various lighting modes controlled by the included remote or a wall switch.

- **White Light:** Provides 6500K daylight bright illumination (1800 lumens).
- **RGB Color Changing:** Choose from gradient colorful lights or seven single color light modes.
- **Dimming:** Stepless dimming from 1% to 100% brightness.
- **Color Temperature Adjustment:** Adjust white light color temperature from 2700K (Warm) to 6500K (Cold).
- **Memory Function:** The light retains the last used setting.
- **Wall Switch Control:** If the remote is unresponsive, quickly pressing the wall switch can cycle between warm and cool white light.



Image 5.1: The lamp showcasing its RGB mood lighting capabilities in a room setting.



Image 5.2: Illustration of the adjustable color temperature range from warm to cold white light.

5.2. Bluetooth Speaker Function

The integrated Bluetooth speaker allows you to play audio from your smartphone or other Bluetooth-enabled devices.

1. **Enable Bluetooth:** Turn on Bluetooth on your smartphone or device.
2. **Pairing:** Search for available Bluetooth devices. The lamp will appear as "HOREVO" or a similar name. Select it to pair.
3. **Password:** If prompted for a password, enter **1111**.
4. **Play Music:** Once paired, you can play your favorite music through the lamp's speaker. The lights can change color with the rhythm of the music.



Image 5.3: The ceiling lamp in a bedroom setting, highlighting its Bluetooth music playback and remote control features.

5.3. Remote Control Usage

The remote control provides full access to all light and speaker functions.

- **Power On/Off:** Turn the light on or off.
- **Brightness Adjustment:** Increase or decrease light intensity.
- **Color Selection:** Cycle through RGB colors or select specific white light temperatures.
- **Music Controls:** Play/pause, skip tracks, and adjust speaker volume.
- **Timing Function:** Set a timer for the light to turn off.

Your browser does not support the video tag.

Video 5.1: Demonstration of the HOREVO ceiling light's remote control functions, including color changing and dimming.

6. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your HOREVO LED Ceiling Lamp.

- **Cleaning:** Ensure the power is off before cleaning. Wipe the fixture with a soft, dry, or slightly damp cloth. Do not use harsh chemicals, abrasive cleaners, or sprays directly on the light.
- **Inspection:** Periodically check the fixture for any loose connections or damage. If any issues are found, disconnect power and consult a qualified technician.
- **LEDs:** The LED chips are integrated and not user-replaceable.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power, loose wiring, faulty fixture.	Check circuit breaker. Verify wiring connections. If problem persists, contact support.
Remote control is unresponsive.	Remote battery low/dead, remote not paired, obstruction.	Replace remote batteries. Ensure clear line of sight to the lamp. Quickly press the wall switch to cycle light modes.
Bluetooth connection unstable or fails.	Device too far, interference, incorrect pairing.	Ensure your device is within range. Turn off and on Bluetooth on your device. Re-attempt pairing (password: 1111). Refer to the product's QA section on the detail page for further solutions.
Speaker sound quality is poor.	Bluetooth connection issue, audio source quality.	Ensure a stable Bluetooth connection. Test with different audio sources. Note that the speaker is designed for ambient sound, not high-fidelity audio.

8. SPECIFICATIONS

Brand	HOREVO
Model Number	X003
Color	Black
Material	Metal, Plastic
Style	Modern
Light Fixture Form	Close to Ceiling
Power Source	Corded Electric
Voltage	110 Volts
Wattage	24 watts

Light Source	LED
Light Color	RGB, White (2700K-6500K)
Brightness	1800 Lumens (Daylight White), 2120 Lumens (Max Output)
Control Method	Remote Control, Wall Switch
Connectivity Protocol	Bluetooth
Dimensions (L x W x H)	11.02"L x 11.02"W x 2.36"H
Item Weight	0.08 Ounces
Water Resistance Level	Waterproof (Note: Not recommended for sustained high humidity areas)
UPC	825665166997



Applications



Bathroom



Dining Room



Balcony



Living Room



Study



Bedroom

Image 8.1: Dimensions of the HOREVO LED Ceiling Lamp, highlighting its ultra-thin design.

9. WARRANTY AND SUPPORT

For warranty information or technical support, please refer to your purchase documentation or contact the seller directly through your order details on the platform where the product was purchased.

The manufacturer, HOREVO, is committed to providing quality products and assistance.