

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Arteck](#) /
- › [Arteck HB305-2 Universal Multi-Device Bluetooth Keyboard User Manual](#)

Arteck HB305-2

Arteck HB305-2 Universal Multi-Device Bluetooth Keyboard User Manual

Model: HB305-2 | Brand: Arteck

This manual provides comprehensive instructions for the setup, operation, and maintenance of your Arteck HB305-2 Bluetooth Keyboard, designed for seamless multi-device connectivity across various operating systems.

INTRODUCTION

The Arteck HB305-2 Universal Multi-Device Bluetooth Keyboard is an ultra-compact wireless solution designed for enhanced productivity across multiple platforms. It features the ability to connect to up to three devices simultaneously, allowing for quick switching with a single click. Its slim and lightweight design makes it highly portable, while the comfortable, quiet keystrokes ensure a pleasant typing experience. The keyboard is equipped with a long-lasting rechargeable battery, providing extended use between charges.

This manual will guide you through the essential steps to get the most out of your new keyboard, from initial setup to advanced features and troubleshooting.

PACKAGE CONTENTS

Please verify that all items are present in your package:

- Arteck Multi-Device Bluetooth Keyboard
- USB-C charging cable
- Welcome guide (this manual)

SETUP GUIDE

1. Initial Charge

Before first use, fully charge your Arteck HB305-2 keyboard using the provided USB-C charging cable.

Connect the USB-C end to the keyboard's charging port (located on the back edge) and the USB-A end to a standard USB power adapter or computer USB port. The charging indicator light will show charging status (refer to the manual's indicator section for details).



Figure 1: Rear view of the keyboard highlighting the USB-C charging port.

2. Power On

Locate the ON/OFF switch on the top right side of the keyboard. Slide the switch to the "ON" position. The power indicator light will illuminate briefly.

3. Pairing with Devices (Up to 3 Devices)

Your Arteck HB305-2 keyboard can connect to three different Bluetooth-enabled devices. Follow these steps for each device:

1. Press and hold the **Fn** key, then press one of the Bluetooth channel keys **F1**, **F2**, or **F3** for 3-5 seconds until the corresponding Bluetooth indicator light (green for F1, blue for F2, red for F3) starts blinking rapidly. This indicates the keyboard is in pairing mode.
2. On your device (computer, tablet, smartphone), go to Bluetooth settings.
3. Search for available Bluetooth devices. You should see "Arteck HB305-2" or a similar name appear in the list.
4. Select "Arteck HB305-2" to initiate the connection. Your device may prompt you to enter a pairing code displayed on its screen. Type this code on the Arteck keyboard and press **Enter**.
5. Once successfully paired, the Bluetooth indicator light on the keyboard will stop blinking and remain solid for a few seconds before turning off, indicating a successful connection.
6. Repeat these steps for up to two additional devices, assigning each to a different F-key channel (F1, F2, or F3).

Connecting to 3 Devices At the Same Time

Pairing by Long Pressing At The First Time
Switch Between Devices With A Single Clicking



Figure 2: Connecting the keyboard to multiple devices simultaneously.

OPERATING INSTRUCTIONS

Switching Between Devices

To switch between your paired devices, simply press the **Fn** key along with the corresponding F-key channel (**F1**, **F2**, or **F3**) for the desired device. The keyboard will automatically connect to the selected device.

Function Keys and Hotkeys

The Artek HB305-2 keyboard includes system-specific function keys and media hotkeys for various operating systems (Windows, iOS, iPad OS, Android, Mac OS). These keys provide quick access to common functions such as volume control, playback, screen brightness, and more.

- **Fn + F1-F3:** Switch between paired Bluetooth devices.
- **Fn + F4-F7:** Media control (Previous Track, Play/Pause, Next Track, Mute).
- **Fn + F8-F10:** Volume control (Volume Down, Volume Up, Search).
- **Fn + F11:** Print Screen.
- **Fn + F12:** Lock Screen.
- **Caps Lock Indicator:** A blue light above the 'A' key indicates Caps Lock is active.

- **Num Lock Indicator:** A blue light above the 'NumLK' key indicates Num Lock is active.



Figure 3: Overview of keyboard layout and function keys.

Comfortable Keystrokes

The keyboard utilizes a scissor-switch mechanism, providing comfortable, quiet, and responsive keystrokes. This design ensures equal pressure distribution and a satisfying tactile feel for extended typing sessions.



COMFORTABLE KEYSTROKES

X structure, exert equal pressure and lower keystrokes in comparison with the clickety keyboard.

MAINTENANCE

To ensure the longevity and optimal performance of your Artek HB305-2 keyboard, follow these maintenance guidelines:

- **Cleaning:** Use a soft, lint-free cloth slightly dampened with water or a mild cleaning solution to wipe the surface of the keyboard. Avoid excessive moisture. For cleaning between keys, use compressed air.
- **Storage:** When not in use for extended periods, store the keyboard in a cool, dry place away from direct sunlight and extreme temperatures.
- **Battery Care:** Avoid completely draining the battery frequently. Recharge the keyboard when the low battery indicator appears. For long-term storage, charge the battery to about 50% to prolong its lifespan.
- **Avoid Spills:** Keep liquids away from the keyboard to prevent damage to internal components.

TROUBLESHOOTING

If you encounter issues with your Artek HB305-2 keyboard, try the following solutions:

- **Keyboard not connecting/pairing:**
 - Ensure the keyboard is powered on and fully charged.
 - Make sure Bluetooth is enabled on your device.
 - Ensure the keyboard is in pairing mode (Bluetooth indicator blinking).
 - Move the keyboard closer to your device.
 - Forget the device from your device's Bluetooth settings and attempt to re-pair.
 - Restart both the keyboard (turn off and on) and your device.
- **Keys not responding:**
 - Check battery level and recharge if necessary.
 - Ensure the keyboard is connected to the correct device channel (F1, F2, or F3).
 - Clean around the affected keys to remove any debris.
- **Lag or delayed input:**
 - Reduce interference by moving away from other wireless devices (Wi-Fi routers, cordless phones).
 - Ensure your device's Bluetooth drivers are up to date.

SPECIFICATIONS

Feature	Detail
Product Dimensions	14.3 x 4.5 x 0.24 inches (36.2 x 11.6 x 0.6 cm)
Item Weight	1.12 pounds (14.3 oz / 406 g)
Manufacturer	Arteck
Item Model Number	HB305-2
Batteries	1 Lithium Ion battery required (built-in rechargeable)
Battery Life	Up to 6 months (based on 2 hours non-stop use per day)
Connectivity Technology	Bluetooth Multi Device
Compatible Devices	Computer, Laptop, Tablet, Smartphone (Windows, iOS, iPad OS, Android, Mac OS)
Keyboard Description	Wireless
Special Feature	Multi Device, Rechargeable
Color	Black
Number of Keys	97
Style	Modern
Included Components	USB-C Charging Cable



Figure 5: Physical dimensions and weight of the keyboard.

WARRANTY AND SUPPORT

The Artek HB305-2 Universal Multi-Device Bluetooth Keyboard comes with a **24-month warranty** from the date of purchase. This warranty covers manufacturing defects and issues arising from normal use.

If you have questions regarding the product, received a defective product, or the product is not as expected, please feel free to contact Artek customer service.

To claim warranty support, please send your order number to the following email address:

support@artek.com

For additional information and resources, you may visit the official Artek Store on Amazon.

[Visit the Artek Store](#)