

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [PrancyBt](#) /

› [PrancyBt Wireless Bluetooth Headset User Manual](#)

## PrancyBt KH122M



# PrancyBt Wireless Bluetooth Headset User Manual

Model: KH122M

## 1. PRODUCT OVERVIEW

---

The PrancyBt KH122M Wireless Bluetooth Headset is designed for clear communication and enhanced productivity in various environments, from office work to mobile use. Featuring advanced Bluetooth 5.2 technology and an AI noise-cancelling microphone, it ensures stable connections and crystal-clear audio. The headset offers versatile connectivity options, including direct Bluetooth pairing and a plug-and-play USB dongle for seamless integration with PCs and other devices.

Its user-friendly design includes a physical on/off toggle switch for instant pairing, an easy-access mute button, and a convenient charging base with smart storage for the USB adapter. With up to 40 hours of talk time, the PrancyBt KH122M is built to support long work sessions and provide reliable performance.

## 2. PACKAGE CONTENTS

---

- 1 x PrancyBt Wireless Bluetooth Headset with Microphone
- 1 x USB Dongle
- 1 x Type-C Charging Cable
- 1 x Charging Station
- 1 x User Manual

## 3. PRODUCT DIAGRAM

---

Familiarize yourself with the components of your PrancyBt headset and charging base.



Image: The PrancyBt wireless Bluetooth headset, featuring an adjustable microphone, is shown resting on its sleek charging base. A compact USB dongle is displayed next to the base, highlighting the complete package.

1. **Headband:** Adjustable for comfortable fit.
2. **Ear Cup:** Houses audio drivers and controls.

3. **Microphone Boom:** Rotates 270° for left or right side use.
4. **On/Off Toggle Switch:** Physical switch for power and instant pairing.
5. **Mute Button:** Dedicated button for microphone mute.
6. **Volume Controls:** Buttons for adjusting audio volume.
7. **USB-C Charging Port:** Located on the headset for direct charging.
8. **Charging Base:** Dock for convenient charging and storage.
9. **USB Dongle Storage Slot:** Integrated into the charging base.
10. **USB Dongle:** For plug-and-play connectivity with PCs.

## 4. SETUP

---

### 4.1. Initial Pairing (Bluetooth)

The headset features an automatic one-step pairing process.

# Super Easy Setup

Simply toggle the switch on  
and it will connect to your device immediately.



Image: A user holds the PrancyBt headset while a smartphone screen in the background displays a "Connect successful" message, illustrating the easy setup process.

1. Ensure the headset is charged.
2. Locate the physical **On/Off toggle switch** on the headset.
3. Slide the switch to the **"On"** position. The headset will automatically enter pairing mode or reconnect to the last paired device.
4. On your device (smartphone, tablet, etc.), enable Bluetooth and search for "PrancyBt KH122M" in the list of available devices.
5. Select the headset to connect. Once connected, a voice prompt will confirm the successful pairing.

## 4.2. Connecting via USB Dongle (Plug & Play)

For computers without Bluetooth or for enhanced functionality like PC mute control, use the included USB dongle.



## Plug in & Go

No driver needed, no complicated setup necessary,  
and you're ready to go.

Image: A person wears the PrancyBt headset while working at a desk with a desktop computer, illustrating the plug-and-play convenience of connecting the headset via its USB dongle.

1. Retrieve the USB dongle from its storage slot in the charging base.
2. Plug the USB dongle into an available USB port on your computer.
3. Slide the headset's **On/Off toggle switch** to the "On" position.
4. The headset will automatically connect to the USB dongle. No driver installation is typically required.
5. Ensure the PrancyBt headset is selected as the audio input and output device in your computer's sound settings.

## 5. OPERATING INSTRUCTIONS

---

### 5.1. Power On/Off

- **Power On:** Slide the **On/Off toggle switch** to the "On" position.
- **Power Off:** Slide the **On/Off toggle switch** to the "Off" position.

## 5.2. Volume Control

- Use the **Volume Up (+)** and **Volume Down (-)** buttons on the ear cup to adjust the listening volume.

## 5.3. Mute Function

The dedicated mute button allows for quick microphone muting.



# Support Mute on Phones & PC

Big and easy to find mute button allows you to mute the mic quickly.  
With USB dongle, you'll love you can be away from your PC and still mute yourself!

Image: A woman wearing the PrancyBt headset is shown with a child next to her, both looking at a laptop. An icon indicating "Mute" is overlaid, emphasizing the headset's mute capability for calls on phones and PCs.

- **Mute Microphone:** Press the **Mute Button** once during a call. A voice prompt will announce "mute on".
- **Unmute Microphone:** Press the **Mute Button** again. A voice prompt will announce "mute off".
- *Note:* When connected via the USB dongle, the mute function is supported across major UC platforms like Skype, Zoom, and Microsoft Teams.

## 5.4. Call Management

- **Answer/End Call:** Press the **Multi-function Button** (usually the main button on the ear cup) once.

- **Reject Call:** Press and hold the **Multi-function Button** for 2 seconds.
- **Redial Last Number:** Double-press the **Multi-function Button**.

## 5.5. AI Noise-Cancelling Microphone

The integrated AI noise-cancelling microphone targets your voice and filters out external noise for clear communication.



# AI Noise Cancelling Mic

Targets your voice and filters out external noise to provide a clear call experience wherever.

Image: A man wearing the PrancyBt headset is shown in an office environment, participating in a video conference call on a large monitor, illustrating the effectiveness of the AI noise-cancelling microphone in professional settings.

- Ensure the microphone boom is positioned close to your mouth for optimal voice pickup.
- The microphone can be rotated 270 degrees to be worn on either the left or right side.

## 6. CHARGING

The PrancyBt headset offers two convenient charging methods.



Image: A hand is shown placing the PrancyBt headset onto its charging base, which features a blue indicator light, demonstrating the ease of charging and storage.

## 6.1. Charging with the Charging Base

1. Connect the Type-C charging cable to the charging base and then to a USB power source (e.g., computer USB port, wall adapter).
2. Place the headset onto the charging base, ensuring the charging contacts align.
3. The indicator light on the base will show the charging status.

## 6.2. Direct Charging (USB-C)

1. Connect the Type-C charging cable directly to the USB-C port on the headset.
2. Connect the other end of the cable to a USB power source.
3. The headset's indicator light will show the charging status.

A full charge takes approximately 2 hours and provides up to 40 hours of talk time.

## 7. MAINTENANCE

---

- **Cleaning:** Use a soft, dry cloth to clean the headset and charging base. Do not use abrasive cleaners or solvents.
- **Storage:** When not in use, store the headset on its charging base to keep it charged and organized. Store in a cool, dry place away from extreme temperatures.
- **Battery Care:** To prolong battery life, avoid fully discharging the headset frequently. Charge it regularly, even if not in constant use.
- **USB Dongle Storage:** Always store the USB dongle in its dedicated slot on the charging base to prevent loss.

## 8. TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Headset does not power on.	Low battery.	Charge the headset for at least 30 minutes.
Cannot pair with device.	Bluetooth not enabled on device; headset not in pairing mode; interference.	Ensure Bluetooth is on. Slide headset switch to "On" to enter pairing. Move closer to device. Turn off other Bluetooth devices.
Unstable Bluetooth connection.	Out of range; interference; outdated Bluetooth driver (PC).	Stay within 10m (33ft) range. Avoid obstacles. Update your computer's Bluetooth driver.
Microphone not working.	Microphone muted; incorrect audio input selected.	Press the mute button to unmute. Check your device's sound settings to ensure PrancyBt headset is selected as input.
Mute button not working on PC.	Not connected via USB dongle; software incompatibility.	Ensure you are connected via the USB dongle for PC mute control. Verify compatibility with your specific UC software.
No sound from headset.	Volume too low; incorrect audio output selected.	Increase headset and device volume. Check your device's sound settings to ensure PrancyBt headset is selected as output.

## 9. SPECIFICATIONS

---

<b>Model Number</b>	KH122M
<b>Brand</b>	PrancyBt
<b>Connectivity Technology</b>	Wireless (Bluetooth 5.2)
<b>Wireless Range</b>	Up to 10 meters (33 feet)
<b>Battery Type</b>	Lithium-Cobalt (Rechargeable)
<b>Charging Time</b>	Approx. 2 hours
<b>Talk Time</b>	Up to 40 hours
<b>Microphone</b>	AI Noise-Cancelling, 270° Rotatable

<b>Special Features</b>	Dedicated Mute Button, USB Bluetooth Dongle, Physical On/Off Toggle Switch, Flexible Ear Cushion, Lightweight Design
<b>Compatible Devices</b>	Mobile phones, Computers, iPad, Smart TV, most Bluetooth-enabled devices

## 10. WARRANTY AND SUPPORT

---

PrancyBt products are manufactured to the highest quality standards. For warranty information, technical support, or customer service inquiries, please refer to the contact details provided with your purchase or visit the official PrancyBt website.

Please retain your proof of purchase for warranty claims.

