

[Manuals.plus](#) /

› [ODK](#) /

› ODK 63-inch Gaming Desk User Manual

ODK ODK 63 inch Computer Desk (0b)

ODK 63-inch Gaming Desk User Manual

Model: ODK 63 inch Computer Desk (0b)

Brand: ODK

PRODUCT OVERVIEW

The ODK 63-inch Gaming Desk is a versatile and robust solution designed for both gaming and home office environments. It features integrated power outlets, dynamic LED lighting, a spacious monitor stand, and convenient storage shelves to keep your workspace organized and efficient.



Image: The ODK 63-inch Gaming Desk in a gaming setup, showcasing its monitor stand, LED lighting, and overall design.

IMPORTANT SAFETY INFORMATION

WARNING:

- Do not exceed a weight limit of 100kg (approximately 220 lbs) on the desk.
- Properly secure the desk to prevent tipping or collapse during and after assembly.

SETUP AND ASSEMBLY

The ODK Gaming Desk is designed for easy assembly, typically taking around 30 minutes. All necessary tools and instructions are included in the package. Follow the step-by-step guide provided with your product for detailed assembly instructions.

Key Components:

- **Long Monitor Stand:** Accommodates two monitors or laptops, providing an ergonomic viewing height.
- **Recessed Power Strip:** Features 3 AC outlets (120V/12A) and 2 USB ports (5V/2A) with a 6.6-foot power cord for convenient device charging.
- **RGB LED Lights:** Built-in LED lighting with 10 dynamic modes and 10 color changes to enhance your gaming or work ambiance.
- **Reversible PC Stand Shelves:** Offers flexible storage options for your PC tower and other accessories.
- **Headphone Hook:** Keeps your headphones within easy reach.
- **Durable Construction:** Constructed with a premium metal frame and thick particleboard for stability and durability, including an additional X cross bar for improved stability.



Image: Detailed dimensions of the ODK 63-inch desk, highlighting the long monitor stand and side shelves.



Image: View of the desk's sturdy construction with an X-bar for stability and the versatile side storage shelves.

Your browser does not support the video tag.

Video: An overview of the ODK Gaming Desk, showcasing its power outlets, LED strips, and various features. (Source: Casaottima Store)

Your browser does not support the video tag.

Video: A demonstration of the ODK Computer Desk with its monitor stand and storage shelves. (Source: Casaottima Store)

OPERATING INSTRUCTIONS

LED Lighting Control:

The desk features built-in RGB LED lights with multiple modes and colors. Use the integrated control panel to adjust the lighting to your preference.

- **Static Color Button (C):** Press once to switch to static color mode. Each press changes the color.
- **Dynamic Mode Button (M):** Press once to switch to dynamic mode effect. Each press changes the

dynamic mode. Press and hold for 3 seconds to switch to demo mode, where the strip automatically cycles through various dynamic modes.

- **Speed & Brightness and Power Button (S/B / Power):**

- In static mode, press to adjust brightness. Each press switches to a different brightness level.
- In dynamic mode, press to adjust dynamic mode speed. Each press changes the speed.
- Press and hold to shut down when the strip is on. Press to turn on when the strip is off.

The product has a power-off memory function; the strip can restore the color, brightness, and mode in the next power-on.



Image: Detailed instructions for controlling the RGB LED lights, showing the function of each button on the control panel.

Power Outlets:

The integrated power strip provides convenient access to power for your devices.

- Plug your devices into the 3 AC outlets (120V/12A).
- Use the 2 USB ports (5V/2A) to charge compatible USB devices.



Recessed Power Stripe

With 3 outlets & 2 USB ports



120V/12A
3AC Outlets



6.6-Foot
Power Cord



5V/2A
2 USB Ports

Image: A close-up view of the recessed power strip on the desk, showing the 3 AC outlets and 2 USB ports.

MAINTENANCE

To ensure the longevity and appearance of your ODK Gaming Desk, follow these simple maintenance guidelines:

- **Cleaning:** Wipe the desk surfaces with a dry cloth to remove dust and spills. Avoid abrasive cleaners or harsh chemicals that may damage the finish.
- **Stability Check:** Periodically check all screws and connections to ensure they are tight and secure. Retighten if necessary.
- **Weight Distribution:** Distribute weight evenly across the desk surface and shelves to prevent strain on any single point.

TROUBLESHOOTING

If you encounter any issues with your ODK Gaming Desk, please refer to the following common solutions:

- **Desk Wobbles:** Ensure all assembly screws are fully tightened. Check that the desk is placed on a flat, even surface. Adjust leveling feet if present.

- **LED Lights Not Working:** Verify that the power cord for the LED lights is securely plugged into both the desk and a working power outlet. Check the control panel settings (power, brightness, mode).
- **Power Outlets Not Functioning:** Confirm the desk's main power cord is securely plugged into a live wall outlet. Test the outlet with another device to ensure it is functional.

For issues not covered here, please contact ODK customer support.

SPECIFICATIONS

Feature	Detail
Brand	ODK
Model Name	ODK 63 inch Computer Desk
Model Number	0b
Product Dimensions	63"D x 21.6"W x 34"H
Color	Black
Style	Gaming
Base Material	Metal (feet Pad)
Top Material Type	Engineered Wood
Special Feature	LED Lights, Power Outlets, Monitor Stand, Storage Shelves
Item Weight	50 Pounds
Maximum Weight Recommendation	220 lbs (100kg)
Required Assembly	Yes
Recommended Number of People for Assembly	2

WARRANTY AND SUPPORT

ODK is committed to providing excellent customer service. For any quality problems, a fast refund or replacement is available.

- **Customer Service:** ODK offers 24-hour online professional pre-sale and after-sale service.
- **Returns:** Enjoy 30-day easy returns.

For support, please contact ODK directly through their official channels or the retailer where the product was purchased.

