

MARKLIFE P50

MARKLIFE P50 Label Maker Machine User Manual

Model: P50 | Brand: MARKLIFE

INTRODUCTION

This manual provides comprehensive instructions for the setup, operation, and maintenance of your MARKLIFE P50 Label Maker Machine. Please read this manual carefully before using the device to ensure proper functionality and longevity.

WHAT'S IN THE BOX

Upon unboxing, please verify that all components listed below are present:

- MARKLIFE P50 Label Maker Machine
- USB-C Charging Cable
- Label Tapes (3 rolls included):
 - 1.57" x 1.18" (40x30mm) White Gap Label
 - 2" x 2" (50x50mm) Circle Gap Label
 - 1.57" x 2.36" (40x60mm) White Gap Label



Image: The MARKLIFE P50 Label Maker Machine shown with three rolls of label tape of different sizes and shapes, demonstrating the variety included in the package.

SETUP

1. Label Paper Installation

1. Hold the sides of the label maker and gently lift up the paper cover to open the compartment.
2. Remove the paper roll holder from the paper bin.
3. Take out the left flap of the paper roll holder.
4. Place the label paper roll onto the right movable plate of the holder.
5. Insert the left bezel back onto the holder, ensuring the arrows on both baffles are uniformly facing forward.
6. Place the assembled paper roll holder back into the paper bin. Ensure the yellow label on the paper roll is on the right side and the print side of the label paper is facing down.

7. Drag a section of the label paper to the paper outlet.
8. Press down with both hands to close the paper cover firmly.
9. Long press the power switch to start the device. Double-click the switch key to perform a test print.
10. The label paper can be torn down and to the right near the paper outlet after printing.

Your browser does not support the video tag.

Video: A detailed tutorial demonstrating the process of installing label paper into the MARKLIFE P50 Label Maker, including opening the cover, assembling the paper roll holder, inserting the paper, and closing the cover.

2. App Download and Login

1. Download the "Marklife" app from your device's app store (available for Android and iOS).
2. Open the app. You can choose to log in using your email, a third-party app (like Facebook), or proceed as a guest.

3. Bluetooth Connection

1. In the Marklife app, click on the "UNLINK" or "Not connected" icon, typically located in the top left corner.
2. Allow Bluetooth to be turned on when prompted by the app to connect to the printer.
3. The app will search for nearby print devices. Once your P50 printer appears in the list (e.g., "P50S_..."), click "UNLINK" or "Connect" next to it.
4. If the circle icon next to your printer name turns green, the printer is successfully connected.

OPERATING INSTRUCTIONS

1. Creating a Label

1. From the main app screen, click "Create label".
2. Select the label stock type: "Continuous Label" if you are using continuous paper, or "Gap Label" if you are using pre-cut labels with gaps.
3. Click "Quick to select a size" and choose the same size as the label stock loaded into your label machine. Confirm your selection.

2. Editing Text

1. Double-click the text box on the label editor screen to enter the text.
2. Enter the desired text you want to print.
3. Click "Text layout" to adjust font size, spacing, and line spacing. Swipe left or right on the sliders to adjust these parameters.
4. Use the "B" icon to bold the text, the "U" icon to underline, and the "I" icon to italicize.
5. Click the vertical text icon (A with an arrow pointing up) to print text vertically.
6. Click "Font Options" to change the style of the font.
7. To move the text box, click "Text" and drag it to the desired position.

8. Pinch the text box to change the size of the label stock preview.
9. Click and move the double-headed arrow on the text box to increase its length.

3. Printing

1. After editing, click "Print".
2. Adjust the "Print Density" slider to change the clarity of the font.
3. Use the minus (-) and plus (+) buttons next to "Print Copy" to increase or decrease the number of copies.
4. Click "Print Now" to start printing. You can cancel printing if needed.



Image: Various applications of the MARKLIFE P50 Label Maker, including price tags for clothing, labels for handmade soaps, and bakery item labels, showcasing its versatility for small businesses.



Image: Additional label examples, such as food identification labels for pork belly and homemade beverages, and a shipping address label on a package, highlighting practical uses.

MAINTENANCE

- **Cleaning the Print Head:** Regularly clean the thermal print head with an alcohol wipe to ensure clear and consistent print quality. Avoid touching the print head directly with your fingers.
- **Battery Care:** To prolong battery life, avoid fully discharging the device frequently. Charge it regularly, especially if it will be stored for an extended period.
- **Storage:** Store the label maker in a cool, dry place away from direct sunlight and extreme temperatures.
- **Use Approved Labels:** Only use thermal label paper specifically designed for the MARKLIFE P50 to prevent damage to the print head and ensure optimal performance.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Printer not turning on.	Low battery or power issue.	Charge the device using the provided USB-C cable. Ensure the charging indicator light is on.
Cannot connect via Bluetooth.	Bluetooth is off on the device or phone; app permission issues; printer not discoverable.	Ensure Bluetooth is enabled on your smartphone. Grant Bluetooth permissions to the Marklife app. Restart both the printer and your phone, then try connecting again.
Poor print quality (faint or unclear).	Low print density setting; dirty print head; incorrect label type.	Increase the print density in the app settings. Clean the print head. Ensure you are using thermal labels compatible with the P50.
Labels are not feeding correctly or getting stuck.	Improper label installation; label roll not aligned.	Re-install the label paper, ensuring it is properly seated in the paper roll holder and aligned. Make sure the paper cover is securely closed.
App crashes or freezes.	Software bug; insufficient phone memory.	Close and restart the Marklife app. Ensure your phone's operating system and the app are updated to the latest versions. Clear app cache if necessary.

SPECIFICATIONS

Feature	Detail
Brand	MARKLIFE
Model Number	P50
Printing Technology	Thermal
Printer Output	Monochrome (Black and White)
Connectivity Technology	Bluetooth, USB
Compatible Devices	Android, iOS, PC, Tablets
Maximum Media Size	2 inches (0.59"-2.24" width range)
Item Weight	6 ounces
Product Dimensions	4 x 3 x 2 inches





Feature	Detail
Special Feature	Lightweight, Portable
Battery	Built-in 1200mAh Battery

WARRANTY AND SUPPORT


For warranty information, technical support, or service inquiries, please refer to the official MARKLIFE website or contact their customer service directly. Keep your purchase receipt as proof of purchase for warranty claims. You can also find additional support and tutorials by visiting the MARKLIFE store on Amazon[MARKLIFE Amazon Store](#).

© 2023 MARKLIFE. All rights reserved.

Related Documents - P50

	P50 Label Printer User Manual Comprehensive user manual for the P50 Label Printer, covering setup, operation, app integration, printing, troubleshooting, and safety guidelines.
	Marklife P50 Label Printer User Manual Comprehensive user manual for the Marklife P50 Label Printer, covering setup, app installation, label creation, features, troubleshooting, and maintenance.
	P15 Label Printer User Manual User manual for the P15 Label Printer, covering initial setup, wireless connection via the Marklife app, label creation methods, replacing consumables, and safety precautions.
	MARKLIFE P50 MARKLIFE P50
<p>P50 Inkless Label Printer</p> <p>NO.1 Product Structure</p> <p>NO.2 Introduction to parameters</p> <p>NO.3 APP download</p> <p>NO.4 Install stickers</p> <p>NO.5 Connect the printer</p> <p>NO.6 Operation steps</p>	P50 Inkless Label Printer: User Guide and Setup Comprehensive guide to setting up and using the Marklife P50 Inkless Label Printer, including product structure, parameters, app connection, sticker installation, and operation steps.

**M1 Label Printer
User Manual**



[Marklife M1 Label Printer User Manual](#)

Comprehensive user manual for the Marklife M1 portable label printer, detailing setup, connection via Bluetooth, label loading, indicator light meanings, and app operation for creating and printing custom labels.