

[manuals.plus](#) /› [MARKLIFE](#) /› **MARKLIFE P50 Label Maker Machine Instruction Manual**

MARKLIFE P50

MARKLIFE P50 Label Maker Machine Instruction Manual

Model: P50 | Brand: MARKLIFE

1. INTRODUCTION

The MARKLIFE P50 is a compact and portable thermal label maker designed for a wide range of labeling needs, from small business organization to home use. Utilizing thermal printing technology, it requires no ink, offering a cost-effective and convenient labeling solution. This manual provides detailed instructions for setting up, operating, maintaining, and troubleshooting your P50 label maker.



Figure 1: MARKLIFE P50 Label Maker with included label rolls.

2. SETUP GUIDE

2.1 Unboxing and Initial Charge

Upon unboxing your MARKLIFE P50, ensure all components are present: the label maker, USB-C charging cable, and included label rolls. Before first use, fully charge the device using the provided USB-C cable. The charging port is located on the side of the device.

Portable and Long Battery Life



Figure 2: The P50 label maker is portable and features a built-in 1200mAh battery with Type-C charging.

2.2 Loading Label Rolls

To load a label roll:

1. Gently hold the sides of the label maker and lift the paper cover to open the compartment.
2. Remove the paper roll holder in the paper bin.
3. Separate the left flap from the holder.
4. Place the label paper roll onto the right movable plate, ensuring the print side faces down.
5. Re-insert the left flap in the direction of the arrow, ensuring both left and right baffles are uniformly facing forward.
6. Place the assembled roll holder back into the paper bin, ensuring the yellow label on the roll is on the indicated side.
7. Drag a section of the label paper to the paper outlet.
8. Press down with both hands to securely close the paper cover.

Your browser does not support the video tag.

Video 1: Detailed instructions on how to load label paper into the P50 label maker.

3 Rolls of Labels

Meet More Needs




Figure 3: The P50 comes with three rolls of labels to meet various needs.

2.3 App Download and Bluetooth Connection

The P50 label maker operates via a dedicated mobile application. It supports both iOS and Android devices.

1. Download the "Marklife" app from your device's app store.
2. Open the app. You can choose to log in via email, a third-party app, or as a guest.
3. Ensure Bluetooth is enabled on your mobile device.
4. In the app, click "UNLINK" or the connection icon to search for nearby print devices.
5. Select your P50 printer from the list (e.g., "P50S_..."). Once connected, the indicator in the app will turn green.

Your browser does not support the video tag.

Video 2: Guide on connecting the P50 label maker to a computer for printing.

P50 label printer supports

Mobile smart devices & PC devices



Figure 4: The P50 label printer supports both mobile smart devices and PC devices for versatile use.

3. OPERATING INSTRUCTIONS

3.1 Creating and Editing Labels

The Marklife app offers extensive customization options for your labels:

1. In the app, click "Create label".
2. Select the label stock type (Continuous Label or Gap Label) and confirm.
3. Choose the label size that matches your loaded paper (e.g., 40x30mm).
4. Double-click the text box to enter your desired content.
5. Use the "Text layout" and "Font Options" to customize:
 - Adjust font size by swiping left or right.
 - Modify spacing between characters.
 - Adjust line spacing for multi-line text.
 - Bold, underline, or italicize text.
 - Print vertical text.

- Change font style from a variety of options.

6. You can also add pictures, stickers, dates, Excel data, barcodes (e.g., [0123456789005](#)), and QR codes.
7. Adjust the size and position of elements on the label by pinching or dragging.

Your browser does not support the video tag.

Video 3: Comprehensive tutorial on operating the P50 label maker, including label creation and editing.

3.2 Printing Labels

Once your label design is complete:

1. Click the "Print" button in the app.
2. Adjust the print density for clarity (higher number for darker print).
3. Set the number of copies you wish to print.
4. Confirm print settings and initiate printing.



Figure 5: The P50 supports efficient batch printing, capable of printing 100 meters on a single charge.

3.3 Applications

The MARKLIFE P50 is versatile for various applications:

- **Retail & Small Business:** Create price tags, barcode labels (e.g., [6979005834542](#)), clothing labels, jewelry labels, and product identification.
- **Home & Office Organization:** Label food containers, spice jars, cosmetic bottles, cables, storage boxes, and files.
- **Personal Use:** Create custom labels for gifts, school supplies, or personal items.



Figure 6: Examples of labels for clothing, handmade soap, and bakery products.



Figure 7: Labels for food preparation, beverages, and shipping addresses.

Your browser does not support the video tag.

Video 4: Demonstration of the P50's capability to print labels from 12 to 50 mm wide.

4. MAINTENANCE

4.1 Cleaning the Print Head

To ensure optimal print quality, regularly clean the thermal print head. Use a soft, lint-free cloth lightly dampened with isopropyl alcohol. Gently wipe the print head surface. Allow it to dry completely before closing the cover.

4.2 Label Storage

Store label rolls in a cool, dry place away from direct sunlight and excessive heat to prevent degradation of the thermal coating and adhesive.

4.3 Battery Care

For long-term battery health, avoid completely draining the battery frequently. If storing the device for

an extended period, charge it to about 50% and recharge every few months.

5. TROUBLESHOOTING

5.1 Common Issues and Solutions

- **Poor Print Quality:**
 - Check print density settings in the app.
 - Clean the print head (refer to Maintenance section).
 - Ensure the label roll is inserted correctly with the print side facing down.
- **Paper Jams or Misfeeds:**
 - Ensure the label roll is properly seated and aligned within the paper bin.
 - Verify that the paper cover is securely closed.
 - Remove any jammed paper carefully.
- **Bluetooth Connection Issues:**
 - Ensure the P50 is powered on and within range of your device.
 - Restart the P50 and your mobile device.
 - Forget the device in your phone's Bluetooth settings and re-pair.
 - Ensure the Marklife app has Bluetooth permissions enabled.
- **Labels Sliding During Printing:**
 - Ensure the label roll holder's baffles are snug against the roll to prevent lateral movement.

For further assistance, refer to the "Help Center" within the Marklife app or contact customer support.

6. SPECIFICATIONS

Feature	Detail
Brand	MARKLIFE
Model Name	P50 LABEL PRINTER
Printing Technology	Thermal
Connectivity Technology	Bluetooth, USB
Printer Media Size Maximum	2 inches (0.59"-2.24" width range)
Printer Output	Monochrome (Black and White)
Item Weight	6 ounces
Product Dimensions	4"D x 3"W x 2"H
Battery	Built-in 1200mAh (Type-C Charging)



Figure 8: The P50 label printer is compatible with labels ranging from 0.59 to 2.24 inches in width.

7. WARRANTY AND SUPPORT

7.1 Warranty Information

The MARKLIFE P50 Label Maker comes with a limited warranty. Please refer to the product packaging or the official MARKLIFE website for specific warranty terms and conditions.

7.2 Customer Support

For technical support, product inquiries, or warranty claims, please contact MARKLIFE customer service through the following channels:

- **In-App Support:** Access the "Help Center" or "View tutorial video & Technical Support" section within the Marklife app.
- **Email:** Refer to the contact information provided in the app or on the product packaging.

- **Online:** Visit the official MARKLIFE store on Amazon:[MARKLIFE Store](#).

© 2023 MARKLIFE. All rights reserved.

Related Documents - P50

 P50 Label Printer User Manual	<p>P50 Label Printer User Manual</p> <p>Comprehensive user manual for the P50 Label Printer, covering setup, operation, app integration, printing, troubleshooting, and safety guidelines.</p>
 Marklife P50 Label Printer User Manual	<p>Marklife P50 Label Printer User Manual</p> <p>Comprehensive user manual for the Marklife P50 Label Printer, covering setup, app installation, label creation, features, troubleshooting, and maintenance.</p>
 P15 Label Printer Use Manual	<p>P15 Label Printer User Manual</p> <p>User manual for the P15 Label Printer, covering initial setup, wireless connection via the Marklife app, label creation methods, replacing consumables, and safety precautions.</p>
 MARKLIFE P50	<p>MARKLIFE P50</p> <p>MARKLIFE P50</p>
<small>P50 Inkless Label Printer</small> NO.1 Product Structure NO.2 Introduction to parameters NO.3 APP download NO.4 Install stickers NO.5 Connect the printer NO.6 Operation steps	<p>P50 Inkless Label Printer: User Guide and Setup</p> <p>Comprehensive guide to setting up and using the Marklife P50 Inkless Label Printer, including product structure, parameters, app connection, sticker installation, and operation steps.</p>
<p>M1 Label Printer User Manual</p> 	<p>Marklife M1 Label Printer User Manual</p> <p>Comprehensive user manual for the Marklife M1 portable label printer, detailing setup, connection via Bluetooth, label loading, indicator light meanings, and app operation for creating and printing custom labels.</p>