

Petbank BlackCY-009

Petbank Automatic Fish Feeder User Manual

Brand: Petbank | **Model:** BlackCY-009

1. INTRODUCTION

The Petbank Automatic Fish Feeder is designed to provide convenient and reliable feeding for your aquarium fish and turtles. Featuring a USB-rechargeable battery, LCD screen, and customizable scheduling, it ensures your aquatic pets are fed even when you are away. This manual provides detailed instructions for setup, operation, and maintenance.

Key Features:

- **Smart Interval Mode:** Easily set feeding intervals (8, 12, 24, or 48 hours).
- **USB-Powered & Long-Lasting:** Rechargeable battery lasts 3-6 months on a single charge.
- **Customized Feeding Schedule:** Program up to 4 feeding times per day with 1-3 spins per session.
- **Large Capacity & Adjustable Mount:** 200ml container for various feed types, with adjustable slider for portion control.
- **Two Flexible Mounting Options:** Clamp for tank rim or double-sided sticker for tank lid.

2. PRODUCT COMPONENTS

The Petbank Automatic Fish Feeder package includes the following:

- Automatic Fish Feeder Unit (Model: CY-009)
- Adjustable Clamp Base for tank mounting
- Double-sided Sticker for lid mounting
- USB Charging Cable



Image: Petbank Automatic Fish Feeder unit with its adjustable clamp base and USB charging cable.



Petbank is a brand that specializes in pet-related items.

We prioritize users and pets by developing products to fulfill their needs with cutting-edge technology and innovation.

Thus every pet owner can provide the finest care for pets, who because of your pampering - live happily ever after.

Image: Detailed diagram showing the adjustable feeding cap, loading sliding cover, rotatable base, LCD display, control buttons (MANUAL, SET, Up, Down, Power), and charging interface.

3. SETUP AND INSTALLATION

Before first use, fully charge the feeder using the provided USB cable. It takes 3-4 hours to fully charge and can last 3-6 months.

3.1 Filling the Food Container

1. Slide open the loading cover on the top of the feeder.
2. Fill the 200ml capacity container with your desired fish food (pellets, granules, flakes, powders).
3. Close the loading cover securely.
4. Adjust the feeding slider to control the amount of food dispensed per rotation.



Image: A hand pouring fish food into the feeder's transparent container.



Image: A hand adjusting the feeding slider on the feeder to control food portion.

3.2 Mounting Options

Choose one of the following methods to install your feeder:

Method 1: Using the Adjustable Clamp Base (for tank walls $\leq 24\text{mm}$)

1. Attach the feeder to the adjustable clamp base.
2. Position the clamp on the rim of your aquarium tank.
3. Tighten the screw on the clamp until the feeder is securely fixed. The base allows for 360° rotation for optimal positioning.

Method 2: Using the Double-Sided Sticker (for tank lids)

1. Peel off the protective film from one side of the double-sided sticker.
2. Attach the sticker firmly to the bottom of the feeder unit.
3. Peel off the remaining protective film.
4. Adhere the feeder to a clean, dry surface on your tank's lid, ensuring it is positioned correctly over the feeding opening.

Easy to Install



Method 1

Fix it to the tank glass $\leq 24\text{mm}$ with adjustable base



Method 2

Attach it to tank top cover with the double-side sticker

Image: The Petbank feeder mounted on the edge of an aquarium using the adjustable clamp base.

Smart Interval Feeding Mode

Press the "▲" and "▼" buttons at the same time to get the interval setting



Image: The Petbank feeder attached to the top cover of an aquarium using a double-sided sticker.

Video: Official demonstration on how to install the automatic fish feeder using both the clamp and sticker methods.

4. OPERATING INSTRUCTIONS

4.1 Power On/Off

Long press the power button () for 3 seconds to turn the feeder on or off.

4.2 Clock Setting

1. Long press the **SET** button for 3 seconds. The hour/minute numbers will flash.
2. Press the ▲ or ▼ buttons to adjust the hour and minute.
3. Press **SET** again to save the clock settings and enter the feeding setting mode.

4.3 Customized Feeding Schedule

You can program up to 4 feeding times per day and adjust the number of rotations (1-3) for each feeding.

1. After setting the clock, the hour/minute numbers for the first feeding time will flash. Press▲ or ▼ to adjust the desired feeding time.
2. Press **SET** to confirm the time. The feeding circle number (1, 2, or 3) will flash.
3. Press ▲ or ▼ to adjust the number of feeding circles (rotations).
4. Press **SET** to save this feeding setting.
5. To set additional feeding times (up to 4), repeat steps 1-4. If you do not wish to set more times, press the **MANUAL** button to save the current settings and exit.

Method 1



Fix it to the tank glass ≤ 24mm with adjustable base

Method 2



Attach it to tank top cover with the double-side sticker

Image: Visual guide for setting the clock and programming feeding times and circles on the feeder's LCD display.

4.4 Smart Interval Feeding Mode

This mode allows you to set automatic feeding at fixed intervals.

1. Press the ▲ and ▼ buttons simultaneously to enter the interval setting mode.
2. Use the ▲ or ▼ buttons to select the desired interval: 8 hours, 12 hours, 24 hours, or 48 hours.
3. The feeder will automatically spin once for each feeding cycle at the selected interval.
4. To exit this mode, press the ▲ and ▼ buttons simultaneously again.

USB Rechargeable

It takes 3-4 hours to fully charge and lasts 3-6 months



360° Rotatable Base

Image: The feeder's display showing options for 8H, 12H, 24H, and 48H smart interval feeding modes.

4.5 Manual Feeding

For immediate feeding, simply press the **MANUAL** button. The feeder will dispense food once.

Video: Official guide demonstrating the multifunctional operation process, including setting time, customized schedules, and manual feeding.

5. MAINTENANCE

5.1 Cleaning

The feeder's food container and dispensing mechanism should be cleaned regularly to prevent food buildup and ensure proper operation. The manufacturer recommends **Hand Wash Only** for cleaning the feeder components. Ensure the unit is completely dry before refilling with food.

5.2 Charging

The feeder is USB-rechargeable. Connect the provided USB cable to the charging port on the feeder and a compatible USB power source. A full charge takes approximately 3-4 hours and provides 3-6 months of continuous use. The LCD display shows the battery level.

No More Worries About Your Fish !



Vacation



On Business



Gatherings



Oversleep

Image: The Petbank feeder connected to a USB charging cable, highlighting its rechargeable feature.

6. TROUBLESHOOTING

Here are some common issues and their potential solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Problem	Possible Cause	Solution
Feeder not dispensing food.	Food container empty; food jammed; dispensing slider closed; low battery.	Refill food; clear any blockages; adjust dispensing slider; charge the feeder.
Display is blank or not responding.	Battery is depleted.	Connect the feeder to the USB charger and allow it to charge fully.
Incorrect feeding times or intervals.	Settings were not saved correctly or were accidentally changed.	Review and re-program the clock and feeding schedules as per Section 4.
Battery life is shorter than expected.	Frequent manual feeding; extreme temperatures; aging battery.	Reduce manual feeding; operate in moderate temperatures; consider keeping it plugged in if battery degradation is significant.

6.1 How to Reset

To delete all settings and reset the feeder to its default state, long press the ▼ button for 5 seconds.

7. SPECIFICATIONS

- **Model Name:** ff01
- **Item Model Number:** BlackCY-009
- **Color:** Black
- **Material:** Plastic
- **Product Dimensions:** 6.5 x 4.72 x 3.46 inches
- **Item Weight:** 10.2 ounces (0.29 Kilograms)
- **Food Container Capacity:** 200ml
- **Power Source:** USB Rechargeable
- **Battery Life:** 3-6 months (after full charge)
- **Feeding Schedule:** Up to 4 times/day, 1-3 rotations/feeding
- **Interval Modes:** 8H, 12H, 24H, 48H
- **Target Species:** Fish, Turtle
- **Care Instructions:** Hand Wash Only
- **Manufacturer:** Petbank
- **Country of Origin:** China
- **Date First Available:** March 28, 2023

8. WARRANTY INFORMATION

The provided information indicates a warranty description of "1". For detailed warranty terms, conditions, and duration, please refer to the official product documentation included with your purchase or contact Petbank

customer support directly.

9. SUPPORT AND CONTACT

For further assistance, technical support, or inquiries regarding your Petbank Automatic Fish Feeder, please refer to the following resources:

- **User Guide (PDF):** A comprehensive user guide is available for download at <https://m.media-amazon.com/images/I/91fBTdNwxBL.pdf>.
- **Manufacturer Website:** Visit the official Petbank website for product updates, FAQs, and contact information.
- **Customer Service:** If you purchased this product from an online retailer, you may also contact their customer service for support.

© 2023 Petbank. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question