

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

> [Amorho](#) /

> [Amorho LED Bathroom Mirror User Manual](#)

## Amorho 4036

# Amorho LED Bathroom Mirror User Manual

Model: 4036

## INTRODUCTION

---

The Amorho 40" x 36" LED Bathroom Mirror is designed to enhance your bathroom experience with its advanced features and elegant design. This mirror incorporates both front and backlit LED lighting, stepless dimming, anti-fog functionality, and a durable shatter-proof construction. Amorho specializes in the research, development, design, production, and sales of high-quality bathroom mirrors, ensuring a complete and scientific quality management system. Our commitment is to provide innovative products that create a wonderful atmosphere for your home.

## SAFETY INFORMATION

---

**⚠ WARNING: Ensure proper wall mounting to avoid hazards from falling or improperly secured mirror.**

- Always disconnect power before installation or maintenance.
- Installation should be performed by a qualified electrician if hard-wiring is chosen.
- Do not expose the mirror to excessive moisture or direct water spray.
- Keep out of reach of children.

## PRODUCT FEATURES

---

- **Double Bright Lights & Black Frame:** Features built-in LED strip lights for both front and backlit illumination, providing enhanced brightness. The mirror is encased in a matte black aluminum frame for a delicate finish.
- **Smart Anti-Fog Function:** Equipped with a defogger that activates automatically upon power-on and turns off after 1 hour, ensuring a clear reflection even in steamy environments.
- **Adjustable Color Temperature & Brightness:** Easily switch between three color temperatures (3000K Warm White, 4000K Neutral Light, 6000K Cold White) and adjust brightness from 10% to 100% using the three touch buttons.
- **Memory Function:** The mirror remembers your last light settings (color temperature and brightness) for convenience upon next activation.
- **Shatterproof & Durable Design:** Constructed from 5MM tempered glass, designed to resist breakage and prevent shattering into sharp pieces if impacted. An epoxy coat provides corrosion resistance for long-term durability.

- **Versatile Installation:** Supports both horizontal and vertical mounting orientations. Can be connected to the power supply via plug-in or hard-wired connection.



Figure 1: Overview of key features including vertical/horizontal installation, wall switch compatibility, touch sensor, LED brightness, brightness memory, anti-fog, 3 color options, and ETL certification.



Aluminum Frame+Front Light+Backlit



Only Front Light

Other's



Only BackLit

Figure 8: Comparison showing the superior illumination of Amorho's mirror with both front and backlit LEDs versus mirrors with only front or only backlit illumination.

## Our Tempered Glass

5MM shatter-proof glass,  
safer to use, without splashing.



## Other's Ordinary Glass

Very thin, explosive,  
easy to hurt hands



Figure 9: Demonstrates the shatter-proof safety of Amorho's 5MM tempered glass compared to ordinary glass that can easily break into sharp pieces.

## SETUP AND INSTALLATION

---

### Package Contents

- Amorho LED Bathroom Mirror
- Mounting Bracket
- Screws and Wall Anchors
- User Manual (this document)

### Installation Steps

1. **Prepare the Wall:** Choose a suitable location on the wall, ensuring it is structurally sound and can support the mirror's weight. Mark the desired height and center point for the mirror.
2. **Mounting Bracket Installation:** Use the included mounting bracket as a template to mark drilling points on the wall.

Drill holes and insert wall anchors if necessary. Securely attach the mounting bracket to the wall using the provided screws.

### 3. Power Connection:

- **Plug-in:** If using the plug-in option, ensure a readily accessible power outlet is nearby. Simply plug the mirror's power cord into the outlet.
- **Hard-wired:** For hard-wired installation, it is recommended to consult a qualified electrician. Disconnect power at the circuit breaker. Connect the mirror's wires to the corresponding household electrical wires (Live to Live, Neutral to Neutral, Ground to Ground) using wire nuts. Ensure all connections are secure and insulated.

4. **Hang the Mirror:** Carefully lift the mirror and align the slots on the back of the mirror with the mounting bracket. Gently lower the mirror onto the bracket until it is securely seated.

5. **Remove Protective Film:** Once the mirror is securely mounted and connected, carefully peel off any protective film from the mirror surface.



Figure 2: The mirror supports both plug-in and hard-wired power connections for flexible installation.



Figure 3: Key components include the black aluminum frame, 5MM tempered glass, and included mounting brackets.



Figure 4: An example of the Amorho LED Bathroom Mirror installed above a sink.

## OPERATING INSTRUCTIONS

---

The Amorho LED Bathroom Mirror features intuitive touch controls located on the mirror surface.

### Power On/Off and Brightness Adjustment

- **Power:** Tap the power touch button (usually indicated by a circle icon) to turn the mirror lights on or off.
- **Brightness Dimming:** When the lights are on, press and hold the brightness touch button (usually indicated by an up/down arrow icon) to steplessly adjust the brightness from 10% to 100%. Release the button when the desired brightness is reached. The mirror will remember your last brightness setting.




## Stepless Dimmable (From 10% to 100%)

Long press to adjust brightness



Added memory function



10%



50%



100%

Figure 5: Visual representation of stepless dimming from 10% to 100% brightness with memory function.

### Color Temperature Adjustment

- **Change Color Temperature:** Tap the color temperature touch button (usually indicated by a sun or color palette icon) to cycle through the three available color temperatures: 3000K (Warm White), 4000K (Neutral Light), and 6000K (Cold White). The mirror will remember your last color temperature setting.



# Free to Switch 3 Color Temperatures



Added memory function



3000k



4000k



6000k

Figure 6: Illustrates the three color temperature options: 3000K (Warm White), 4000K (Neutral Light), and 6000K (Cold White).

## Anti-Fog Function

- **Activate Anti-Fog:** Tap the anti-fog touch button (usually indicated by a steam icon). The defogger will activate and clear fog from the mirror surface. The anti-fog function automatically turns off after 1 hour of operation.



# Smart Anti-fog Addition

The defogging function turns on with the switch and turns off automatically after one hour of operation



**Before**



**After**

Figure 7: Demonstrates the effectiveness of the smart anti-fog function, showing a clear mirror surface after activation.

## MAINTENANCE

---

- **Cleaning:** Use a soft, damp cloth with a mild glass cleaner to clean the mirror surface. Avoid abrasive cleaners or harsh chemicals that may damage the mirror or frame.
- **Frame Care:** Wipe the black aluminum frame with a soft, dry cloth. Do not use liquid cleaners directly on the frame.
- **Electrical Components:** Ensure the mirror is disconnected from power before cleaning any electrical components. Do not attempt to service the internal electrical parts.
- **Long-Term Storage:** If storing the mirror for an extended period, ensure it is clean, dry, and stored in a safe place away from extreme temperatures or humidity.

## TROUBLESHOOTING

---

Problem	Possible Cause	Solution
Mirror lights do not turn on.	No power supply; Loose connection; Faulty switch.	Check if the mirror is properly plugged in or hard-wired. Ensure the wall switch (if applicable) is on. Verify circuit breaker.
Anti-fog function not working.	Anti-fog function not activated; Heater malfunction.	Ensure the anti-fog touch button has been pressed. Allow a few minutes for the heater to warm up.
Lights flicker or dim unexpectedly.	Unstable power supply; Loose wiring; LED driver issue.	Check power connections. Ensure stable power source. If problem persists, contact customer support.
Touch buttons are unresponsive.	Mirror surface is wet or dirty; Electrical interference.	Clean and dry the touch button area. Try cycling power to reset the mirror.

## SPECIFICATIONS

Attribute	Detail
Brand	Amorho
Model Number	4036
Product Dimensions	40"L x 36"W
Frame Material	Aluminum
Mirror Material	Tempered Glass (5MM)
Mounting Type	Wall Mount (Horizontal/Vertical)
Light Source	LED (Front Light and Backlit)
Color Temperatures	3000K / 4000K / 6000K
Brightness Adjustment	Stepless Dimmable (10%-100%)
Special Features	Anti-Fog, Shatterproof, Memory Function, Touch Sensor
Item Weight	33.7 pounds
Power Connection	Plug-in or Hard-wired

## WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the product packaging or contact Amorho directly through their official website or the retailer where the product was purchased. Keep your purchase receipt for warranty claims.

**Amorho Customer Service:** [Visit the Amorho Store on Amazon](#)