

## TOCHIC BPL001-Black

# TOCHIC 45-inch Rustic Pool Table Light Fixture Instruction Manual

Model: BPL001-Black

## INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your TOCHIC 45-inch Rustic Pool Table Light Fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference.

## SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Contact a qualified electrician if you are unfamiliar with proper electrical wiring.
- Use only E26 base bulbs, maximum 60 watts per bulb. Do not exceed the recommended wattage.
- Ensure the fixture is securely mounted to a structurally sound ceiling or junction box capable of supporting the fixture's weight.
- Do not install this fixture in wet or damp locations. It is designed for indoor use only.
- Handle glass components with care to prevent breakage.

## PACKAGE CONTENTS

Verify that all parts are included before beginning installation. If any parts are missing or damaged, contact TOCHIC customer service.

- Light Fixture Body (with pre-attached chain)

- Lamp Shades (3 units)
- Mounting Hardware (Canopy, Mounting Plate, Screws, Wire Nuts)
- Instruction Manual

**Note:** E26 bulbs are not included and must be purchased separately.

## SPECIFICATIONS

Feature	Detail
Model Name	BPL001-Black
Dimensions (L x W x H)	45.08" x 12.2" x 26.69"
Item Weight	19.75 pounds
Material	Metal, Plastic (Acrylic Shade)
Color	Black
Number of Lights	3
Bulb Base	E26
Max Wattage per Bulb	60 Watts
Voltage	110 Volts
Installation Type	Semi Flush Mount (Monopoint with Canopy)
Room Type	Dining Room, Game Room, Kitchen, Billiard Room

The fixture features a rustic design with wildlife silhouettes (bear, elk, trees) on both the main body and the lamp shades. It is suitable for 7' or 8' pool tables and offers adjustable hanging chain length.



Figure 1: Product Dimensions Overview

## SETUP AND INSTALLATION

**Tools Required (Not Included):** Screwdriver, Wire Strippers, Pliers, Electrical Tape, Ladder, Safety Glasses.

1. **Turn Off Power:** Before starting, ensure the power to the circuit you are working on is turned off at the main electrical panel (circuit breaker or fuse box).
2. **Prepare Mounting Location:** If replacing an existing fixture, carefully remove it. Ensure the junction box is securely mounted and capable of supporting the new fixture's weight.
3. **Attach Mounting Plate:** Secure the mounting plate (included in hardware) to the junction box using the provided screws.
4. **Assemble Lamp Shades:** The lamp shades are packed disassembled for safety. Carefully align the panels and secure them using the small screws provided. Do not overtighten until all panels are in place to allow for minor adjustments.
5. **Connect Wiring:** With the help of another person to hold the fixture, connect the electrical wires:

- Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box using a wire nut.
- Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box using a wire nut.
- Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and the ground screw on the mounting plate.

Ensure all connections are secure and covered with electrical tape if necessary.

6. **Mount Fixture:** Carefully lift the fixture and attach the canopy to the mounting plate, securing it with the provided screws or nuts. Adjust the chain length as desired before final tightening. The fixture comes with a 43.31-inch hanging chain, which is height adjustable.
7. **Install Bulbs:** Screw three E26 base bulbs (not included) into the sockets. Do not exceed 60 watts per bulb.
8. **Restore Power:** Turn the power back on at the circuit breaker.



Figure 2: Detail of Lamp Shade Design



Figure 3: Fixture Connection Point Detail

## OPERATING INSTRUCTIONS

Once installed and bulbs are in place, operate the light fixture using your standard wall switch. The fixture is designed for simple on/off functionality. It supports various E26 bulb types including LED, CFL, halogen, incandescent, and fluorescent, allowing you to choose the desired light color and brightness (warm white is a common choice).

Your browser does not support the video tag.

Video 1: Demonstration of the TOCHIC Pool Table Light Fixture in various settings, showcasing its design and illumination.

## MAINTENANCE

- **Cleaning:** To clean the fixture, ensure the power is off. Wipe with a soft, dry cloth. Do not use abrasive cleaners or solvents, as they may damage the finish or acrylic shades.
- **Bulb Replacement:** Always turn off the power before replacing bulbs. Allow bulbs to cool completely before touching. Unscrew the old bulb and screw in a new E26 base bulb (max 60W).
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture Loose wiring connection Faulty bulb	Check circuit breaker/fuse. Ensure wall switch is on. Turn off power, check all wire connections. Replace bulb with a new one.
Flickering light	Loose bulb Loose wiring connection Incompatible dimmer switch (if applicable)	Tighten bulb securely. Turn off power, check all wire connections. Ensure dimmer switch is compatible with LED/CFL bulbs if used.
Fixture is unstable/wobbly	Mounting hardware not secure	Turn off power, tighten all mounting screws and nuts. Ensure junction box is secure.

## WARRANTY AND SUPPORT

This TOCHIC light fixture comes with a **Limited Warranty**. For specific warranty details, claims, or technical

support, please refer to the warranty card included with your product or contact TOCHIC customer service directly.  
**Customer Service:** For assistance, please visit the TOCHIC store on Amazon or refer to the contact information provided in your product packaging.

## PRODUCT OVERVIEW

---



Overall view of the light fixture.



Fixture installed over a pool table.



Fixture used as a dining room chandelier.