Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Dpofirs Dpofirscesyhxw5qa

Dpofirs 1080P Rechargeable Night Vision Camera User Manual

Model: Dpofirscesyhxw5qa | **Brand:** Dpofirs

1. Product Overview

The Dpofirs 1080P Rechargeable Night Vision Camera is a compact video camera designed for home and office surveillance. It offers 1080P video resolution, night vision capabilities, and a built-in magnet for versatile placement. The camera supports both Wi-Fi (2.4GHz only) and non-Wi-Fi operation with Micro storage card recording.

Key Features:

- **1080P Video Resolution:** Provides clear, real-time video monitoring for your home or office.
- **Night Vision:** Enables visibility in low-light conditions and motion detection in the dark.
- **Built-in Magnet:** Allows for easy attachment to any iron material, offering flexible placement options. Remote viewing is accessible via a dedicated app for iOS and Android smartphones.
- **Rechargeable Battery:** Features a compact design with a built-in rechargeable lithium battery (300mAh). It can record while charging and supports manual 360-degree rotation.
- **Flexible Connectivity:** Operates with 2.4GHz Wi-Fi or can record directly to a Micro storage card (not included) when Wi-Fi is unavailable.

2. Package Contents

Please verify that all items listed below are included in your package:

- 1 x Mini Camera
- 2 x Charging Cable (Micro 5pin USB)
- 1 x Base (Magnetic)
- 1 x Iron Sheet
- 1 x User Manual



Image 2.1: All components included in the package: the mini camera, its magnetic base, two USB charging cables, and a small circular iron sheet.

3. Product Components

Familiarize yourself with the camera's various parts and controls.



Image 3.1: Front view of the Dpofirs mini camera, highlighting the central lens and surrounding night vision infrared emitters.



Image 3.2: A detailed view of the camera's control buttons, labeled 'MODE' and 'ON/OFF', located on the side of the device.



Image 3.3: Side profile of the mini camera, demonstrating its attachment to the included magnetic base, allowing for adjustable angles.

4. Setup Instructions

Follow these steps to set up your Dpofirs mini camera:

1. **Unpack and Inspect:** Carefully open the package and ensure all components listed in Section 2 are present and undamaged.
2. **Charge the Camera:** Connect one of the provided Micro USB charging cables to the camera's charging port and the other end to a USB power adapter (not included) or a computer USB port. The camera can record while charging.
3. **Insert Micro SD Card (Optional):** If you intend to record without Wi-Fi or store recordings locally, insert a Micro storage card (up to 128GB, not included) into the designated slot. Ensure the card is inserted correctly.
4. **Power On:** Press and hold the 'ON/OFF' button until the indicator light illuminates.
5. **Mounting:** Utilize the magnetic base to attach the camera to any metallic surface. The included iron sheet can be used to create a magnetic surface if needed. The camera can be manually rotated 360 degrees on its base to achieve the desired viewing angle.
6. **App Connection (for Wi-Fi functionality):** Download the compatible application for iOS or Android smartphones. Follow the in-app instructions to connect the camera to your 2.4GHz Wi-Fi network for remote viewing and control.

5. Operating Instructions

5.1 Basic Operation

- **Power On/Off:** Press and hold the 'ON/OFF' button to power the camera on or off.
- **Mode Switching:** Press the 'MODE' button to cycle through different recording modes (e.g., continuous recording, motion detection recording). Refer to the app for detailed mode configurations if connected via Wi-Fi.
- **Recording without Wi-Fi:** If a Micro storage card is inserted and the camera is powered on, it will automatically begin recording to the card based on its current mode settings.

5.2 Night Vision

The camera is equipped with night vision capabilities, allowing it to capture video in low-light or dark environments. This feature is essential for continuous surveillance, especially during nighttime hours. The camera can also detect motion in the dark.

5.3 Remote Viewing (via App)

Once connected to your 2.4GHz Wi-Fi network and paired with the mobile application, you can:

- View live video feed from anywhere.
- Access recorded footage stored on the Micro storage card.
- Adjust camera settings, including recording modes, motion detection sensitivity, and night vision options.
- Receive alerts for detected motion.

6. Maintenance

To ensure optimal performance and longevity of your camera, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the camera lens and body. Avoid using liquid cleaners or abrasive materials, which can damage the lens or finish.
- **Battery Care:** Charge the camera regularly, even if not in frequent use, to maintain battery health. Avoid extreme temperatures during charging and operation.
- **Storage:** When not in use for extended periods, store the camera in a cool, dry place away from direct sunlight and moisture.

- **Firmware Updates:** Periodically check the mobile application for any available firmware updates for your camera. Keeping the firmware updated can improve performance and add new features.

7. Troubleshooting

If you encounter issues with your Dpofirs mini camera, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Camera does not power on.	Low battery or faulty charging cable.	Charge the camera for at least 2 hours. Try a different charging cable or USB power source.
Cannot connect to Wi-Fi.	Incorrect Wi-Fi password, camera too far from router, or unsupported Wi-Fi frequency.	Ensure correct 2.4GHz Wi-Fi password. Move camera closer to router. Confirm your router is broadcasting on 2.4GHz.
No recording to Micro SD card.	No Micro SD card inserted, card full, or card not formatted correctly.	Insert a Micro SD card. Check card capacity and delete old files or replace with a new card. Format the card via the app or a computer.
Poor video quality.	Dirty lens, insufficient lighting, or network issues.	Clean the camera lens. Ensure adequate lighting or verify night vision is active. Check Wi-Fi signal strength.
App not detecting camera.	Camera not powered on, not in pairing mode, or app issues.	Ensure camera is on. Follow app instructions for pairing mode. Restart the app or reinstall it.

8. Specifications

Detailed technical specifications for the Dpofirs 1080P Rechargeable Night Vision Camera:

Feature	Specification
Video Format	AVI
Video Resolution	1080P
Frame Rate	25fps
Camera Distance	Approx. 6m/19.7ft
Battery Working Time	1 Hour (Built-in 300mAh Lithium Battery)
Recording Range	5
Storage Capacity	Maximum 128G (Micro SD card, not included)
Support System	For Android, For iOS
Power Consumption	240mA/3.7V
Play Software	VLCP Layer/SMP Layer

Feature	Specification
Interface	Micro 5pin USB
Charging Voltage	DC-5V
Connectivity Protocol	Wi-Fi (2.4GHz only)
Mounting Type	Wall Mount (via magnetic base)
Focus Type	Manual Focus
Zoom Type	Digital Zoom
Alert Type	Motion Only
Indoor/Outdoor Usage	Indoor
Item Weight	4.2 ounces
Item Model Number	Dpofirscesyhxw5qa

9. Warranty and Support

For warranty information and technical support, please refer to the documentation included with your purchase or contact Dpofirs customer service through the retailer's platform where the product was purchased. Keep your purchase receipt for warranty claims.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0C9R1P8SD

More documents and user manuals: **https://manuals.plus/**