

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [JZAQ](#) /

› [JZAQ A13 Bluetooth Helmet Speakers & Intercom System User Manual](#)

JZAQ A13

JZAQ A13 Bluetooth Helmet Speakers & Intercom System User Manual

Model: A13

1. INTRODUCTION

The JZAQ A13 Bluetooth Helmet Speakers and Intercom System provides wireless communication and audio playback for motorcycle riders, skiers, cyclists, and other sports enthusiasts. This system features Bluetooth 5.3 connectivity, two-way intercom functionality, noise cancellation, and a waterproof design for reliable performance in various conditions.



Image 1.1: JZAQ A13 Bluetooth Helmet Headset overview.

2. PACKAGE CONTENTS

Before installation, please verify that all items listed below are present in your package:

- JZAQ A13 Headphone Host
- Hard Earbuds
- Soft Earbuds
- Clip Base
- Paste Base
- Horn Velcro
- TYPE-C Charging Cable
- Hard and Soft Velcro Pads
- User Manual



Image 2.1: All components included in the JZAQ A13 package.

3. PRODUCT OVERVIEW

Familiarize yourself with the main unit and its controls:

1500mA large capacity battery

Play for 180 hours, save your charging time, and ride with confidence.



Image 3.1: Diagram illustrating the button functions and ports on the JZAQ A13 unit.

- **Power On/Off/Pause/Play/Connect Button:** Controls power, music playback, and Bluetooth connection.
- **Volume Up/Next Song Button:** Increases volume and skips to the next track.
- **Volume Down/Previous Song/Voice Assistant Button:** Decreases volume, goes to the previous track, and activates the voice assistant.
- **Charging Port:** USB Type-C port for charging the device.
- **Headphone Jack:** Connects the speakers and microphone.

4. SETUP AND INSTALLATION

4.1 Charging the Device

Before first use, fully charge the JZAQ A13 unit. Connect the provided TYPE-C charging cable to the charging port on the unit and a USB power source. A full charge typically takes approximately 2 hours. The device features a 1500mAh battery, providing up to 180 hours of continuous play time.

Button Function



Image 4.1: Illustration of the 1500mAh large capacity battery.

4.2 Helmet Installation

The JZAQ A13 is designed to be compatible with various helmet types. The speakers are ultra-thin (10mm) to ensure comfort and avoid ear pressure.



Suitable for all helmets

Image 4.2: Examples of various helmet types compatible with the JZAQ A13.

Follow these steps to install the system in your helmet:

- 1. Speaker Placement:** Identify suitable locations within your helmet for the speakers, typically in the ear

recesses. Use the provided Velcro pads to secure the speakers.

2. **Microphone Attachment:** Choose between the hard or soft earbuds (microphones) based on your helmet type and preference. Attach the microphone using Velcro in a position that allows clear voice pickup without obstructing your vision or comfort.
3. **Main Unit Mounting:** Use either the clip base or the paste base to attach the main JZAQ A13 unit to the side of your helmet. Ensure it is securely fastened and easily accessible for operation.
4. **Cable Management:** Route all cables neatly within the helmet padding to prevent discomfort or interference.



Image 4.3: Step-by-step visual guide for installing the JZAQ A13 system into a helmet.

5. OPERATING INSTRUCTIONS

5.1 Power On/Off

- **Power On:** Press and hold the Power button for approximately 3 seconds until the indicator light illuminates.
- **Power Off:** Press and hold the Power button for approximately 3 seconds until the indicator light turns off.

5.2 Bluetooth Pairing

The JZAQ A13 uses Bluetooth 5.3 for stable wireless connectivity.

1. Ensure the device is powered off.
2. Press and hold the Power button for approximately 5-7 seconds until the indicator light flashes red and blue alternately, indicating pairing mode.
3. On your mobile phone or Bluetooth-enabled device, search for "JZAQ A13" in the Bluetooth settings.
4. Select "JZAQ A13" to connect. Once paired, the indicator light will flash blue slowly.

5.3 Music Playback

After successful Bluetooth pairing, you can play music from your connected device. The system features Hi-Fi stereo sound and DSP noise reduction technology for clear audio.



Image 5.1: The JZAQ A13 provides clear music playback with noise reduction.

- **Play/Pause:** Press the Power button once.
- **Volume Up:** Press the Volume Up (+) button.
- **Volume Down:** Press the Volume Down (-) button.

- **Next Song:** Press and hold the Volume Up (+) button.
- **Previous Song:** Press and hold the Volume Down (-) button.

5.4 Two-Way Intercom

The JZAQ A13 supports two-way intercom communication between two riders within a range of up to 200 meters. The universal pairing function allows connection with other compatible intercom systems.



Image 5.2: Illustration of two-way intercom communication between riders.

- **Initiate Intercom:** Consult the specific instructions for initiating intercom with another JZAQ A13 unit or a universally paired device.
- **End Intercom:** Press the Power button once during an active intercom call.

5.5 Phone Calls

The system supports hands-free calling with automatic answering and DSP noise reduction for clear voice communication.

- **Answer Call:** The system will automatically answer incoming calls after a few rings.
- **End Call:** Press the Power button once.

- **Reject Call:** Press and hold the Power button for 2 seconds.

5.6 Voice Assistant

Activate your smartphone's voice assistant (e.g., Siri) directly from the JZAQ A13.

- **Activate Voice Assistant:** Press the Volume Down (-) button twice quickly.

6. MAINTENANCE

6.1 Waterproofing

The JZAQ A13 features IPX67 deep waterproof technology with Nano coating, making it suitable for use in rainy or snowy conditions and capable of operating in temperatures as low as -20°F.



Image 6.1: The JZAQ A13 demonstrating its IP67 deep waterproof capability.

6.2 Cleaning and Storage

- Wipe the unit with a soft, damp cloth. Avoid using harsh chemicals or abrasive cleaners.
- Ensure the charging port cover is securely closed to maintain water resistance.

- Store the device in a cool, dry place when not in use.

7. TROUBLESHOOTING

If you encounter issues with your JZAQ A13, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Device does not power on	Low battery; Device frozen	Charge the device fully; Perform a hard reset (if applicable, refer to manufacturer for specific steps).
Cannot pair with phone	Not in pairing mode; Bluetooth off on phone; Device already paired	Ensure device is in pairing mode (flashing red/blue); Turn on phone's Bluetooth; Forget previous connections on phone and re-pair.
No sound from speakers	Volume too low; Speakers disconnected; Faulty connection	Increase volume on device and phone; Check speaker connections; Try re-plugging speakers into the main unit.
Intercom not connecting	Out of range; Incorrect pairing procedure	Ensure riders are within 200m range; Repeat intercom pairing steps for both units.
Poor voice quality during calls/intercom	Microphone position; Excessive wind noise	Adjust microphone closer to mouth; Ensure microphone is shielded from direct wind.

8. SPECIFICATIONS

Key technical specifications for the JZAQ A13 Bluetooth Helmet Speakers & Intercom System:

Feature	Specification
Model Name	A13
Brand	JZAQ
Connectivity Technology	Wireless (Bluetooth)
Bluetooth Version	5.3
Battery Capacity	1500mAh
Battery Life (Play Time)	Up to 180 Hours
Charging Time	2 Hours
Intercom Range	Up to 200 meters (two-way)
Water Resistance Level	IPX67 (Waterproof)
Noise Control	Sound Isolation, DSP Noise Reduction
Special Features	Built-In Voice Assistant, Fast Charging, Includes microphone, Lightweight
Item Weight	7.4 ounces (0.21 Kilograms)

Feature	Specification
Operating Temperature	-20°F to (unspecified upper limit)

9. WARRANTY AND SUPPORT

The JZAQ A13 Bluetooth Helmet Speakers & Intercom System comes with a **2-year warranty**. For any product-related inquiries, technical assistance, or warranty claims, please contact JZAQ customer service through the Amazon Buyer Center. Our customer service team is available to assist you.