

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

- › [Yamiry](#) /
- › [Yamiry Smart Lock YR01 with WiFi Gateway User Manual](#)

## Yamiry YR01

# Yamiry Smart Lock YR01 with WiFi Gateway User Manual

---

## INTRODUCTION

---

Welcome to your new Yamiry Smart Lock YR01. This manual provides detailed instructions for the installation, setup, operation, and maintenance of your smart lock and its included WiFi gateway. Please read this manual thoroughly before use to ensure proper functionality and safety.

## PRODUCT OVERVIEW

---

The Yamiry Smart Lock YR01 offers multiple secure access methods, including biometric fingerprint, phone application, keypad code, key fob, and traditional keys. The included WiFi gateway enables remote control and voice assistant integration, enhancing your home security and convenience.



This image displays the complete Yamiry Smart Lock YR01 system, featuring the main lock unit with a numeric keypad and fingerprint scanner, the door handle, the compact white WiFi gateway, and two key fobs for convenient access.

## WHAT'S INCLUDED

The Yamiry Smart Lock YR01 package typically includes the following components:

- Smart Lock Unit (with Biometric Fingerprint Sensor and Keypad)
- WiFi Gateway
- Key Fobs
- Regular Keys
- Installation Hardware (screws, strike plate, etc.)



An exploded diagram showing all the individual components of the Yamiry Smart Lock YR01, illustrating the interior and exterior lock assemblies, the deadbolt mechanism, strike plate, mounting screws, and physical keys required for installation.

## SPECIFICATIONS

| Feature          | Detail   |
|------------------|--|
| Brand            | Yamiry   |
| Special Feature  | Keyless  |
| Lock Type        | Biometric, Keypad  |
| Material         | Metal  |
| Recommended Uses | Home security, office security, keyless access control, smart home integration |
| Style            | Smart Lock with WIFI Gateway, Remote Control                                   |

| Feature               | Detail          |
|-----------------------|-----------------|
| Color                 | Black           |
| Included Components   | WiFi gateway    |
| Controller Type       | Amazon Alexa    |
| Shape                 | Rectangular     |
| Control Method        | Voice           |
| Connectivity Protocol | Bluetooth       |
| Model Name            | Smart Lock YR01 |
| Item Model Number     | YR01            |

## INSTALLATION GUIDE

The Yamiry Smart Lock YR01 is designed for easy installation, typically replacing an existing deadbolt without requiring additional drilling. It fits door thicknesses from 1-3/8 inches to 1-3/4 inches.

### Physical Installation

Follow the detailed instructions provided in the product packaging for physical installation of the lock components. A screwdriver is generally the only tool required for this process.

### Gateway Setup and App Integration

To enable remote control and voice assistant features, the included WiFi gateway must be set up and connected to the Nice Digi App. The following video provides a visual guide:

Your browser does not support the video tag.

Instructional video demonstrating the setup process for the Yamiry WiFi Gateway with the Nice Digi App. This guide covers powering on the gateway, checking indicator lights, adding it to the app, and linking your smart lock devices.

#### Steps for Gateway Setup:

- Power on the Gateway:** Connect the WiFi gateway to a power source using the provided Micro USB cable.
- Check Indicator Lights:** Ensure the blue light is always on and the red light is blinking. This indicates the gateway is powered and ready for pairing.
- Add Gateway to Nice Digi App:** Open the Nice Digi App on your smartphone. Tap "Add Device" and follow the on-screen prompts to connect the gateway to your 2.4GHz Wi-Fi network. (Note: The gateway only works with 2.4GHz Wi-Fi, not 5GHz).
- Add Existing Devices to Gateway:** Within the app, tap on the newly added gateway, then select "Add Device" to link your smart lock to the gateway. Ensure your lock is already added to the app via Bluetooth before this step.

# Product Detail

Network: Work with 2.4G WiFi

Power Input: 5V/500mA

Power Interface: Micro USB



A close-up image of the compact Yamiry WiFi Gateway, highlighting its dimensions (2.36"x2.36"x0.59"), and indicating its power input (5V/500mA) and Micro USB interface.

## OPERATING INSTRUCTIONS

Your Yamiry Smart Lock YR01 offers various convenient and secure methods for locking and unlocking your door.

### Remote Control via Nice Digi App

With the WiFi Gateway successfully connected, you can control your lock from anywhere with an internet connection using the Nice Digi App. This includes unlocking, locking, programming temporary or permanent access codes, managing e-keys, and viewing real-time access records.

# Real Time Notification



An image showing a person using the Nice Digi App on their smartphone to remotely lock or unlock the smart lock, demonstrating the convenience of controlling the lock from any location with an internet connection.

## Voice Control with Alexa and Google Home

The smart lock integrates seamlessly with Amazon Alexa and Google Home for convenient voice control. Ensure your Nice Digi account is linked to your smart assistant's app (Alexa App or Google Home App) and that voice unlock features are enabled in the lock's settings within the respective app.

# Voice Control

Hi Alexa, unlock the door.

works with  
amazon alexa

works with  
Google Assistant

The door is open.

This image illustrates the voice control functionality, with a person speaking to an Amazon Echo device to unlock the door, and the Yamiry Smart Lock visible on a door in the background, confirming the action.

## Other Access Methods

- **Biometric Fingerprint:** Register your fingerprints through the Nice Digi App for quick and secure access.
- **Keypad Code:** Use a personalized numeric code on the lock's keypad for entry.
- **Key Fob:** Tap the provided key fob to the designated area on the lock to unlock the door.
- **Regular Keys:** Traditional physical key access is always available as a reliable backup.

## MAINTENANCE

To ensure optimal performance and longevity of your Yamiry Smart Lock YR01, regular maintenance is recommended:

- **Battery Replacement:** Replace batteries promptly when the low battery indicator appears in the app or on the lock. Use high-quality alkaline batteries for best performance.
- **Cleaning:** Clean the keypad and fingerprint sensor with a soft, dry cloth. Avoid abrasive cleaners, solvents, or

excessive moisture, as these can damage the electronic components.

- **Firmware Updates:** Regularly check the Nice Digi App for available firmware updates. Installing updates ensures your lock has the latest features, security enhancements, and bug fixes.
- **Mechanical Check:** Periodically check that all mounting screws are tight and that the lock's mechanical components operate smoothly without obstruction.

## TROUBLESHOOTING

---

If you encounter issues with your Yamiry Smart Lock YR01, refer to the following common solutions:

- **Lock Not Responding:** Check battery levels. If batteries are low, replace them immediately. Ensure the lock is within Bluetooth range of your phone or within Wi-Fi range of the gateway if using remote features.
- **Fingerprint Sensor Issues:** Ensure your finger is clean and dry when using the sensor. Try re-registering your fingerprint in the Nice Digi App if issues persist.
- **App Connectivity Problems:** Verify your WiFi gateway is powered on and successfully connected to your 2.4GHz Wi-Fi network. Restart the gateway and your home router if necessary. Ensure the Nice Digi App is updated to the latest version on your smartphone.
- **Voice Control Not Working:** Confirm that your Nice Digi account is correctly linked to your Amazon Alexa or Google Home app. Check that "unlock by voice" is enabled in the smart assistant's settings for the specific lock, and that you are providing the correct voice confirmation code if required.
- **Remote Unlock/Lock Delays:** This could be due to network congestion or poor Wi-Fi signal strength between the gateway and your router, or between your phone and the internet. Ensure the gateway is placed in an optimal location for strong signal reception.

For further assistance, please contact customer support.

## WARRANTY AND SUPPORT

---

Yamiry offers a 30-day money-back guarantee and a 1-year product warranty from the date of purchase for your Smart Lock YR01. Lifetime customer support is also provided to assist you with any questions or issues you may encounter.

The Nice Digi App, which controls your smart lock, is free to use forever, with no subscription or extra fees required.

For support, please refer to the contact information provided in your product packaging or visit the official Yamiry website for the most up-to-date support resources.