

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [IKIMI](#) /

> [IKIMI Pet Grooming Kit with Vacuum and Dryer, Model CSJ1200-A02 Instruction Manual](#)

IKIMI CSJ1200-A02

IKIMI Pet Grooming Kit with Vacuum and Dryer (Model CSJ1200-A02)

Instruction Manual

1. INTRODUCTION

Thank you for choosing the IKIMI Pet Grooming Kit with Vacuum and Dryer. This 3-in-1 device is designed to provide a comprehensive solution for pet grooming, including vacuuming loose hair, drying wet fur, and trimming. Please read this manual thoroughly before operating the device to ensure safe and efficient use. Keep this manual for future reference.



Image 1.1: Overview of the IKIMI Pet Grooming Kit, including the main unit, hose, trimmer, and multiple grooming attachments. A golden retriever and a cat are shown in the background, illustrating the product's use for different pets.

2. SAFETY INSTRUCTIONS

To prevent injury or damage, always follow these basic safety precautions:

- Read all instructions before use.
- This appliance is for household pet grooming use only. Do not use for commercial purposes or any other application.
- Do not operate the appliance with a damaged cord or plug. If the appliance is not working as it should, has been dropped, damaged, left outdoors, or dropped into water, return it to a service center.
- Do not immerse the main unit, cord, or plug in water or other liquids.
- Keep the appliance away from heat sources, direct sunlight, and sharp edges.
- Ensure the voltage indicated on the appliance matches your local power supply before connecting.

- Always unplug the appliance from the power outlet when not in use, before cleaning, or before changing accessories.
- Supervise children and pets to ensure they do not play with the appliance.
- Do not block air openings or operate the appliance on a soft surface where openings may be blocked. Keep air openings free of lint, hair, and the like.
- Use only attachments recommended by the manufacturer.
- This product is designed for 110V-120V power supply. Do not attempt to use it with 240V power.

3. PACKAGE CONTENTS

Please check the package contents upon unboxing. If any items are missing or damaged, contact customer support.

- Main Unit (Vacuum/Dryer)
- Flexible Hose
- Pet Trimmer with Vacuum Function
- Grooming Brush Attachment
- Deshedding Tool Attachment
- Cleaning Nozzle Attachment
- Crevice Tool Attachment
- Hair Dryer Nozzle
- Various Guide Combs for Trimmer (e.g., 3mm, 6mm, 9mm, 12mm)
- Power Adapter
- User Manual



Image 3.1: Visual representation of the complete IKIMI Pet Grooming Kit and its accessories, demonstrating the potential grooming results.

4. SETUP

1. **Unpack the Device:** Carefully remove all components from the packaging.
2. **Connect the Hose:** Attach the flexible hose to the main unit. Ensure it is securely twisted or clicked into place to prevent detachment during use.
3. **Select and Attach Tool:** Choose the desired grooming or cleaning attachment (e.g., grooming brush, trimmer, dryer nozzle) and firmly connect it to the other end of the flexible hose.
4. **Power Connection:** Plug the power adapter into the main unit, then plug the adapter into a standard 110V-120V electrical outlet.

5. OPERATING INSTRUCTIONS

The IKIMI Pet Grooming Kit offers three primary functions: vacuuming, drying, and trimming.

5.1. Vacuum & Grooming Mode

This mode is ideal for collecting loose pet hair during brushing or trimming, and for general household cleaning.

1. **Attach Grooming Tool:** Connect the grooming brush, deshedding tool, or trimmer to the hose.
2. **Turn On:** Rotate the power knob on the main unit to the desired suction level. Start with a lower setting and increase as needed.
3. **Grooming:** Gently brush your pet's fur. The vacuum will simultaneously collect loose hair directly into the dust cup, minimizing mess.
4. **Trimming:** When using the trimmer, select the appropriate guide comb. The vacuum function will collect trimmed hair as you cut.
5. **Household Cleaning:** Attach the cleaning nozzle or crevice tool to vacuum pet hair from furniture, carpets, or hard-to-reach areas.

16000pa
collects 99% of pet hair

Brand A		8000pa
A brand of hair trimmer		
Brand B		13000pa
B brand hairdressing machine		
IKIMI		16000pa
IKIMI all in one Grooming Kit		

Image 5.1: The grooming brush attachment in use, illustrating the vacuum's effectiveness in collecting pet hair.



Vac-Trimmer

Makes Pets Styling Easier



Image 5.2: The Vac-Trimmer attachment, designed to make pet styling easier by collecting trimmed hair.



Plug in the Cleaning Nozzle

Vacuum out flying hairs from carpets and sofas easily

Image 5.3: The cleaning nozzle in use, demonstrating its ability to vacuum flying hairs from household surfaces.

5.2. Drying Mode

Use this mode to quickly and efficiently dry your pet's fur after bathing.

1. **Attach Dryer Nozzle:** Connect the hair dryer nozzle to the hose.
2. **Turn On:** Rotate the power knob on the main unit. The device will switch to blowing air. Adjust the knob to control the wind speed and temperature.
3. **Drying:** Direct the airflow towards your pet's fur, keeping a safe distance to avoid overheating. The device provides high-velocity air (up to 30m/s) and adjustable temperatures (98°F-150°F / 36°C-65°C).
4. **Monitor Pet Comfort:** Always monitor your pet for signs of discomfort or overheating. Adjust settings as necessary.



High Velocity Drying Hair



Image 5.4: The high-velocity drying function in use, showing the effectiveness of the airflow and temperature control.

Vacuum & Dryer Combo

Dual-Functionality for Easy Cleaning and Comfort



Image 5.5: The Vacuum & Dryer Combo in action, illustrating its versatility for various pet care tasks.

6. MAINTENANCE

Regular maintenance ensures optimal performance and extends the lifespan of your IKIMI Pet Grooming Kit.

- **Empty Dust Cup:** After each use, or when the dust cup is full, detach it from the main unit and empty the collected hair and debris. Clean the inside of the cup with a damp cloth if necessary.
- **Clean Filter:** The device features a filter to prevent hair from entering the motor. Regularly remove and clean the filter. Tap out loose debris, and if washable, rinse with water and ensure it is completely dry before reinserting.
- **Clean Attachments:** Remove any hair or debris from the grooming brush, deshedding tool, trimmer blades, and nozzles. Use a small brush or damp cloth. For trimmer blades, a drop of clipper oil can be applied periodically.
- **Wipe Down Unit:** Use a soft, dry, or slightly damp cloth to wipe the exterior of the main unit and hose. Do not use harsh chemicals or abrasive cleaners.
- **Storage:** Store the appliance and its accessories in a clean, dry place, away from direct sunlight and extreme temperatures.

7. TROUBLESHOOTING

If you encounter issues with your IKIMI Pet Grooming Kit, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Device does not turn on.	Not plugged in. Power outlet malfunction. Damaged power cord/adapter.	Ensure power cord is securely plugged into the unit and outlet. Test the outlet with another appliance. Contact customer support if cord/adapter is damaged.
Low suction power.	Dust cup is full. Filter is clogged. Hose or attachment is blocked. Hose not securely attached.	Empty the dust cup. Clean the filter thoroughly. Check hose and attachments for blockages and clear them. Ensure hose is securely connected to the main unit and attachment.
Trimmer not working.	Trimmer not properly connected to the hose. Blades are clogged with hair. Internal malfunction.	Ensure the trimmer is firmly attached to the hose. Clean the trimmer blades thoroughly. If the issue persists, contact customer support.
Hose detaches during use.	Hose not securely twisted/clicked into place.	Reattach the hose, ensuring it is twisted or clicked firmly until secure.

8. SPECIFICATIONS

Feature	Detail
Brand	IKIMI
Model Number	CSJ1200-A02
ASIN	B0CF5DSJYY
UPC	774882327318
Power	1500W Powerful Motor (Source of strong airflow)
Suction Power	16000Pa (collects 99% of pet hair)
Air Velocity (Drying)	Up to 30m/s
Blowing Temperature	Adjustable, 98°F-150°F (36°C-65°C)
Recommended Uses	Professional, Grooming, Clipping

Feature	Detail
Special Features	USB Accessible (for trimmer charging, if applicable), Removable Blade
Target Audience	Dog
Dimensions (Package)	44.5 x 34.8 x 19.51 cm
Weight (Package)	5.11 kilograms
Voltage	110V-120V (Not available for 240V)



Image 8.1: Diagram of the 1500W powerful motor, highlighting its role in generating strong airflow for both vacuuming and drying functions.

9. WARRANTY AND SUPPORT

IKIMI products are manufactured to high-quality standards. For warranty information, technical support, or service inquiries, please refer to the contact information provided with your purchase or visit the official IKIMI

website. Please retain your proof of purchase for warranty claims.