

Manuals.plus /

> [GLOBO](#) /

> Globo AGL MINA 4-Bulb Suspension Light Fixture User Manual

GLOBO 15326-4N

Globo AGL MINA 4-Bulb Suspension Light Fixture User Manual

Model: 15326-4N | Brand: GLOBO

1. INTRODUCTION

Thank you for choosing the Globo AGL MINA 4-Bulb Suspension Light Fixture. This manual provides essential information for the safe installation, operation, and maintenance of your new lighting product. Please read these instructions carefully before installation and retain them for future reference.

2. SAFETY INFORMATION

- **Electrical Safety:** Installation must be performed by a qualified electrician or a competent person in accordance with local electrical codes and regulations. Always disconnect power at the main circuit breaker before installation, maintenance, or bulb replacement.
- **Voltage:** Ensure the supply voltage matches the fixture's specified voltage (230 Volts).
- **Bulb Compatibility:** Use only E27 base bulbs with a maximum wattage of 40W per socket. Do not exceed the maximum wattage.
- **Indoor Use Only:** This fixture has an IP20 rating, meaning it is protected against solid objects larger than 12.5mm but has no protection against water. It is designed for indoor use only in dry locations.
- **Handling:** Handle the fixture with care to avoid damage to the wood, metal components, or electrical wiring.
- **Heat:** Bulbs can become hot during operation. Allow them to cool before touching or replacing.

3. PACKAGE CONTENTS

Please check that all components are present and undamaged:

- 1 x Globo AGL MINA Suspension Light Fixture (pre-assembled with wood beam, metal shades, and wiring)
- 1 x Ceiling Mounting Plate
- Mounting Hardware (screws, wall anchors)
- Instruction Manual

Note: E27 bulbs are not included and must be purchased separately.

4. SPECIFICATIONS

Brand	GLOBO
Model Number	15326-4N
Style	Modern
Color	Black, Natural Wood
Material	Metal, Wood
Finish	Matte, Textured
Number of Sockets	4
Socket Type	E27
Max Wattage per Bulb	40W
Total Max Wattage	160W
Voltage	230 Volts
IP Rating	IP20 (Indoor Use)
Dimmability	Dimmable with compatible E27 bulbs
Installation Type	Ceiling Mount, Suspended
Product Dimensions (L x W x Max H)	825 mm x 136 mm x 1400 mm
Item Weight	2.8 kg

5. SETUP & INSTALLATION

Important: Ensure power is disconnected at the main circuit breaker before beginning installation.

- 1. Prepare the Installation Area:** Choose a suitable location on the ceiling for mounting. Ensure the ceiling can support the weight of the fixture.
- 2. Mount the Ceiling Plate:** Detach the mounting plate from the fixture. Position the mounting plate on the ceiling and mark the drilling points. Drill holes and insert appropriate wall anchors (if necessary). Secure the mounting plate to the ceiling using the provided screws.
- 3. Connect Wiring:** Carefully connect the household electrical wires to the corresponding wires of the fixture. Typically, this involves connecting live (L), neutral (N), and ground (E) wires. Ensure all connections are secure and properly insulated.
- 4. Attach the Fixture:** Carefully lift the fixture and attach it to the mounted ceiling plate, securing it with the screws or fasteners provided. Ensure the fixture is firmly in place.
- 5. Install Bulbs:** Screw four E27 base bulbs (not included) into the sockets. Do not overtighten.
- 6. Restore Power:** Once installation is complete and all connections are secure, restore power at the main circuit breaker.



An overhead view of the complete light fixture, illustrating its construction with the ceiling plate, suspension mechanism, and the four light sources.

6. OPERATING INSTRUCTIONS

Once installed and powered, the Globo AGL MINA light fixture operates via a standard wall switch connected to your household electrical system. Simply toggle the wall switch to turn the light on or off.

- **Dimmability:** If you have installed dimmable E27 bulbs and your electrical system includes a compatible dimmer switch, you can adjust the light intensity. Refer to your dimmer switch's instructions for operation.



The suspension light fixture shown in operation, casting a warm light and demonstrating its aesthetic appeal when illuminated.

7. MAINTENANCE

- **Cleaning:** Disconnect power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish of the metal or wood.
- **Bulb Replacement:** Ensure the fixture is turned off and bulbs have cooled completely before attempting to replace them. Unscrew the old bulb and screw in a new E27 bulb, ensuring it does not exceed 40W.
- **Inspection:** Periodically inspect the fixture for any signs of wear, damage, or loose connections. If any issues are found, disconnect power and consult a qualified electrician.



Detail of the light fixture showing the E27 bulb sockets within the distinctive black metal cage shades and the natural wood element.

8. TROUBLESHOOTING

- **Light does not turn on:**

- Check if the power supply is connected and the circuit breaker is on.
- Ensure bulbs are correctly installed and not faulty. Test with a known working bulb.
- Verify all wiring connections are secure.

- **Flickering light:**

- Ensure bulbs are fully screwed in.
- If using dimmable bulbs, ensure they are compatible with your dimmer switch.
- Check for loose wiring connections.

- **Fixture is loose:**

- Disconnect power and re-tighten the mounting screws on the ceiling plate.

If you experience persistent issues not covered here, please consult a qualified electrician.



The Globo AGL MINA suspension light fixture, featuring a natural wood beam and four black metal cage lampshades, illuminates a dining area.

9. WARRANTY & SUPPORT

For warranty information or technical support, please refer to the retailer where the product was purchased or visit the official GLOBO Lighting website. Keep your proof of purchase for any warranty claims.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0CGVFS741>

More documents and user manuals: <https://manuals.plus/>