Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

ARZOPA A1

ARZOPA Portable Monitor A1 - Instruction Manual

Brand: ARZOPA | Model: A1

1. Product Overview

The ARZOPA Portable Monitor A1 is a 15.6-inch Full HD 1080P ultra-slim display designed for enhanced productivity and entertainment on the go. Featuring an IPS panel for wide viewing angles and vibrant colors, it offers versatile connectivity options for various devices.



Image: Front view of the ARZOPA Portable Monitor A1, showcasing its 15.6-inch Full HD 1080P display and slim design.

Key Features:

- **Full HD 1080P IPS Screen:** Immerse yourself in a vivid and accurate image with a 1920 x 1080 resolution IPS screen. Enjoy a wide 178° viewing angle for an enhanced visual experience.

- **Portable Monitor with Stand:** Crafted with high-quality and durable metal materials, the monitor with built-in kickstand can be easily adjusted to your preferred viewing angle.
- **Multiple Display Modes:** Choose from duplicate mode, extend mode, or second screen mode to suit your preferences. Connect your smartphone to desktop or phone mode effortlessly with this versatile monitor.
- **Ultra Slim Design:** Designed for easy travel, ARZOPA portable monitor is lightweight and compact. Weighing only 1.6lb, it boasts a slim profile with thicknesses of 0.35-inch.
- **Wide Compatibility:** Enjoy hassle-free plug-and-play functionality with the portable monitor. It is compatible with various ports and devices, including laptops, PCs, Macs, phones, Xbox, PS3, PS4, PS5, and Switches. No app or driver installation required.

Informational Video:

▶ **Watch video online**

Informational video about the product - Watch before you buy

Video: An informational overview of the ARZOPA Portable Monitor, highlighting its features and benefits for various uses.

2. Setup and Connections

The ARZOPA Portable Monitor offers flexible connectivity for a wide range of devices. It features multiple ports for both power and video signal transmission, ensuring a plug-and-play experience without the need for additional drivers.

Available Ports:

- **Mini HDMI Port:** For video input from devices with HDMI output.
- **USB Type-C Ports (x2):** Full-featured USB-C ports support both power delivery and video signal (DisplayPort Alternate Mode). One port can be used for power input, and the other for data/video.



Image: Close-up view of the ARZOPA Portable Monitor's side, detailing the Mini HDMI and dual USB Type-C ports for easy access and connectivity.

Connecting Your Device:

1. **For USB-C compatible devices (e.g., modern laptops, smartphones with DisplayPort Alt Mode):**Connect a single USB-C to USB-C cable from your device to one of the monitor's USB-C ports. This cable can transmit both video and power.
2. **For HDMI devices (e.g., older laptops, PCs, gaming consoles):** Connect an HDMI to Mini HDMI cable from your device to the monitor's Mini HDMI port. You will also need to connect a USB-A to USB-C cable (or a separate power adapter) to one of the monitor's USB-C ports for power.
3. Ensure your device's display settings are configured to extend or duplicate the display as desired.



Image: The ARZOPA Portable Monitor seamlessly connected to a variety of devices, including a Nintendo Switch, Xbox, PlayStation, mobile phone, and laptop, demonstrating its broad compatibility.

Setup Demonstration:

▶ **Watch video online**

What Do you Really Get?? Unboxing & Review of Arzopa !

Video: A user demonstrates the quick and easy setup of the ARZOPA Portable Monitor with a laptop, highlighting its

plug-and-play functionality.

3. Operating the Monitor

The ARZOPA Portable Monitor is designed for intuitive operation with easily accessible controls for brightness, volume, and On-Screen Display (OSD) menu navigation.

Controls:

- **Power/Return Button:** Turns the monitor on/off and acts as a back button in the OSD menu.
- **Volume Adjustment (+/-):** Increases or decreases the audio volume.
- **Brightness Adjustment (+/-):** Adjusts the screen brightness.
- **OSD Menu Button:** Press to enter the On-Screen Display menu for advanced settings.



Image: The ARZOPA Portable Monitor's integrated kickstand allows for easy adjustment to various viewing angles, enhancing comfort and versatility.

Adjusting Settings:

1. To adjust brightness or volume, simply press the corresponding +/- buttons.
2. To access the OSD menu, press the OSD button. Use the +/- buttons to navigate through options and the Power/Return button to select or go back.
3. The integrated kickstand allows for easy rotation and angle adjustment to match your viewing preference,

whether for work or entertainment.

Controls and Adjustments Video:

▶ Watch video online

Video: A detailed look at the monitor's controls, including volume and brightness adjustments, and how to utilize the integrated kickstand for optimal viewing.

4. Maintenance and Care

To ensure the longevity and optimal performance of your ARZOPA Portable Monitor, follow these simple maintenance guidelines:

- **Cleaning:** Use a soft, lint-free cloth to gently wipe the screen and exterior. For stubborn smudges, slightly dampen the cloth with water or a screen-safe cleaning solution. Avoid harsh chemicals or abrasive materials.
- **Handling:** Always handle the monitor with care. Avoid dropping it or subjecting it to strong impacts. When transporting, use the provided protective cover or a padded bag.
- **Storage:** Store the monitor in a cool, dry place away from direct sunlight and extreme temperatures.
- **Connectivity:** Ensure cables are connected securely but do not force them into ports. Disconnect cables by pulling on the plug, not the cable itself.

5. Troubleshooting

If you encounter any issues with your ARZOPA Portable Monitor, please refer to the following common troubleshooting steps:

- **No Signal/Black Screen:**
  - Ensure all cables (USB-C, HDMI, power) are securely connected.
  - Verify that your source device (laptop, phone, console) is powered on and outputting a display signal.
  - Try a different cable or port on both the monitor and your source device.
  - Check your source device's display settings to ensure it's set to extend or duplicate the display.
- **No Power:**
  - Ensure the power cable is connected to a working power source (wall adapter, laptop USB-C port).
  - If using a USB-C cable for both power and video, ensure your device supports power delivery via USB-C.
  - Try a different power adapter or USB-C port.
- **Display Issues (Flickering, Incorrect Colors):**
  - Adjust the brightness and contrast settings via the OSD menu.
  - Ensure your display resolution is set to 1920 x 1080P on your source device.
  - Try a different cable or port.

For further assistance, please refer to the warranty and support information below.

6. Specifications

Feature	Detail
Screen Size	15.6 Inches
Resolution	1920 x 1080 Pixels (FHD 1080p)
Panel Type	IPS
Aspect Ratio	16:9
Image Brightness	300 cd/m²
Item Weight	1.69 pounds
Product Dimensions	0.35 x 8.66 x 13.78 inches
Total USB Ports	2 (Type-C)

7. Warranty and Support

ARZOPA stands behind the quality of its products. Your ARZOPA Portable Monitor A1 comes with the following:

- **30-Day Return/Exchange Guarantee:** If you are not satisfied with your purchase, you may return or exchange it within 30 days.
- **12-Month Warranty Service:** The monitor is covered by a 12-month warranty against manufacturing defects.
- **Lifetime Customer Support:** ARZOPA provides lifetime customer support for all its products.
- **24/7 Online Support:** Access online support anytime for your convenience.

For support inquiries, please visit the official ARZOPA website or contact their customer service team directly.

Manufacturer: ARZOPA

© 2023 ARZOPA. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0CH9XW8RK

More documents and user manuals: **https://manuals.plus/**