

[Manuals.plus](#) /

› [Buytra](#) /

› Multi-function Nut Milk Maker - 35oz Automatic Soy & Oat Milk Machine with 10 Blades, 18 Hour Timer, Keep Warm, Measuring Cup, Brush, Recipe Book

Buytra B0CHJKZFR3

Multi-function Nut Milk Maker User Manual

Model: B0CHJKZFR3 | Brand: Buytra

INTRODUCTION

Thank you for choosing the Buytra Multi-function Nut Milk Maker. This appliance is designed to simplify the process of creating fresh, healthy beverages such as nut milk, soy milk, oat milk, rice paste, and juices. With its advanced 10-blade system, large 35oz (1L) capacity, and convenient features like an 18-hour timer and keep-warm function, it offers versatility and ease of use for your daily nutritional needs. Please read this manual thoroughly before operation to ensure safe and efficient use of your new appliance.



The Buytra Multi-function Nut Milk Maker, showcasing its sleek design and the variety of beverages it can produce.

IMPORTANT SAFETY INSTRUCTIONS

To reduce the risk of fire, electric shock, or injury, always follow these basic safety precautions:

- Read all instructions before using the appliance.
- Do not immerse the main unit, power cord, or plug in water or other liquids.
- Close supervision is necessary when any appliance is used by or near children.
- Unplug from outlet when not in use and before cleaning. Allow to cool before putting on or taking off parts.
- Do not operate any appliance with a damaged cord or plug, or after the appliance malfunctions or has been damaged in any manner.
- The appliance generates heat and steam during operation. Exercise caution to avoid burns.
- Ensure the lid is properly aligned and securely closed before operation to prevent E2 errors and ensure safe use.

- Use only accessories and attachments recommended by the manufacturer.
- Do not use outdoors.
- Do not let cord hang over edge of table or counter, or touch hot surfaces.
- Do not place on or near a hot gas or electric burner, or in a heated oven.
- Always attach plug to appliance first, then plug cord into the wall outlet. To disconnect, turn any control to "off", then remove plug from wall outlet.
- Do not use appliance for other than intended household use.

PRODUCT OVERVIEW

The Buytra Nut Milk Maker is designed for efficiency and convenience, featuring a robust internal structure and user-friendly controls.

Key Components and Features:

- **304 Food Grade Stainless Steel Inner Pot:** Ensures durability and food safety.
- **Upgraded 10-Blade 3D Design:** Features 10 durable stainless steel blades, including 4 shark-tooth blades, for efficient processing and smooth results.
- **Double-layer Silicone Ring:** Provides anti-spill and anti-splash protection.
- **Magnetic Induction Lid:** Ensures the machine only operates when the lid is correctly aligned and closed, enhancing safety.
- **Anti-slip Mats:** Located at the base for stability during operation.
- **Smart LED Screen:** Displays function, timer settings, and remaining time.
- **One-Touch Operation:** Simple button controls for various programs.

304 food grade stainless steel inner pot



Double-layer silicone ring, anti-spill and anti-splash



Magnetic induction, start by pointing at the armrest, stop when opening the cover



Anti-slip mats



Internal components and design features, including the 304 food-grade stainless steel inner pot, anti-slip mats, and comfortable handle.

10 Powerful Blades & High Speed and More Smooth Taste



High Temperature Automatic Cleaning & Quickly Remove Dirt



The advanced 10-blade system designed for smooth blending and the automatic cleaning function.

Delay Start Time up to 18 Hours



Visual representation of the product's dimensions and the wide range of healthy beverages it can produce, such as oat milk, almond milk, and various fruit juices.

SETUP

Before first use, please follow these steps:

1. **Unpack:** Carefully remove the appliance and all accessories from the packaging.
2. **Initial Cleaning:** Wash the inner pot and lid with warm, soapy water. Rinse thoroughly and dry completely. Wipe the exterior of the main unit with a damp cloth. Do not immerse the main unit in water.
3. **Placement:** Place the nut milk maker on a stable, flat, and heat-resistant surface, away from direct sunlight or heat sources.
4. **Lid Alignment:** Ensure the lid is correctly aligned with the handle. The protruding part of the lid must align with the handle for the machine to operate and to avoid an "E2" error.

E2" indicates that the lid is not in place and the protruding part of the lid should be aligned with the handle.



Illustration showing the correct alignment of the lid with the handle to ensure proper operation and prevent the E2 error message.

Quickly Blending Ensure the Smooth Taste of the Drink



Others
6 Stainless Steel Blades

VS



Ours
Updated 10-Leaf Blades

The magnetically controlled induction lid ensures the machine starts only when the lid is properly aligned, stopping operation if the cover is opened for safety.

OPERATION

The Buytra Nut Milk Maker offers multiple functions for various beverage preparations. Always ensure the machine is plugged into a suitable power outlet (220V).

Basic Operation Steps:

1. **Add Ingredients:** Pour your desired nuts, soybeans, fruits, or grains into the inner pot. For best results with nuts, use pre-shelled varieties.
2. **Add Water:** Fill the pot with water. Do not exceed the maximum water level indicated inside the pot (1L for hot drinks, 1.2L for cold drinks).
3. **Secure Lid:** Place the lid on the machine, ensuring it is correctly aligned with the handle.
4. **Select Function:** Press the 'Function/Cancel' button to cycle through the available programs: 'Thick Soymilk', 'Soy Milk', 'Rice Paste', 'Complementary Food', 'Boil Water', 'Juice', 'Keep Warm', and 'Cleaning'. The selected function will be displayed on the LED screen.
5. **Start:** The machine will automatically begin the selected program after a brief pause.
6. **Completion:** The machine will beep to indicate the end of the program and automatically shut off.



A visual guide to the three simple steps for operating the machine: adding ingredients, adding water, and selecting the desired function.



The intuitive control panel with one-touch buttons for various functions like Soy Milk, Rice Paste, Juice, and Cleaning.

35 OZ - 40 OZ Nut Milk Maker

Make your favorite healthy milk/juice



The delay start function allows users to set a program up to 18 hours in advance, ensuring fresh beverages are ready when needed.

Specific Functions and Times:

Menu	Working Time (Approx.)
Thick Soymilk	36 minutes
Soy Milk	28 minutes
Rice Paste	30 minutes
Complementary Food	36 minutes
Boil Water	12 minutes
Juice	3 minutes
Keep Warm	Default 6 hours

Menu	Working Time (Approx.)
Cleaning	1 minute

Approximate working times for each function. Note that actual times may vary slightly based on ingredients and conditions.



The versatility of the machine, capable of making soy milk, nut milk, rice paste, fruit juice, hot water, and baby food.

MAINTENANCE & CLEANING

Regular cleaning ensures the longevity and optimal performance of your nut milk maker.

Automatic Cleaning:

The machine features an automatic cleaning function:

1. After use, add a small amount of water to the inner pot.
2. Select the 'Cleaning' function on the control panel.
3. The machine will run a short cleaning cycle (approx. 1 minute).

Manual Cleaning:

For thorough cleaning, especially after making thick beverages:

- Unplug the machine and allow it to cool completely.
- Remove any remaining liquid or residue from the inner pot.
- Use the provided cleaning brush to scrub the inner pot and blades.
- Wash the lid and inner pot with warm, soapy water. Rinse thoroughly.

- Wipe the exterior of the main unit with a damp cloth. Do not use abrasive cleaners or immerse the main unit in water.
- Ensure all parts are completely dry before storing.

TROUBLESHOOTING

If you encounter issues with your nut milk maker, please refer to the table below for common problems and solutions.

Problem	Possible Cause	Solution
Machine displays "E2" error	Lid is not properly aligned or closed.	Ensure the protruding part of the lid is aligned with the handle and the lid is securely closed.
Machine does not start	Not plugged in; power outage; lid not closed properly.	Check power connection; ensure lid is correctly aligned and closed.
Beverage is not smooth enough	Ingredients not pre-soaked (if required); too many ingredients; insufficient water.	Ensure ingredients like soybeans are properly soaked; do not overfill; ensure water level is adequate. Use pre-shelled nuts.
Overflow during operation	Exceeded maximum water level.	Do not exceed the MAX fill line (1L for hot, 1.2L for cold).
Unusual noise during operation	Foreign object inside; machine not stable.	Unplug and check for foreign objects; ensure machine is on a stable, flat surface.

SPECIFICATIONS

Feature	Detail
Brand	Buytra
Model	B0CHJKZFR3
Capacity	35 Fluid Ounces (1L for hot, 1.2L for cold)
Heating Power	800W
Rated Frequency	50 Hz
Voltage	220 Volts
Blades	Upgraded 10-blade 3D design
Special Features	Automatic Cleaning, Heating, Keep Warm Setting, 18-hour Delay Start

Feature	Detail
Product Dimensions	5.4"D x 5.4"W x 4.1"H (Approximate)
Item Weight	3.74 pounds
Included Components	Soy Milk Maker, Power Cord, Manual, Cleaning Brush, Measuring Cup

Detailed technical specifications for the Buytra Multi-function Nut Milk Maker.

WARRANTY & SUPPORT

This Buytra Multi-function Nut Milk Maker comes with a limited warranty. For specific warranty terms and conditions, please refer to the warranty card included in your product packaging or contact Buytra customer support. If you have any questions, require technical assistance, or need to report an issue, please contact our customer support team. Contact information can typically be found on the product packaging or on the official Buytra website.

© 2024 Buytra. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

