

[Manuals.plus](#) /

› [ASHATA](#) /

› ASHATA Q8 Unlocked Cell Phone for Seniors User Manual

ASHATA Q8

ASHATA Q8 Unlocked Cell Phone for Seniors User Manual

Model: Q8 (ASHATAynf1ho3gtw-11)

1. INTRODUCTION

Welcome to the user manual for your ASHATA Q8 Unlocked Cell Phone for Seniors. This guide provides detailed instructions on how to set up, operate, and maintain your device. Designed with ease of use in mind, the ASHATA Q8 features large buttons, a clear display, and essential functions like an SOS key and super flashlight, making it ideal for elderly users.

Please read this manual thoroughly to ensure proper use and to maximize the benefits of your new phone.



Figure 1: Front and back view of the ASHATA Q8 Unlocked Cell Phone. The phone features a clear display, large keypad with an orange SOS button, and a durable black casing.

2. SETUP

2.1 Package Contents

Before you begin, ensure all items are present in the package:

- ASHATA Q8 Cell Phone
- Rechargeable Battery (3000mAh)
- USB Cable



Figure 2: The ASHATA Q8 phone, its rechargeable battery, and the included USB charging cable.

2.2 Installing the Battery

1. Gently remove the back cover of the phone.
2. Align the battery contacts with the terminals inside the phone.
3. Insert the battery firmly into its compartment.
4. Replace the back cover, ensuring it clicks into place.

2.3 Installing SIM Cards

The ASHATA Q8 supports dual SIM cards (2G GSM quad band 850, 900, 1800, 1900). This allows you to use two different phone numbers or networks simultaneously.

1. With the back cover and battery removed, locate the SIM card slots.
2. Carefully insert your SIM card(s) into the designated slots, ensuring the gold contacts face downwards and the notched corner aligns correctly.
3. Reinsert the battery and replace the back cover.



Figure 3: The ASHATA Q8 phone with its back cover removed, revealing the battery compartment and dual SIM card slots.

Dual SIM Cards Slot

2G GSM: 850 900 1800 1900



Figure 4: Illustration of the dual SIM card slots and the supported 2G GSM frequencies (850, 900, 1800, 1900).

2.4 Charging the Battery

Before first use, fully charge the phone's battery.

1. Connect the USB cable to the charging port on the phone.
2. Connect the other end of the USB cable to a compatible USB power adapter (not included) or a computer's USB port.
3. The charging indicator on the phone will illuminate. Once fully charged, the indicator may change color or turn off.

2.5 Powering On/Off

- **To Power On:** Press and hold the Power/End Call button (usually red) until the screen lights up.
- **To Power Off:** Press and hold the Power/End Call button until the power-off options appear, then confirm.

3. OPERATING INSTRUCTIONS

3.1 Making and Receiving Calls

- **Making a Call:**
 1. Enter the phone number using the keypad.
 2. Press the Call button (usually green) to initiate the call.
 3. To end the call, press the End Call button (usually red).
- **Receiving a Call:**
 1. When the phone rings, press the Call button to answer.
 2. To end the call, press the End Call button.



9 emergency contacts can be set
One touch dialing
Dual LED lights one touch flashlight
Voice conversion function
including male voice, female voice
and child voice exchange

Figure 5: The ASHATA Q8 phone displaying its large, easy-to-read buttons and clear screen, designed for user convenience.

3.2 Using the SOS Function

The SOS key is designed for emergencies, allowing you to quickly contact pre-set numbers.

1. **Setting SOS Contacts:** Navigate to the SOS settings in the phone's menu. You can set up to 9 emergency contacts.
2. **Activating SOS:** In an emergency, press and hold the dedicated SOS button (orange button on the keypad). The phone will automatically dial the emergency contacts in sequence and send an emergency SMS message.



Figure 6: A close-up view highlighting the prominent orange SOS button on the ASHATA Q8 keypad, designed for quick access in emergencies.

3.3 Using the Super Flashlight

The phone is equipped with a powerful flashlight for convenience.

- **To Turn On/Off:** Locate the dedicated flashlight button on the side of the phone or access it through the phone's menu. Press or slide the button to activate/deactivate the flashlight.



Figure 7: The ASHATA Q8 phone with its dual LED flashlight actively illuminated, demonstrating its brightness.

3.4 Voice Assistance and Conversion

The ASHATA Q8 includes voice assistance features and a voice conversion function.

- **Voice Assistance:** Specific keys or menu options may activate voice prompts for navigation or reading out numbers. Refer to the phone's menu for detailed settings.
- **Voice Conversion:** This feature allows you to change your voice during a call to a male, female, or child voice. Access this function through the call options menu during an active call.

3.5 Multimedia and Basic Functions

The phone includes basic multimedia and utility functions accessible via the main menu.

- **Navigation:** Use the directional keys and the "OK" button to navigate through the menu.
- **Menu Options:** Access features such as contacts, messages, call history, settings, and other utilities.




Figure 8: The ASHATA Q8's screen displaying various multimedia and utility icons, including messages, camera, and music.

4. MAINTENANCE

4.1 Cleaning Your Phone

- Use a soft, dry, lint-free cloth to clean the phone's screen and body.
- Avoid using harsh chemicals, cleaning solvents, or strong detergents.
- Do not expose the phone to excessive moisture.

4.2 Battery Care

- To prolong battery life, avoid fully discharging the battery frequently.
- Charge the phone regularly, but do not leave it connected to a charger for extended periods after it is fully charged.
- Store the phone in a cool, dry place when not in use for long durations.



Figure 9: An illustration depicting the ASHATA Q8 phone's capability for long standby time, emphasizing its 3000mAh battery.

5. TROUBLESHOOTING

Problem	Possible Cause	Solution
Phone does not power on	Low battery; Battery not installed correctly	Charge the battery; Reinstall the battery ensuring proper contact.
Cannot make/receive calls	No network signal; SIM card not installed correctly; SIM card not activated	Move to an area with better signal; Reinstall SIM card(s); Contact your service provider to activate SIM.
Poor call quality	Weak network signal; Obstructions	Move to an open area; Ensure nothing is blocking the phone's speaker or microphone.
SOS function not working	No emergency contacts set; No network signal	Set up emergency contacts in the SOS settings; Ensure phone has network coverage.

6. SPECIFICATIONS

Feature	Detail
Brand	ASHATA
Model Name	Q8 (ASHATAynf1ho3gtw-11)
Connectivity Technology	Bluetooth, USB
Cellular Technology	2G GSM (850, 900, 1800, 1900)
Wireless Carrier	Unlocked
Screen Size	2.4 Inches
Memory Storage Capacity	32 MB

Feature	Detail
Battery Capacity	3000 Milliamp Hours
SIM Card Slot Count	Dual SIM
Color	Black
Item Weight	9 ounces
Package Dimensions	5.91 x 3.54 x 2.76 inches

7. WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the documentation provided with your purchase or contact ASHATA customer service directly. Keep your proof of purchase for warranty claims. You can visit the ASHATA store for more information:[ASHATA Store on Amazon](#)

© 2023 ASHATA. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0CKYMPFDL>

More documents and user manuals: <https://manuals.plus/>