

Yuposl YPF01

Yuposl Automatic Pet Feeder YPF01 User Manual

Model: YPF01

1. INTRODUCTION

Thank you for choosing the Yuposl Automatic Pet Feeder. This device is designed to provide scheduled and portion-controlled meals for your cats and small dogs, ensuring their health and well-being even when you are away. Please read this manual thoroughly before use to ensure proper operation and maintenance.



The Yuposl Automatic Pet Feeder, Model YPF01, in black.

2. PRODUCT FEATURES

- **Timed and Portion-Controlled Feeding:** Schedule up to 6 meals per day, with 1 to 16 portions per meal, to prevent overeating or missed meals.
- **Anti-Clogging Design:** Compatible with dry food sizes from 2-15mm. Features an automatic reverse rotation mechanism to clear blockages, ensuring consistent feeding.
- **Food Freshness Preservation:** Multi-sealed structure with a reinforced lid seal and desiccant compartment keeps food fresh and prevents insect intrusion.
- **2-Way Power Supply:** Operates via Type-C power adapter (included) or 3 D-size alkaline batteries (not included) for up to 180 days, providing backup during power outages.
- **Easy to Clean:** Food-grade ABS shell and a removable 15° tilted stainless steel bowl for easy washing. Note: The main unit is not washable; wipe with a damp towel.
- **Ideal for Multiple Pets:** Allows for flexible placement to prevent food competition, supporting healthy eating habits for each pet.

3. PACKAGE CONTENTS

Please check that all items are present and in good condition upon unpacking:

- Automatic Pet Feeder Main Unit
- Stainless Steel Food Bowl
- Bowl Holder
- Top Lid with Desiccant Compartment
- Desiccant Pack
- USB Type-C Power Cable (1.5m braided, chew-resistant)
- Power Adapter
- User Manual

4. SETUP

1. **Assemble the Feeder:** Place the main unit on a flat, stable surface. Attach the bowl holder to the main unit, then insert the stainless steel bowl into the holder.
2. **Power Supply:**
 - **AC Power:** Connect the USB Type-C cable to the port at the bottom of the feeder and plug the adapter into a wall outlet.
 - **Battery Backup:** For power outage protection or cordless use, install 3 D-size alkaline batteries (not included) into the battery compartment at the bottom of the unit.
3. **Fill with Food:** Open the top lid by sliding the safety lock to the unlocked position and pressing the two pinch grips. Insert the desiccant pack into its designated compartment on the underside of the lid. Pour dry pet food (2-15mm size) into the food tank. Close the lid securely and slide the safety lock to the locked position.



Ensure the lid is securely locked for freshness.

5. OPERATING INSTRUCTIONS

5.1 Control Panel Overview

The feeder features a user-friendly control panel with a digital display and several buttons:

- **Lock/Unlock Button:** Press and hold to unlock the panel for setting.
- **Set Button:** Used to enter and confirm settings.
- **+/- Buttons:** Adjust values (time, portions).
- **Manual Feed Button:** Dispenses a single portion instantly.



The intuitive control panel for easy meal management.

5.2 Setting the Current Time

1. Press and hold the **Lock/Unlock button** for 3 seconds until the padlock icon disappears.
2. Press and hold the **Set button** for 3 seconds until the hour digit starts flashing.
3. Use the **+/- buttons** to adjust the hour. Press **Set** to confirm.
4. The minute digit will flash. Use the **+/- buttons** to adjust the minutes. Press **Set** to confirm.
5. The AM/PM indicator will flash. Use the **+/- buttons** to select AM or PM. Press **Set** to confirm and exit time setting.

5.3 Programming Meal Plans

The feeder supports up to 6 meal times per day.

1. Ensure the control panel is unlocked (no padlock icon). If locked, press and hold the **Lock/Unlock button** for 3 seconds.
2. Press the **Set button** once to enter Meal 1 setting. The meal number (e.g., '1') and hour digit will flash.
3. Use the **+/- buttons** to set the desired feeding hour. Press **Set** to confirm.
4. Adjust minutes and AM/PM as described in