Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

GoGonova GT01006

GoGonova 20V Cordless Full Size Glue Gun

Model: GT01006

Manufactured by GoGonova

1. Important Safety Information

Please read all safety warnings and instructions carefully before operating this product. Failure to follow the warnings and instructions may result in electric shock, fire, and/or serious injury.

- **High Temperature:** The nozzle and melted glue reach high temperatures. Avoid direct contact with skin to prevent burns.
- **Ventilation:** Use in a well-ventilated area.
- **Children:** Keep out of reach of children. Adult supervision is required if children are present.
- **Battery Safety:** Use only the specified GoGonova 20V 1.5Ah Lithium-ion battery. Do not attempt to use other brands or battery types. Fully charge the battery before first use.
- **Dripless Design:** While designed to be dripless, always exercise caution and use a protective mat to prevent accidental drips on surfaces.

2. Package Contents

Verify that all items listed below are included in your package:

- GoGonova 20V Cordless Full Size Glue Gun
- 1.5Ah Lithium-ion Battery
- Battery Charger (DC Adapter)
- 12 Pcs Full Size Glue Sticks (0.43" diameter)

3. Setup Instructions

1. **Charge the Battery:**
   Before first use, fully charge the 1.5Ah Lithium-ion battery using the provided DC adapter. The battery indicator will show charging status.



Image: The complete GoGonova glue gun kit, including the pink glue gun, 20V battery, charger, and a pack of 12 glue sticks.

2. **Attach the Battery:**

   Align the battery with the base of the glue gun handle and slide it firmly into place until it clicks securely. Ensure it is properly seated.

3. **Insert Glue Stick:**

   Insert a full-size glue stick (0.43" diameter) into the opening at the rear of the glue gun. Push it gently until it stops. Do not force it.

4. Operating Instructions

1. **Power On:**

   Press and hold the power button (usually marked with a power symbol) on the base of the handle for a few seconds until the LCD digital display illuminates.

2. **Adjust Temperature:**

   Use the '+' and '-' buttons next to the power button to adjust the desired temperature. The LCD display will show the

current temperature, which can be set between 212°F (100°C) and 392°F (200°C) with ±1°C/°F precision. Allow approximately 120 seconds for the glue gun to reach the set temperature.



Image: Close-up of the GoGonova glue gun's LCD digital display, showing the temperature setting (392°F) and the temperature adjustment buttons.



Image: An illustration of the GoGonova 20V Cordless Glue Gun, highlighting its copper nozzle, 120s fast heating, 60W heavy-duty power, temperature display, rechargeable battery, and temperature adjustment/power ON/OFF buttons.

3. **Apply Glue:**

   Once the desired temperature is reached, gently squeeze the trigger to dispense melted glue from the nozzle. The dripless design helps prevent excess glue from dripping when the trigger is released.

4. **Power Off:**

   After use, press and hold the power button until the LCD display turns off. Remove the battery for storage if not in continuous use.

5. Maintenance

- **Cleaning the Nozzle:** Allow the glue gun to cool completely. Gently wipe any excess glue from the nozzle with a dry cloth. Do not use water or solvents.
- **Storage:** Store the glue gun in a dry, cool place, away from direct sunlight and moisture. Remove the battery if storing for extended periods.
- **Battery Care:** Store the battery in a cool, dry place. Avoid extreme temperatures.

6. Troubleshooting

- **Glue gun not heating:**
  - Ensure the battery is fully charged and properly attached.
  - Verify the power button has been pressed and held until the LCD display is active.
- **Glue not flowing:**
  - Check that a glue stick is fully inserted and has reached the heating chamber.
  - Confirm the temperature setting is appropriate for the glue stick type and allow sufficient time for heating.
- **Battery not holding charge/short operating time:**
  - Ensure the battery was fully charged before use. A full charge provides approximately 30-40 minutes of operation.
  - Verify that only GoGonova batteries are used, as other brands are not compatible.

7. Specifications

Model Number	GT01006
Brand	GoGonova
Power Source	Battery Powered
Voltage	20 Volts
Wattage	30 watts (Superior 60W power for heavy-duty tasks)
Battery Type	1.5Ah Lithium-ion
Temperature Range	212°F to 392°F (100°C to 200°C)
Pre-heating Time	Approximately 120 seconds
Glue Stick Diameter	0.43 inches (Full Size)
Features	LCD Digital Display, Dripless Nozzle, Anti-Scald Nozzle, Ergonomic Design
Compatible Materials	Fabric, Plastic, Wood

8. Warranty and Support

GoGonova products are designed for reliability and performance. For any questions, technical support, or warranty claims, please contact GoGonova customer service. Refer to the 'Thank You' card included in your package for specific contact details or visit the official GoGonova website.

Please retain your proof of purchase for warranty purposes.

© 2025 GoGonova. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question

and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0CQK2SVNQ

More documents and user manuals: **https://manuals.plus/**