

Groview Groview-B2D-US

GROVIEW Mini Projector Bluetooth User Manual

Model: Groview-B2D-US

Brand: Groview

1. INTRODUCTION

This manual provides essential instructions for the safe and efficient operation of your GROVIEW Mini Projector Bluetooth, Model Groview-B2D-US. Please read this manual thoroughly before using the projector and retain it for future reference.

The Groview-B2D-US is a compact and portable projector featuring electric focus, Bluetooth 5.1 connectivity, and a fully sealed optical engine designed for reduced noise and extended lifespan. It supports Full HD 1080P input with a native 720P resolution and offers a digital zoom function.

2. SAFETY INFORMATION

- Do not look directly into the projector lens when the lamp is on.
- Ensure proper ventilation around the projector to prevent overheating. Do not block ventilation openings.
- Use only the power adapter supplied with the projector.
- Do not expose the projector to rain, moisture, or extreme temperatures.
- Avoid placing the projector on unstable surfaces.
- Do not attempt to disassemble or repair the projector yourself. Contact qualified service personnel for assistance.
- Keep the projector away from children and pets.

3. WHAT'S IN THE Box

Verify that all items are present in the packaging:

- 1 x Groview Electric Focus Projector
- 1 x HDMI Cable
- 1 x Power Cord
- 1 x Remote Control
- 1 x User Manual (this document)

4. PRODUCT OVERVIEW

4.1 Projector Components

The following image illustrates the main components of the Groview Mini Projector.



Figure 1: Front and side view of the Groview Mini Projector, showing the lens and ventilation.

4.2 Input/Output Ports

The rear panel of the projector features various ports for connecting external devices.

MULTIPLE DEVICE CONNECTION



Figure 2: Rear panel of the projector, displaying the HDMI, USB, and Audio ports.

- **HDMI Port:** Connects to devices such as TV sticks, laptops, game consoles, and Blu-ray players.
- **USB Port:** Connects to USB flash drives for media playback.
- **Audio Port (3.5mm Jack):** Connects to external speakers or headphones.
- **IR Receiver:** For remote control signals.

5. SETUP

5.1 Power Connection

1. Connect the power cord to the projector's power input.
2. Plug the other end of the power cord into a power outlet.

5.2 Projector Placement

Place the projector on a stable, flat surface. For optimal image quality, position the projector perpendicular to the projection surface (wall or screen). The projector can create a large image from a relatively short distance.

5.3 Focus Adjustment

The Groview-B2D-US features electric focus, allowing for precise image clarity adjustment using the remote control.

2-SECOND SMOOTH ELECTRIC FOCUS



Figure 3: Adjusting the projector's focus using the remote control for a clear image.

1. Turn on the projector.
2. Point the remote control at the projector.
3. Press the dedicated focus buttons (usually marked with 'F+' and 'F-' or similar icons) on the remote until the projected image is sharp and clear.

5.4 Keystone Correction

The projector includes a keystone adjustment slider on the rear panel. This allows you to correct trapezoidal distortion if the projector is not perfectly aligned with the screen. Adjust the slider until the

image appears rectangular.

5.5 Initial Power On

Press the power button on the projector or the remote control to turn on the device. The projector will boot up and display the main interface.

6. OPERATING INSTRUCTIONS

6.1 Connecting Devices

The projector offers multiple connectivity options:

- **HDMI:** Connect an HDMI cable from your source device (e.g., TV Stick, laptop, game console) to the projector's HDMI port. Select the HDMI input source from the projector's menu.
- **USB:** Insert a USB flash drive into the USB port. The projector's media player will typically detect the drive automatically, allowing you to browse and play supported media files.
- **Bluetooth 5.1:** Connect to external Bluetooth speakers or headphones for enhanced audio.

BLUETOOTH 5.1 & HIFI SPEAKER

Connect to a Speaker and Enjoy Surround Sound



Figure 4: The projector wirelessly connected to Bluetooth headphones and a speaker.

1. Enable Bluetooth on your external audio device and set it to pairing mode.
2. On the projector, navigate to the Bluetooth settings menu.
3. Select your device from the list of available devices to pair.

Note: Bluetooth does not support smartphone mirroring.

6.2 Smartphone Connection Methods

To connect a smartphone, an adapter is required:



Figure 5: Illustration of connecting iOS devices via Lightning to HDMI adapter and Android devices via Micro USB/Type C to HDMI adapter or Google Chromecast.

- **iOS Devices:** Use a Lightning to HDMI adapter cable.
- **Android Devices:** Use a Micro USB/Type C to HDMI adapter cable or a Google Chromecast.

6.3 Navigation and Menu

Use the arrow buttons on the remote control to navigate through the projector's on-screen menu. The 'OK' or 'Enter' button confirms selections, and the 'Back' or 'Return' button goes back to the previous menu.

6.4 Digital Zoom Function

The projector features a digital zoom function, allowing you to adjust the image size from 75% to 100% without moving the projector.




Figure 6: Visual representation of the digital zoom feature, scaling the projected image from 100% down to 75%.

Access the zoom settings through the projector's menu and use the remote control to adjust the desired size.

6.5 Remote Control Usage

The included remote control operates the projector's functions. Ensure batteries are correctly installed. *Note: A coin may be needed to open the battery compartment.*

7. MAINTENANCE

7.1 Cleaning

- **Lens:** Gently wipe the lens with a soft, lint-free cloth specifically designed for optical surfaces. Do not use abrasive cleaners.
- **Exterior:** Wipe the projector's exterior with a soft, dry cloth. For stubborn marks, a slightly damp cloth can be used, followed by a dry one.

7.2 Dust-proof Design

The Groview-B2D-US features a fully sealed optical engine, which helps prevent dust and debris from entering the projector and affecting image quality or lifespan.




Figure 7: An internal view of the projector, illustrating its advanced dust-proof sealed optical engine.

7.3 Storage

When not in use, store the projector in a cool, dry place, away from direct sunlight and extreme temperatures. Use the lens cap to protect the lens from dust and scratches.

8. TROUBLESHOOTING

- **No Image:** Check power connection, input source selection, and ensure the lens cap is removed. Verify the connected device is powered on and outputting a signal.
- **Blurry Image:** Adjust the electric focus using the remote control. Ensure the projector is placed at an appropriate distance from the screen.
- **No Sound:** Check the volume settings on both the projector and the connected source device. If using Bluetooth, ensure the external audio device is properly paired and its volume is up.
- **Remote Control Not Working:** Check the batteries in the remote control and ensure there are no obstructions between the remote and the projector's IR receiver.
- **Overheating Warning:** Ensure ventilation openings are not blocked. Turn off the projector and allow it to cool down before restarting.

For further assistance, please contact Groview customer support.

9. SPECIFICATIONS

Feature	Specification
Brand	Groview
Model Number	Groview-B2D-US



Native Resolution	1280 x 720 pixels
Supported Resolution	1080P Full HD
Connectivity Technology	3.5mm Jack, Bluetooth 5.1, HDMI, USB
Special Features	Electric Focus, Fully Sealed Optical Engine, Mini size & Lightweight, 150" Display, Digital Zoom (75%-100%)
Recommended Uses	Indoor/Outdoor
Item Weight	2.99 pounds
Product Dimensions	4.8 x 5.7 x 6.9 inches
Color	Gray

10. WARRANTY AND SUPPORT

Groview products are designed for reliability and performance. For information regarding warranty coverage and customer support, please refer to the warranty card included with your purchase or visit the official Groview website. Our service team is available to assist with any product-related inquiries.

© 2024 Groview. All rights reserved.

Related Documents - Groview-B2D-US

	<p><u>GROVIEW JQ818C Projector User Manual: Features, Setup, and Troubleshooting</u></p> <p>Comprehensive user manual for the GROVIEW JQ818C projector. Learn about product overview, specifications, connecting devices (HDMI, USB, wireless), projector settings, and troubleshooting common issues. Get detailed setup instructions and support contact information.</p>
	<p><u>GROVIEW JQ818C Projector User Manual - Setup and Operation Guide</u></p> <p>Official user manual for the GROVIEW JQ818C projector. This guide details setup, operation, safety warnings, product specifications, and multimedia support for this 1080P, WiFi, and Bluetooth enabled projector. Learn to connect and use your device for an optimal home theater experience.</p>

时间:	2023-2-10	产品型号:	JQ818C
尺寸:	105*145mm		
重量:	105g	包装:	纸盒

[GROVIEW JQ818C Projector User Manual](#)


Comprehensive user manual for the GROVIEW JQ818C projector, covering setup, operation, specifications, connectivity, and safety guidelines for an enhanced visual experience.



User Manual

[GROVIEW JQ818C Projector User Manual: Features, Setup, and Troubleshooting](#)

Comprehensive user manual for the GROVIEW JQ818C projector. Learn about product overview, specifications, connecting devices (HDMI, USB, wireless), projector settings, and troubleshooting common issues. Get detailed setup instructions and support contact information.



Please read this manual carefully before using the projector.

[GROVIEW JQ818C Projector User Manual - Setup and Operation Guide](#)

Official user manual for the GROVIEW JQ818C projector. This guide details setup, operation, safety warnings, product specifications, and multimedia support for this 1080P, WiFi, and Bluetooth enabled projector. Learn to connect and use your device for an optimal home theater experience.

时间:	2023-2-10	产品型号:	JQ818C
尺寸:	105*145mm		
重量:	105g	包装:	纸盒

[GROVIEW JQ818C Projector User Manual](#)

Comprehensive user manual for the GROVIEW JQ818C projector, covering setup, operation, specifications, connectivity, and safety guidelines for an enhanced visual experience.