

Q Acoustics M40

Q Acoustics M40 Powered Speakers User Manual

Model: M40 | Brand: Q Acoustics

INTRODUCTION

The Q Acoustics M40 powered micro-tower wireless audio system offers a convenient and effective solution for immersive, full-size sound in your home without requiring large, imposing loudspeakers. Designed for optimal audio performance and seamless integration into any living space, the M40 provides high-resolution wireless streaming and versatile connectivity options.



Image: Front view of the Q Acoustics M40 speakers in black, showcasing their sleek, tall design.

SETUP

Unpacking and Contents

Carefully unpack all components from the box. Ensure all items listed below are present:

- 1 Powered speaker (approx. 27 lbs 5 oz)


- 1 Passive speaker (approx. 26 lb)
- 1 Remote handset (including batteries)
- 1 Speaker cable (13.1 feet)
- 1 US power cord (5.9 feet)
- 4 Rear Stabilisers
- 8 M5 screws
- 8 Spike feet
- 8 Spike covers
- 2 Foam bungs
- 1 User manual (this document)

Each speaker measures approximately W10 x D11.7 x H28 inches.

Speaker Placement

The M40 speakers are designed to perform optimally in various room environments. For best sound quality, consider the following:

- **Stereo Imaging:** Position the speakers to form an equilateral triangle with your primary listening position for optimal stereo imaging.
- **Distance from Walls:** While compact, the M40 benefits from some distance from rear and side walls. Experiment with placement to find the best balance of bass response and soundstage.
- **EQ Switch:** The M40 features a clever EQ switch to optimize audio performance based on the speaker's position in the room (e.g., corner, against a wall, or in free space). Adjust this switch according to your setup.



Discreet design.
Towering sound.

Measuring just 71cm tall, the M40
boasts a unique ultra-compact and
room-friendly micro-tower design.

Image: Q Acoustics M40 speakers in walnut, demonstrating their discreet design and how they blend into a home environment.

Connecting Your Speakers

The M40 system includes one powered speaker and one passive speaker. Connect the passive speaker to the powered speaker using the provided speaker cable. Ensure correct polarity (red to red, black to black) for optimal sound.

The powered speaker offers multiple input options for various audio sources:

- **Bluetooth 5.0:** For wireless streaming from smartphones, tablets, and laptops. Supports aptX HD and aptX Low Latency for high-resolution audio (up to 24bit/48kHz).
- **2 x Phono (RCA):** For connecting devices like CD players or pre-amplified turntables.
- **3.5mm Jack (AUX):** For general audio devices.
- **Optical (S/PDIF):** For connecting TVs, set-top boxes, or gaming consoles.
- **USB Type B:** For connecting to a computer, supporting high-resolution audio up to 24bit/192kHz.
- **Sub Out:** An output for connecting an optional external subwoofer for enhanced bass.

Connect the power cord to the powered speaker and then to a wall outlet. The system has a peak power output of 2 x 100W and continuous power of 2 x 50W.




Image: Detailed view of the M40's rear panel, highlighting the comprehensive range of digital and analog input connections.



Convenience
and power
2 x 100 watts of built-in
amplification means
no extra boxes required.

Image: The M40 speaker integrated into a home setup, demonstrating its ability to connect with various audio sources like a turntable.

OPERATING INSTRUCTIONS

Power On/Off

To power on the speakers, ensure the power cord is connected and press the power button on the remote control or the top of the powered speaker. The LED indicator will illuminate. To power off, press the power button again.

Source Selection

Use the input selector buttons on the remote control or the powered speaker to cycle through the available audio sources (Bluetooth, AUX, Optical, USB, Phono).

Bluetooth Pairing

1. Select Bluetooth as the input source on the M40 speakers. The Bluetooth indicator light will flash, indicating pairing mode.
2. On your device (smartphone, tablet, laptop), enable Bluetooth and search for "Q Acoustics M40" in the list of available devices.
3. Select the M40 to pair. Once connected, the Bluetooth indicator light on the speaker will become solid.
4. You can now stream audio wirelessly from your device to the M40 speakers.

Wireless streaming

High-resolution wireless streaming of popular music services via Bluetooth® and aptX™ HD.



Image: Demonstrating high-resolution wireless streaming via Bluetooth from a smartphone to the M40 speakers.

Adjusting EQ Settings

The M40 features an EQ switch on the powered speaker to optimize sound based on speaker placement. Refer to the diagram or markings on the speaker for specific settings (e.g., 'Corner', 'Wall', 'Free Space'). Adjust this switch to match your speaker's position for the most balanced audio output.



Image: Illustrates the concept of optimized audio performance through the EQ switch, adapting sound to room positioning.

MAINTENANCE

To ensure the longevity and optimal performance of your Q Acoustics M40 speakers, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry, lint-free cloth to clean the speaker cabinets. Avoid abrasive cleaners, solvents, or polishes, as they may damage the finish.
- **Grilles:** The speaker grilles are designed to protect the drivers. If they become dusty, gently brush them with a soft brush or use a low-power vacuum cleaner with a brush attachment.
- **Placement:** Avoid placing speakers in direct sunlight, near heat sources, or in areas with high humidity. Ensure adequate ventilation around the powered speaker.
- **Cables:** Periodically check all cable connections for secure fit. Avoid kinking or pinching cables.

TROUBLESHOOTING

If you encounter issues with your M40 speakers, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
No power / Speakers do not turn on	Power cord not connected; Power outlet issue; Internal fault.	Ensure power cord is securely plugged into the speaker and a working wall outlet. Try a different outlet. If the issue persists, contact customer support.
No sound	Incorrect input source selected; Volume too low; Speaker cable disconnected; Bluetooth not paired.	Verify the correct input source is selected. Increase volume. Check the speaker cable connection between powered and passive speakers. Re-pair Bluetooth device.
Bluetooth connection unstable or drops	Device too far from speakers; Interference; Multiple devices trying to connect.	Move your device closer to the speakers. Avoid placing speakers near other wireless devices. Disconnect other Bluetooth devices from the speakers.
Distorted sound	Volume too high; Poor audio source quality; Incorrect EQ setting.	Reduce volume. Try a different audio source. Adjust the EQ switch on the powered speaker to match room placement.
Speakers turn off automatically (unexpectedly)	Auto-standby feature; Power supply issue.	The speakers may have an auto-standby feature to save power. If they turn off during active use, ensure stable power supply. If the problem is frequent, contact support.

SPECIFICATIONS

The following table details the technical specifications of the Q Acoustics M40 speakers:

Feature	Detail
Model Name	M40
Speaker Type	Tower
Connectivity Technology	Bluetooth
Wireless Communication Technology	Bluetooth 5.0 (aptX HD, aptX Low Latency)
Audio Output Mode	Stereo
Speaker Maximum Output Power	2 x 100 Watts (Peak)
Continuous Power	2 x 50 Watts
Mid/Bass Driver	2 x 125 mm (5.0 inches)
Tweeter Diameter	0.9 inches
Frequency Response (-6dB)	38 Hz – 22 kHz
Crossover Frequency	2.5 kHz
Inputs	2 x Phono, 3.5mm Jack, Optical (S/PDIF), USB Type B
USB Max. Resolution	24 bit/192 kHz
Outputs	Sub out
Product Dimensions (W x D x H)	10"D x 11.7"W x 28"H (with stabilisers)
Item Weight	76.1 pounds (total for pair)
Color Options	Black, Walnut, White
Control Method	Remote, Button
Manufacturer	Q Acoustics

Feature	Detail
Country of Origin	China

Tech specs

Mid/Bass unit 2 x 125 mm (5.0 in)

Treble unit 1 x 22 mm (0.9 in)

Crossover frequency 2.5 kHz

Frequency response (-6dB) 38 Hz – 22 kHz

Wireless connectivity

Bluetooth® 5.0, aptX™, aptX™ HD, aptX™ Low Latency, SBC, AAC

Inputs

2 x Phono, 3.5mm Jack, Optical (S/PDIF), USB Type B connector (Max. resolution: 24 bit/192 kHz)

Outputs Sub out

Peak power output: 2 x 100 W

Dimensions (W x H x D) 250 mm x 710 mm x 296 mm (10" x 28" x 11.7") with stabilisers

Image: A visual summary of the M40's technical specifications for quick reference.

WARRANTY AND SUPPORT

Warranty Information

The Q Acoustics M40 speakers come with a limited warranty. For specific details regarding the warranty period and coverage, please refer to the warranty card included in your product packaging or visit the official Q Acoustics website.

Optional protection plans may be available for extended coverage:

- 2-Year Protection Plan
- 3-Year Protection Plan

- Complete Protect (monthly plan)

Please note that return policies typically allow for a 30-day refund/replacement period from the date of purchase.

Customer Support


For technical assistance, troubleshooting beyond this manual, or warranty claims, please contact Q Acoustics customer support. You can find contact information on the official Q Acoustics website or through the retailer where you purchased the product.

Visit the official [Q Acoustics Store](#) for more information and support resources.


© 2024 Q Acoustics. All rights reserved.

Related Documents - M40

 Sasandu-TX User Manual	SB Acoustics Sasandu-TX User Manual User manual for the SB Acoustics Sasandu-TX floor-standing speakers, detailing technical specifications, assembly instructions, and part lists.
	Mount Baker Theatre Technical Specifications and Venue Guide Comprehensive technical specifications, venue layout, equipment inventory, and operational policies for Mount Baker Theatre, including details on lighting, sound, carpentry, and stage facilities.
 CA-3080 / CA-3090 Owner's Guide Powered Speaker System with Control Pod	Cyber Acoustics CA-3080 CA-3090 Powered Speaker System Owner's Guide Comprehensive owner's guide for the Cyber Acoustics CA-3080 and CA-3090 3-piece powered speaker systems with control pod, covering setup, connections, controls, features, and troubleshooting.
 CA-3080 / CA-3090 Owner's Guide Powered Speaker System with Control Pod	Cyber Acoustics CA-3080 CA-3090 Powered Speaker System Owner's Guide The Cyber Acoustics CA-3080 and CA-3090 are three-piece powered speaker systems with a control pod, designed for superior audio performance with computers, smartphones, and other audio devices. This owner's guide provides setup, connection, control, and troubleshooting instructions.

 CA-3080 / CA-3090 Owner's Guide Powered Speaker System with ControlPad	Cyber Acoustics CA-3080 CA-3090 Powered Speaker System Owner's Guide Discover how to set up, connect, and troubleshoot your Cyber Acoustics CA-3080 or CA-3090 2.1 powered speaker system. This owner's guide provides essential safety instructions, setup tips for optimal audio, and detailed connection steps for computers, smartphones, and gaming consoles.
 Boston VR1, VR2, VR3 VRB, VRC High Performance Home Theater Loudspeakers	Boston Acoustics VR Series: High Performance Home Theater Loudspeakers Explore the Boston Acoustics VR series, featuring high-performance home theater loudspeakers including the VR1, VR2, VR3 floorstanding models, the VRB bookshelf speaker, and the VRC center channel. This guide covers detailed specifications, optimal speaker placement, connection methods (basic hookup, bi-wiring, bi-amplification), speaker care, and listening level advice for an immersive audio experience.

Documents - Q Acoustics – M40




[\[pdf\]](#) User Manual Owner's Manual Declaration of Conformity

User Manual Q Acoustics M40 Active Floorstanding Speakers with Bluetooth Pair K B Audio q acoustics m40 user manual v 1749564125 cdn shopify s files 1 0055 9906 8206 |||

ENGLISH EN DEUTSCH DE ESPAOL ES FRANAIS FR ITALIANO IT NEDERLANDS NL PORTUGUESE PT SVENSKA SE **M40** HD WIRELESS SYSTEM OWNER S MANUAL POLSKIE PL F ENGLISH EN **M40** HD WIRELESS SYSTEM OWNER S MANUAL EU DECLARATION OF CONFORMITY **M40** conforms with the following EU Directives ...

lang:en score:36 filesize: 10.54 M page_count: 170 document date: 2023-12-22




[\[pdf\]](#) User Manual Owner's Manual Declaration of Conformity

User Manual Q Acoustics M20 Active Bookshelf Speakers with Bluetooth K B Audio q acoustics m20 user manual v 17495629 cdn shopify s files 1 0055 9906 8206 |||

ENGLISH EN DEUTSCH DE ESPAOL ES FRANAIS FR ITALIANO IT NEDERLANDS NL PORTUGUESE PT SVE ... e zetten, druk op op de afstandsbediening of druk lang op het bedieningspaneel. Auto stand-by Het Q **M40** systeem heeft een energiebesparende automatische stan by functie. Als er geen muziek wordt afge...

lang:en score:28 filesize: 8.37 M page_count: 146 document date: 2023-12-18




[pdf] User Manual Owner's Manual Declaration of Conformity

Parsiisqsti →Q Acoustics M20 HD Pair SoundiumQ17416 IS User Manual ALL r7soundium It cdn shop files Q17416 r7 v 2000460355981448293 |||

ENGLISH EN DEUTSCH DE ESPAOL ES FRANAIS FR ITALIANO IT NEDERLANDS NL

PORTUGUESE PT SVE ... e zetten, druk op op de afstandsbediening of druk lang op het bedieningspaneel. Auto stand-by Het Q **M40** systeem heeft een energiebesparende automatische stan by functie. Als er geen muziek wordt afge...

lang:en score:25 filesize: 8.37 M page_count: 146 document date: 2023-12-18



[pdf] Specifications Accessories

Ficha tecnica 2 91 Mb Q Acoustics M40 Wiim Pro Ext supersonido es documento 23664 |||

M SERIES HD WIRELESS MUSIC SYSTEMS Two speakers, one entire high-resolution wireless audic system. Introducing the M Series from Q Acoustics. The M Series powered speaker range consists of two compact but powerful models: M20 bookshelf and **M40** micro-towers. Each model is designed to deliver extrao...

lang:en score:24 filesize: 2.91 M page_count: 12 document date: 2024-01-30




[pdf]

M40 White Paper Layout 03 cdr Kieron HD Wireless Music System 13 hours ago — provides options to connect your TV via Bluetooth Optical and Analogue Phono or 3 5mm jack Position the system either side of for stunning q acoustics m40 white paper cdn webshopapp shops 161315 files 456107331 |||

M40 HD Wireless Music System Techical Information **M40** HD Wireless Music System This is a new design, not an adaption of one of our many award-winning passive products. Designing a dedicated music system allowed the engineers to optimise all the acoustic elements of the **M40**, creating a produ that...

lang:en score:22 filesize: 4.2 M page_count: 10 document date: 2024-01-12




[pdf] Specifications Dimension Guide Declaration of Conformity

Control Web SUPERSONIDO Q Acoustics M40 HD Wireless Audio System Review SuperSonido Mar 2 2024 · I m thinking specifically of the KEF LSX II LT it doesn t have analogue inputs but does an HDMI socket It has Wi Fi connectivity supersoni es doc 51483 24986 |||

Q Acoustics **M40** HD Wireless Audio System Review All the services you need on the**M40** by Simon Lucas Mar 2, 2024 Review Specs Discussion 34 Hi-Fi Review Q Acoustics **M40** Hi-Fi Speaker 2024 MSRP: 749.00 10 SCORE OUT OF 10 Q Acoustics **M40** HD Wireless Audio System Review Slightly b and certain...

lang:en score:21 filesize: 504.03 K page_count: 9 document date: 2024-11-07




[\[pdf\]](#) User Manual Owner's Manual Declaration of Conformity

User manual Armour Home Electronics Limited M40BT HD Wireless Music System YGM YGMM40BT m40bt

ENGLISH EN FRANAIS FR M 40 HD WIRELESS SYSTEM OWNER S MANUAL EN M 40 HD WIRELESS SYSTEM OWNER ... eakers from the cartons by holding the cabinets. Do not use the protective bags to lift them. The Q **M40** loudspeakers are heavy - get assistance to lift them. When manoeuvring loudspeakers, do not dra...

lang:en score:20 filesize: 1.95 M page_count: 28 document date: 2023-08-24



[\[pdf\]](#)

Discreet Design Towering Sound15 lug 2025 — Following the success of award winning M20 HD wireless audio system Q Acoustics brings its expertise and latest acoustic technologies to an audio201549iear nl docs spec sheet 201549 srsltid AfmBOors KLaN1lyRmloQ0rE9plkwHESyuG CS5pG066oCTXnTlg2A6H |||

M40 Discreet Design. Towering Sound. The new **M40** by Q Acoustics. Powered micro-towers that combine a ... nager for further information. E: sales@armourhome.co.uk / T: 44 0 1279 50 11 11

qacoustics.co.uk/**m40** ...

lang:en score:18 filesize: 3.82 M page_count: 8 document date: 2024-01-31



[\[pdf\]](#)

4026k00h8wpzl6ssrmck4pua260yjm63Полочная акустика Q Acoustics Q3020c QA3324 Satin White цена 49 990 руб купить Галерея безупречной электроники Назаровuqfm1jcn3z2pg5nyjbvj811hoengujoxnazarov gallery ru upload iblock c04 uqfm1jcn3z2pg5nyjbvj811hoengujox |||

Introducing 3000 generation c Q Acoustics latest affordable, high-performance loudspeaker series, f ... driver trims. Available in four new finishes: Pin Oak, Claro Walnut, Satin White, Satin Black. **M40** C3 Continuous Curved Cone™ This new speaker series features a C3 Continuous Curved Cone™ mid..

lang:en score:17 filesize: 273.77 K page_count: 7 document date: 2024-05-10



[\[pdf\]](#)

Introducing 3000 generation c British audio specialist Q Acoustics introduces the affordable and high performance 3000c loudspeaker series Building on formidable legacy of the b3670913554c562632a7c2e0a1011a11 off ru upload iblock b36 |||

Introducing 3000 generation c Q Acoustics latest affordable, high-performance loudspeaker series, f ... driver trims. Available in four new finishes: Pin Oak, Claro Walnut, Satin White, Satin Black. **M40** C3 Continuous Curved Cone™ This new speaker series features a C3 Continuous Curved Cone™ mid..

lang:en score:17 filesize: 273.77 K page_count: 7 document date: 2024-05-10




[pdf]

Brett Worth WZfrQQYrOqyqvNla0oyDnM 2 hifisound de out media r
DqGy7sp9xrszNf10FJIBbDRd9O4Vy6uah7LKn6XKKECdxVhMDiCx8fFcgi1jgZro2bleCTPQYFm15RJlyrJYTbOqbSVLCuuYI
R 3000C Produkt Broschüre EN Q Acoustics 3010C Regal Lautsprecher NEU! kaufen bei dehifisound hifi
Komponentenhifisound 2hifisound
BMAu1xfbUH9DFwNeyLmshfNXGVwpTKTnjVkyH1yVolxfgyV0kGrWtpEx9sxUAVQtF3EtTwbdJ20LOZVQFLDrN5Ry1sEmvK
lw25gAA3JFYahRe77u3OvN OmgO nhifisound |||

Introducing 3000 generation c Q Acoustics latest affordable, high-performance loudspeaker series, f ...
tinuous Curved Cone™ mid/bass driver design, first introduced in award-winning 5000 series and the
M40 powered micro-tower speakers. Q Acoustics latest technical platform elevates the 3000c above
its...

lang:en score:17 filesize: 595.06 K page_count: 7 document date: 2024-09-03



[pdf] User Manual Owner's Manual Declaration of Conformity

Download user manualQ Acoustics M40 Walnut Powered Bluetooth Speakers Per Pair Richer SoundsQ18373
ISM40UserManual ALL r6richersounds content product files Q18373 r6 |||
ENGLISH EN DEUTSCH DE ESPAOL ES FRANAIS FR ITALIANO IT NEDERLANDS NL
PORTUGUESE PT SVENSKA SE **M40** HD WIRELESS SYSTEM OWNER S MANUAL POLSKIE PL F
ENGLISH EN **M40** HD WIRELESS SYSTEM OWNER S MANUAL EU DECLARATION OF
CONFORMITY **M40** conforms with the following EU Directives ...
lang:en score:17 filesize: 10.54 M page_count: 170 document date: 2023-12-22




[pdf]

Review Hi Fi Choice Junio 2024 2 84 Mb Q Acoustics M40 Planar 1 PLUS Ext supersonido es documento 24197 |||
Rock n roll is magic Perfect pair Rioting on the road Dekoni x Hifiman Cobalt with Guns N Roses over-
ear headphones passion for sound Issue No. 516 July 2024 Debut decks Group Test We audition six c
the best new cutting edge start-up vinyl spinners iFi Audio s GO bar Kensei DAC/amp...
lang:en score:15 filesize: 2.84 M page_count: 2 document date: 2024-06-10

[pdf]

Martin Klaassen Consumentenprijslijst 2024 2 iEarQ 3010 3020 5010 5020 M 20 VPE 1 stuk Muurbeugel für 3090 Q Acoustik
en IDC bevelen QED kabels aan Lautsprecherkabel q acousticsiear nl docs prijslijst q acoustics srsItd
AfmBOoqQgTPUast2hXXFOGaU h3HBFcLKMD92JCWUcOXIOR7csiSKy03 iEarConsumentenprijslijst Lautsprecherkabel Q
Lautsprecherkabel iear AfmBOoo0Ha6YemDseli4ZlZJBYPKdDlc64HJ0aun SjqDhJfLJp7aJSG0iear
h3HBFcLKMD92JCWUcOXIOR7csiSKy03iear AfmBOoqK9rEHveHU9TJ2 Naaogje 0rmx36k7mQOWle DI1it6zSWUic
DI1it6zSWUiciear AfmBOorizUUUpZLftfdKcWzd4s8bziMOPXC4OTzBgvqv8EGaes33DM i0
AfmBOOpFXCHSoy4PZ39xPWei4x3UKZkT7cXYVhSpuvK0Fht4JQ1J11c0iear i0iear AfmBOorv7nMWv9MleLldDdfxGm
nUa9L8Qf2u1MFdCGfhUM8zEzN4ENC AfmBOooiOsx80EPYOG0OBkTnepkXV61mNgGyNkshFcu7EYqv ncGuEWziear ||| |||
Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-bindende



adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr ||| Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-binden
adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr ||| Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-binden
adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr ||| Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-binden
adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr ||| Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-binden
adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr ||| Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de niet-binden
adviesverkoopprijs in eenheden en euro s incl. BTW. Prijslijst, technische kenmerken en fouten uitgezonderd. Eerdere Q
Acoustics pr

Consumentenprijslijst 2024/2 geldig vanaf 01.09.2024 Let op: Prijsopgaven komen overeen met de nie
... en pcs B /H/D mm Gewicht 38 Hz - 22 kHz 2,5 kHz 86dB w/m 2 x 50 W RMS 250 x 710 x 296 12,1k
M20 **M40** Connecties: Bluetooth 5.0 mit aptXTM, aptXTM HD, aptXTM Low Latency, SBC und AAC
kompatibel U...

lang:nl score:14 filesize: 2.59 M page_count: 28 document date: 2024-08-29



[pdf] User Manual Instructions Specifications Guide

User ManualGoldring GR3 Turntable with E3 Cartridge Built in Phono Pre Amp K B Audiogoldring gr3 user manualcdn shopify
files 1 0055 9906 8206 goldring manual v 1749726241 |||

GR3 GOLDRING TURNTABLE OWNER S GUIDE CONTENTS Important information 1 Compliance
information ... input on your amplifier using the appropriate phono cables. If connecting to a Q Acoustic
M20 or **M40** it is recommended to use the 3.5 mm jack to phono cable supplied . IMPORTANT: Many
amplifiers a...

lang:it score:12 filesize: 785.61 K page_count: 12 document date: 2024-09-05



[pdf]


GOLDRING GR3 27 sept 2024 — Goldring a globally recognised name in the world of analogue audio and renowned for its precision engineered phono cartridges announces Ext supersonido es documento 24757 |||
GOLDRING GR3 New premium belt-driven turntable GR3 represents Goldring s stylish re-entry into th
... an ideal companion for products from sister company, Q Acoustics, such as its award-winning M20
and **M40** powered stereo speakers. Additionally, GR3 comes with a choice of high-quality interconnect:
fro...

lang:en score:11 filesize: 2.05 M page_count: 4 document date: 2024-09-25



[pdf] Decleration of Conformity Press Release

Brett Worth Goldring GR3 press release doc av connection Products |||
Goldring re-enters the turntable market with GR3: A premium blend of audiophile class and user-frien .
an ideal companion for products from sister company, Q Acoustics, such as its award-winning M20 and
M40 powered stereo speakers. Additionally, GR3 comes with a choice of high-quality interconnects fro
lang:en score:11 filesize: 517.77 K page_count: 4 document date: 2024-10-03



[pdf] Catalog

Sennheiser Revue 11 microphone audio equipment catalog headphones revue microphones lcweb2 loc gov master mbrs
recording preservation manuals |||
w..... 11M lltlht to .1len11_. In pertculr with IWg8rd 10 lIChnl...1prog..... Preface De ... A,U F.ach
ftlttrophOf1.1 o f U liS lype IS tt,frpl -d mp1ele ,01- h . l 9lIMl 1. 51 cm1lt. rq **m40** 10 17 ,OOO H.I le :e:L
u red 13 Supercardioid Directional Microphone MD 419 N . MD 419 N-T...
lang:en score:9 filesize: 80.59 M page_count: 144 document date: 2013-11-25

