

## ToughTested MOAB 65

# ToughTested MOAB 65 Portable Charger User Manual

Model: MOAB 65

## INTRODUCTION

The ToughTested MOAB 65 is a high-capacity, rugged portable charger designed to provide reliable power for laptops, smartphones, and other USB-powered devices. With its 40,000mAh battery and advanced fast-charging capabilities, it is an ideal companion for outdoor adventures, remote work, and extended travel. This manual provides essential information for the safe and efficient use of your MOAB 65 portable charger.



Image: The ToughTested MOAB 65 Portable Charger, showcasing its rugged design and power indicator lights.

## Safety Information

Please read all safety warnings and instructions before using this product to prevent injury or damage.

- Do not expose the power bank to extreme temperatures (above 60°C/140°F or below -10°C/14°F).
- Do not disassemble, modify, or attempt to repair the device. This will void the warranty and may cause harm.
- Keep away from water and liquids. While the MOAB 65 is IP64 rated for dust and water resistance, it is not designed for submersion.
- Avoid dropping or subjecting the device to severe impacts.
- Use only certified charging cables and adapters.

- Keep out of reach of children.
- Dispose of the power bank responsibly according to local regulations. Do not dispose of in household waste.

## PACKAGE CONTENTS

---

Verify that all items are present in your package:

- ToughTested MOAB 65 Portable Charger
- Heavy-duty USB-C to USB-C Power Delivery PET Cable
- User Manual (this document)




Image: The included heavy-duty USB-C to USB-C Power Delivery PET cable.

## PRODUCT OVERVIEW

Familiarize yourself with the components of your MOAB 65 portable charger.

Component	Description
Power Button	Activates the power bank and checks battery level.
LED Power Indicators	Displays the remaining battery capacity.
USB-C PD (Input/Output) Port	65W Power Delivery for charging laptops and rapid charging of the power bank itself.
USB-C PD (Output) Port	20W Power Delivery for fast charging smartphones and other compatible devices.
USB-A QC 3.0 Port	Quick Charge 3.0 output for fast charging non-Type C devices.
Sealed Port Covers	Protects ports from dust and water, maintaining IP64 rating.

# FAST CHARGING FOR PHONES

20WATT USBC-C Power Delivery  
QC3 USB fast charging



Image: Side view of the MOAB 65 showing the USB-A and USB-C output ports with their protective covers.

## Charging the MOAB 65 Portable Charger

Before first use, fully charge your MOAB 65. It is recommended to use a 65W USB-C PD wall charger (not included) for the fastest charging time.

1. Open the sealed port cover for the USB-C PD (Input/Output) port.
2. Connect the included USB-C to USB-C cable to the USB-C PD (Input/Output) port on the MOAB 65.
3. Connect the other end of the cable to a compatible USB-C PD wall charger.
4. The LED power indicators will illuminate and blink to show charging progress. All four LEDs will be solid when fully charged.

A full charge can take several hours depending on the power of your wall charger.

## OPERATING INSTRUCTIONS

### Checking Battery Level

Press the power button once to check the remaining battery capacity. The LED indicators will light up:

- 4 LEDs: 75-100%
- 3 LEDs: 50-75%
- 2 LEDs: 25-50%
- 1 LED: 0-25% (Recharge soon)

### Charging Devices

The MOAB 65 features multiple output ports for versatile charging.

#### 1. **For Laptops (USB-C PD 65W):**

Open the sealed port cover for the USB-C PD (Input/Output) port. Connect your laptop's USB-C charging cable to this port and to your laptop. The MOAB 65 will automatically begin charging.



Image: The MOAB 65 connected to a laptop via its USB-C PD port, demonstrating laptop charging capability.



# FAST CHARGING FOR LAPTOPS

65WATT USB-C Power Delivery  
Input / Output



Image: Visual representation highlighting the 65W USB-C Power Delivery input/output for laptops.

## 2. For Smartphones & Tablets (USB-C PD 20W or USB-A QC 3.0):

Open the sealed port cover for the desired output port (USB-C or USB-A). Connect your device's charging cable to the MOAB 65 and to your device. The Instasense Processor will automatically detect your device and deliver optimal charging power.



# FAST CHARGING FOR PHONES

20WATT USB-C Power Delivery  
QC3 USB fast charging



Image: Close-up of the MOAB 65's output ports, including the 20W USB-C PD and QC3 USB-A, designed for fast phone charging.

### 3. Simultaneous Charging:

You can charge multiple devices simultaneously using the available output ports. The MOAB 65 will intelligently distribute power.

# FAST CHARGE LAPTOPS AND PHONES AT THE SAME TIME



Image: Two MOAB 65 units shown side-by-side, illustrating the capability to fast charge laptops and phones concurrently.

*Note: For optimal fast charging, ensure your device and cable support Power Delivery (PD) or Quick Charge (QC) technology.*

# PD FAST CHARGING

**MacBook**  
100% IN  
EN

**2** HRS

**ANDROID**  
70% IN  
EN

**30** MINS

**IPHONE**  
50% IN  
EN

**30** MINS



Image: Infographic detailing fast charging times for various devices: MacBook 100% in 2 hours, Android 70% in 30 minutes, iPhone 50% in 30 minutes.

## MAINTENANCE

- **Cleaning:** Wipe the exterior with a soft, dry cloth. Do not use harsh chemicals or abrasive materials. Ensure port covers are closed before cleaning.
- **Storage:** Store the power bank in a cool, dry place away from direct sunlight and extreme temperatures. For long-term storage, charge the power bank to about 50-75% every 3-6 months to maintain battery health.
- **Port Covers:** Always ensure the sealed port covers are securely closed when not in use, especially in dusty or wet environments, to maintain the IP64 rating.

# IP64

## Weatherproof & Dustproof



Image: The MOAB 65 with water droplets on its surface, illustrating its IP64 weatherproof and dustproof capabilities.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
Power bank not charging	Cable or adapter issue; power bank fully discharged; faulty port.	Try a different USB-C cable and wall adapter. Ensure the adapter is powerful enough (e.g., 65W PD). Allow a few minutes for a deeply discharged unit to respond.
Device not charging from power bank	Power bank low on charge; incorrect cable; device not compatible; power bank in standby.	Check power bank battery level. Ensure cable is securely connected and functional. Try a different port. Press the power button to activate output.
Slow charging	Cable not supporting fast charge; device not supporting fast charge; multiple devices connected.	Use a certified PD/QC compatible cable. Ensure your device supports fast charging. Disconnect other devices if faster charging is needed for one specific device.



Problem	Possible Cause	Solution
LED indicators not working	Minor software glitch; internal issue.	Try fully discharging and then recharging the power bank. If the issue persists, contact customer support.

## SPECIFICATIONS

Feature	Detail
Model	MOAB 65
Battery Capacity	40,000mAh (142Wh)
USB-C PD (Input/Output)	65W Power Delivery
USB-C PD (Output)	20W Power Delivery
USB-A (Output)	Quick Charge 3.0
Dimensions	7 x 4 x 1.5 inches
Weight	1.8 pounds
IP Rating	IP64 (Dustproof & Water Resistant)
Battery Type	Lithium Ion
Color	Black / Orange

## WARRANTY AND SUPPORT

The ToughTested MOAB 65 Portable Charger comes with a **5-year warranty**, ensuring reliability and peace of mind. This warranty covers defects in materials and workmanship under normal use. For warranty claims, technical support, or any questions regarding your MOAB 65, please contact ToughTested customer service:

- **Website:** Visit the official ToughTested website for support resources and contact information. [www.toughtested.com](http://www.toughtested.com)
- **Email:** Refer to the ToughTested website for the most current support email address.
- **Phone:** Refer to the ToughTested website for the most current support phone number.

Please have your product model (MOAB 65) and proof of purchase ready when contacting support.




Image: ToughTested "Built for Every Adventure" logo, emphasizing the brand's commitment to durability.

© 2024 ToughTested. All rights reserved.