

[manuals.plus](#) /› [WORKPRO](#) /› [WORKPRO Battery Hot Glue Gun 3.6 V Instruction Manual W125277](#)

WORKPRO W125277

WORKPRO Battery Hot Glue Gun 3.6 V

Model: W125277

1. INTRODUCTION

The WORKPRO Battery Hot Glue Gun is a versatile, cordless tool designed for various crafting, artistic, and repair tasks. Featuring a 3.6V 2500mAh lithium-ion battery, it offers portability and efficient operation. This manual provides essential information for safe and effective use, including setup, operation, maintenance, and troubleshooting.

2. SAFETY INSTRUCTIONS

Always observe the following safety precautions to prevent injury or damage to the product:

- The glue gun nozzle and melted glue become very hot during operation. Avoid direct contact with skin to prevent burns.
- Do not use the glue gun while it is charging.
- Ensure adequate ventilation when using the glue gun, as some glues may emit fumes.
- Keep the tool out of reach of children and pets.
- Do not attempt to disassemble or modify the glue gun. Refer all servicing to qualified personnel.
- The intelligent safety system automatically shuts off the power after 8 minutes of inactivity to protect users and conserve energy.
- Always place the glue gun on its stand or a heat-resistant surface when not in use.

- ◆ Press and hold power switch for 2-3 seconds to start
- ◆ Turn off automatically after 8 minutes of inactivity



- ◆ For storage, charge the battery to 50% to 75% capacity and recharge it at least once every 3 to 6 months to maintain its lifespan.

Image: Safety features and charging instructions for the WORKPRO Hot Glue Gun. It highlights the automatic shut-off after 8 minutes of inactivity and the warning not to use while charging. It also shows the recommended battery charge for storage.

3. PACKAGE CONTENTS

Verify that all items are present in the package:

- 1 x WORKPRO Battery Hot Glue Gun
- 20 x Glue Sticks (7 mm x 100 mm)
- 1 x USB Charging Cable

MINI CORDLESS GLUE GUN SIZE



Image: The WORKPRO Mini Cordless Glue Gun showing its dimensions (140mm length, 120mm height) and the included 20 pieces of 7mm x 100mm glue sticks, along with its weight of 196g.

4. PRODUCT OVERVIEW

Familiarize yourself with the components of your WORKPRO Battery Hot Glue Gun:



Image: Diagram of the WORKPRO Hot Glue Gun with key parts labeled, including the ON/OFF Switch, Less Drip Nozzle, Type-C Charging port, Trigger, Energy Indicator, Working Status Indicator, and Bracket.

- **ON/OFF Switch:** Powers the device on and off.
- **Less Drip Nozzle:** Dispenses hot glue with reduced dripping.
- **Type-C Charging Port:** For connecting the USB charging cable.
- **Trigger:** Controls the flow of melted glue.
- **Energy Indicator:** Shows battery charge level.
- **Working Status Indicator:** Indicates heating status (red for heating, green for ready).
- **Bracket:** Provides a stable resting position for the glue gun.

5. SETUP AND CHARGING

5.1 Initial Charging

Before first use, fully charge the glue gun. Connect the provided USB Type-C charging cable to the glue gun's charging port and to a compatible USB power source (e.g., laptop, power bank, or USB charger). The Energy Indicator will show charging status. A full charge provides up to 100 minutes of intermittent working time or 30 minutes of continuous use.

Important: For optimal battery lifespan, charge the battery to 50% to 75% capacity for storage and recharge it at least once every 3 to 6 months.

5.2 Loading Glue Sticks

Insert a 7mm diameter glue stick into the opening at the back of the glue gun. Push it gently until it stops. Do not force the glue stick.

6. OPERATING INSTRUCTIONS

6.1 Powering On and Preheating

1. Ensure a glue stick is loaded.
2. Press and hold the ON/OFF switch for 2-3 seconds to turn on the glue gun. The Working Status Indicator will light up red, indicating that the gun is heating.
3. Wait approximately 100 seconds for the glue gun to preheat. The MCH heating system ensures rapid and consistent temperature.
4. When the Working Status Indicator changes from red to green, the glue gun is ready for use.



Image: The WORKPRO Hot Glue Gun illustrating its 100-second fast preheating capability and its 2500mAh battery capacity.

6.2 Applying Glue

1. Once the indicator is green, position the nozzle close to the surface where glue is needed.
2. Gently press the trigger to dispense glue. The flexible trigger allows for controlled glue flow.
3. Apply glue as needed. For continuous application, periodically push a new glue stick into the back of the gun to maintain flow.
4. After applying glue, release the trigger. The less-drip nozzle design helps minimize excess glue.



Image: The WORKPRO Hot Glue Gun demonstrating its less-drip nozzle feature, emphasizing safety and efficiency during glue application.



Image: A person using the WORKPRO Hot Glue Gun to apply glue to a small decorative item, demonstrating its use in crafting.

6.3 Powering Off

To turn off the glue gun, press and hold the ON/OFF switch for 2-3 seconds. The Working Status Indicator will turn off. The glue gun will also automatically shut off after 8 minutes of inactivity.

7. MAINTENANCE

- **Cleaning:** Ensure the glue gun is completely cool before cleaning. Gently wipe the exterior with a clean, damp cloth. Do not use abrasive cleaners or solvents.
- **Nozzle Care:** Do not attempt to clean the nozzle while it is hot. Any hardened glue around the nozzle can be carefully removed once the gun is cool.
- **Storage:** Store the glue gun in a dry, cool place, away from direct sunlight and out of reach of children. Ensure the battery is charged to 50-75% capacity for long-term storage.

8. TROUBLESHOOTING

Problem	Possible Cause	Solution
Glue gun does not turn on.	Battery is depleted.	Charge the glue gun using the provided USB cable.
Glue gun heats up but no glue dispenses.	No glue stick loaded or glue stick is too short.	Insert a new glue stick and ensure it is fully inserted.
Glue flow is inconsistent or slow.	Insufficient preheating time; partially used glue stick.	Allow full preheating until the indicator is green. Ensure a fresh glue stick is fully inserted.
Glue gun automatically shuts off.	8 minutes of inactivity detected.	This is a safety feature. Press and hold the ON/OFF switch for 2-3 seconds to restart.

9. SPECIFICATIONS

Brand	WORKPRO
Model Number	W125277
Voltage	3.6 Volts
Power Source	Battery Powered
Battery Capacity	2500mAh Lithium-ion
Preheating Time	Approx. 100 seconds
Automatic Shut-Off	After 8 minutes of inactivity
Glue Stick Diameter	7 mm
Item Weight	196 Grams
Material	Plastic
UPC	820909604570

10. WARRANTY AND SUPPORT

For warranty information or technical support, please refer to the documentation provided with your purchase or contact WORKPRO customer service directly. Keep your proof of purchase for any warranty claims.

