

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Jectse](#) /

› **Jectse Baby Safety Monitor User Manual (Model: Jectsebuige0ohxz-11)**

Jectse Jectsebuige0ohxz-11

Jectse Baby Safety Monitor User Manual

Model: Jectsebuige0ohxz-11

INTRODUCTION

Thank you for choosing the Jectse Baby Safety Monitor. This device is designed to provide reliable monitoring of your baby, offering peace of mind with its advanced features. Please read this manual thoroughly before use to ensure proper operation and to maximize the benefits of your monitor.



Image: The Jectse Baby Safety Monitor, showing both the camera unit and the parent display unit with a baby sleeping on its screen.

PRODUCT FEATURES

The Jectse Baby Safety Monitor is equipped with several features to assist in monitoring your child:

- **Energy Saving Mode:** The monitor features an energy-saving mode with adjustable sound detection levels (High 50dB, Medium 55dB, Low 60dB). The display automatically activates upon detecting sound in the

baby's room and turns off after approximately 30 seconds of silence to conserve power.

- **Two-Way Talk:** Equipped with a built-in microphone and speaker, this baby monitor allows for two-way communication, enabling you to comfort your baby remotely.
- **Automatic Infrared Night Vision:** The monitor automatically switches to infrared night vision mode in low light conditions, providing clear images up to 5-10 meters, even in complete darkness.
- **Temperature Monitoring:** An integrated alarm alerts you if the room temperature exceeds 30°C (86°F) or drops below 20°C (68°F).
- **Feeding Reminder:** Configure a feeding reminder function to ensure your baby receives regular feedings.
- **Cry Detection:** The monitor detects your baby's crying and displays an alarm notification, alerting you to the situation promptly.
- **Lullaby Playback:** Soothe your baby to sleep with pre-programmed lullabies.
- **Digital Zoom:** The display unit supports 2x/4x digital zoom for a closer view of your baby.

PACKAGE CONTENTS

Please verify that all items are present in the package:

- 1 x Monitor Unit (Parent Unit)
- 1 x Camera Unit (Baby Unit)
- 2 x Power Adapters (EU Plug)
- 1 x User Manual
- 2 x Screws
- 2 x Expansion Tubes



Image: The Jectse Baby Safety Monitor units along with the included screws and expansion tubes for mounting.

SETUP INSTRUCTIONS

1. Camera Unit Placement

1. Place the camera unit in a location that provides a clear view of your baby's crib or play area. Ensure it is at least 1 meter (3 feet) away from the baby to prevent entanglement with cables.
2. For wall mounting, use the provided screws and expansion tubes. Mark the desired position, drill pilot holes, insert expansion tubes, and secure the camera base.
3. Connect one power adapter to the camera unit and plug it into a power outlet.

2. Monitor Unit Setup

1. Place the monitor unit in a convenient location where you can easily view the screen and hear alerts.
2. Connect the second power adapter to the monitor unit and plug it into a power outlet. The monitor unit has a built-in rechargeable battery for portable use.
3. Power on both the camera and monitor units. They should automatically pair. If pairing fails, refer to the troubleshooting section.

OPERATING INSTRUCTIONS

Basic Operation

- **Power On/Off:** Press and hold the power button on both units to turn them on or off.
- **Volume Control:** Use the volume buttons on the monitor unit to adjust the sound level.
- **Brightness Control:** Adjust screen brightness via the menu settings on the monitor unit.

Advanced Features

- **Two-Way Talk:** Press and hold the microphone button on the monitor unit to speak to your baby. Release the button to listen.
- **Energy Saving Mode (VOX):** Access the menu on the monitor unit to enable or disable VOX mode and set the sound detection sensitivity (High, Medium, Low).
- **Feeding Reminder:** Navigate to the menu settings to set up feeding reminder alarms at desired intervals (e.g., 2 hours, 4 hours).



Image: The monitor display showing a baby being fed, with icons indicating 2-hour and 4-hour feeding reminder settings.

- **Lullaby Playback:** Select the lullaby option from the monitor's menu to play soothing melodies. You can choose from various built-in lullabies.



Image: The camera unit positioned near a sleeping baby, with musical notes indicating the lullaby playback function.

- **Digital Zoom:** Use the dedicated zoom button on the monitor unit to magnify the image 2x or 4x.

Supports 2x/4x zoom amplification

See every detail of the baby clearly



Image: The monitor display showing a split screen with a baby, demonstrating the 2x/4x zoom amplification feature for detailed viewing.

MAINTENANCE

- **Cleaning:** Use a soft, dry cloth to clean the surfaces of both the camera and monitor units. Do not use abrasive cleaners or solvents.
- **Storage:** If storing the monitor for an extended period, ensure both units are powered off and disconnected from power. Store in a cool, dry place.
- **Battery Care:** For the monitor unit's built-in battery, avoid fully discharging it frequently. Charge it regularly to maintain battery health.

TROUBLESHOOTING

- **No Picture/Sound:** Ensure both units are powered on and connected to power. Check that they are within range of each other.
- **Poor Signal/Interference:** Move the units closer to each other. Avoid placing them near other electronic devices that may cause interference (e.g., Wi-Fi routers, microwaves).
- **Units Not Pairing:** Power off both units, then power them back on. If the issue persists, consult the full user manual for specific pairing instructions.
- **Battery Not Charging:** Ensure the power adapter is securely connected to both the monitor unit and the power outlet. Check if the power outlet is functional.

- **Temperature Alarm Issues:** Verify that the camera unit is not placed directly in sunlight or near a heat source/vent, which could affect temperature readings.

SPECIFICATIONS

Item Type	Baby Camera Monitor
Material	ABS (Acrylonitrile Butadiene Styrene)
Weight	Approx. 432 g / 15.2 oz
Camera Resolution	720P
Screen Resolution	320 x 240
Video Frame Rate	18-20 fps
Screen Size	2.8 inches
Display Battery Capacity	2600 mAh, Lithium Battery (built-in)
Model Number	Jectsebuige0ohxz-11

WARRANTY AND SUPPORT

For detailed warranty information, please refer to the warranty card included with your product or visit the official Jectse website. If you encounter any issues or require technical assistance, please contact Jectse customer support through their official channels.

Manufacturer: Jectse

ASIN: B0CWN5RPKQ