

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [VIVO](#) /

> [VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount Instruction Manual](#)

VIVO STAND-V202T

VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount Instruction Manual

Model: STAND-V202T | **Brand:** VIVO

PRODUCT OVERVIEW

The VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount (STAND-V202T) is designed to optimize your workspace by securely holding two ultrawide monitors in a vertical stacked array. This heavy-duty mount is compatible with screens up to 43 inches and 25 lbs per arm, featuring VESA 75x75mm or 100x100mm mounting holes. It offers smooth articulation for comfortable viewing angles, integrated cable management, and height adjustment along the center pole for customized screen placement. Constructed from high-grade steel and aluminum, this stand provides a stable and adjustable solution for your monitor setup.



Image: Rear view of the VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount with two ultrawide monitors attached, showcasing the VESA plates and the central pole.



Image: Front view of the VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount installed on a desk, holding two ultrawide monitors displaying a starry sky. Text overlay indicates 'Secure Mounting for screens up to 43 inches'.

SETUP INSTRUCTIONS

Follow these steps to properly assemble and install your VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount.

Your browser does not support the video tag.

Video: Official VIVO assembly guide for the STAND-V202T Dual Ultrawide Vertical Monitor Desk Mount. This video provides a visual walkthrough of the entire installation process.

- Step 1: Assemble the Clamp Base.** Connect the clamp brace to the base. Then, apply the soft pad to the clamp brace. Secure the lower clamp to the clamp assembly using the provided screws and Allen wrench. Install the assembled clamp on your desktop and snap on the cover.
- Step 2: Install the Lower Pole.** Screw the lower pole into the base of the clamp assembly. Slide a cable clip onto the lower pole before fully tightening the pole to the base.

3. **Step 3: Attach the Lower Arm.** Slide the lower monitor arm onto the lower pole and tighten it at your desired height. Thread the upper pole onto the lower pole. Attach a cable clip to the upper pole.
4. **Step 4: Attach the Upper Arm.** Attach the upper monitor arm onto the upper pole and tighten it. Attach the remaining cable clips to the arms for cable management.
5. **Step 5: Attach Monitors to VESA Plates.** Securely attach your monitors to the VESA plates on each arm using the appropriate screws. Ensure the VESA plates are properly aligned with your monitor's mounting holes (75x75mm or 100x100mm).

OPERATING INSTRUCTIONS

Once assembled, you can adjust your monitors for optimal viewing comfort.

- **Height Adjustment:** The monitor arms can be adjusted vertically along the 32-inch center pole to achieve the perfect stacked height for your setup.
- **Tilt and Swivel:** Each monitor arm offers +5° to -12° tilt and 180° swivel. Use the provided tools to adjust the tension of these joints as needed to ensure fluid or stationary movement.
- **Screen Leveling:** Fine-tune the screen leveling with a +3° to -3° adjustment to ensure your monitors are perfectly aligned.
- **Cable Management:** Utilize the integrated cable clips on the arms and center pole to keep your power and AV cords organized and out of sight, contributing to a clean workspace.

Height Adjustment



Heavy Duty "C" Clamp

Image: Side view of the VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount illustrating height adjustment along the 32-inch pole. The heavy-duty C-clamp is visible at the base.



Cable Management

Image: Close-up view of the VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount arm, highlighting the cable management clips that help organize wires along the arm and central pole.



Image: Two monitors on the VIVO Dual Vertically Stacked Ultra-Wide Monitor Desk Mount, demonstrating the 180° swivel and +5° to -12° tilt capabilities for easy articulation. A locking VESA plate is also shown for added security.

MAINTENANCE

To ensure the longevity and optimal performance of your monitor mount, regular maintenance is recommended.

- **Cleaning:** Wipe down the mount periodically with a soft, damp cloth to remove dust and debris. Avoid using harsh chemicals or abrasive cleaners.
- **Tightness Check:** Periodically check all screws and bolts, especially those securing the clamp to the desk and the VESA plates to the monitors. Tighten any loose connections to maintain stability and prevent sagging.
- **Joint Lubrication:** If you notice any stiffness or squeaking in the articulating joints, a small amount of silicone-based lubricant can be applied to improve movement.

TROUBLESHOOTING

If you encounter any issues with your monitor mount, refer to the following common troubleshooting tips:

- **Monitor is Not Stable/Sags:**

- Ensure the desk clamp is securely tightened to the desktop.
- Verify that the VESA plate screws attaching the monitor to the arm are fully tightened.
- Check the tightness of the screws on the articulating joints of the arm.

- **Limited Movement/Stiff Joints:**

- Loosen the tension screws on the articulating joints slightly to allow for freer movement.
- Apply a small amount of silicone lubricant to the joints if they remain stiff.

- **Cables are Not Organized:**

- Utilize all provided cable clips to route cables neatly along the arms and central pole.
- Ensure cables are not too taut, allowing for full range of motion without strain.

SPECIFICATIONS

Attribute	Value
Brand	VIVO
Model Number	STAND-V202T
Item Weight	14.8 pounds
Package Dimensions	17.28 x 8.58 x 5.67 inches
Color	Black
Material	Alloy Steel
Mounting Type	Tabletop Mount
Movement Type	Articulating
Maximum Compatible Size	43 Inches
Minimum Compatible Size	32 Inches
Compatible Devices	Monitor
UPC	840408800037

WARRANTY AND SUPPORT

For warranty information, technical support, or to access additional resources, please visit the official VIVO website or contact their customer service. Keep your purchase receipt for warranty claims.

