

JUMMICO 0183

JUMMICO Electric Height Adjustable Desk (Model 0183) -
Instruction Manual

Model: 0183 | Dimensions: 200 x 80 cm | Color: White

1. SAFETY INFORMATION

Please read this instruction manual carefully before assembly and operation to ensure safe and correct use of your JUMMICO Electric Height Adjustable Desk. Keep this manual for future reference.

- **Power Supply:** Ensure the desk is connected to a grounded power outlet with the correct voltage. Do not overload the power strip.
- **Children and Pets:** Keep children and pets away from the desk during operation to prevent injury.
- **Weight Capacity:** Do not exceed the maximum load capacity of 60 kg. Distribute weight evenly on the desktop.
- **Clearance:** Ensure there are no obstacles above or below the desk when adjusting its height. The anti-collision feature helps prevent damage, but caution is always advised.
- **Liquid Spills:** Avoid spilling liquids on the control panel or electrical components. In case of a spill, immediately unplug the desk and contact customer support.
- **Maintenance:** Do not attempt to disassemble or repair the motor or control system yourself. Contact qualified personnel for service.

2. PACKAGE CONTENTS

Verify that all components are present before beginning assembly. Refer to the following list and diagrams.



Image: Overview of all desk components and hardware.

Parts List:

- B1 (x1), B2 (x1), B3 (x1), B4 (x1), B5 (x1), B6 (x1), B7 (x2), B8 (x2), B9 (x1), B10 (x1), B11 (x2), B12 (x2), B13 (x1), B14 (x6), B15 (x2), B16 (x1), B17 (x1)

Hardware List:

- a (x9), b (x8), c (x18), d (x14), e (x11), f (x1), g (x2)

3. ASSEMBLY INSTRUCTIONS

Follow these steps carefully for proper assembly. An assembly video is available for visual guidance.

Video: Full assembly guide for the JUMMICO Electric Height Adjustable Desk.

Step 1: Connect Crossbar Sections

Join the two crossbar sections (B9) using the provided screws (f M4) and tighten them securely. This forms the central support for the desk frame.



Image: Securing the crossbar sections together.

Step 2: Attach Legs to Crossbar

Attach the desk legs (B1 and B2) to the assembled crossbar (B9) using screws (a) and the M5 wrench (f). Ensure they are firmly connected to form the main frame.



Image: Fastening the legs to the central crossbar.

Step 3: Secure Side Brackets

Install the side brackets (B8) to the top of the legs using screws (a) and the M5 wrench (f). These brackets provide additional support for the desktop.



Image: Installing the side support brackets.

Step 4: Install Feet

Attach the feet (B7) to the bottom of the desk legs using screws (b) and the M5 wrench (f). Ensure they are stable and level.



Image: Fastening the feet to the desk legs.

Step 5: Assemble Desktop Panels

Connect the desktop panels (B3, B4, B5, B6) using the wooden dowels (e) and metal plates (B14, B15) with screws (c) and the M4 wrench (f). Ensure the panels align correctly for a seamless surface.



Image: Assembling the multi-piece desktop.

Step 6: Attach Desktop to Frame

Carefully place the assembled desktop onto the desk frame. Secure the desktop to the frame using screws (d) and the M4 wrench (f). Ensure all connection points are tight.



Image: Securing the desktop to the base frame.

Step 7: Install Drive Rod

Insert the drive rod (B10) into the motor mechanism and connect it to the opposite leg. This rod synchronizes the movement of both legs for smooth height adjustment.



Image: Connecting the drive rod for synchronized leg movement.

Step 8: Mount Control Panel

Mount the control panel (B16) to the underside of the desktop using screws (d). Ensure it is positioned conveniently for access.



Image: Attaching the desk's control panel.

Step 9: Connect Power Adapter

Connect the power adapter (B17) to the control panel and then plug it into a suitable power outlet. Ensure all electrical connections are secure.



Image: Plugging in the power adapter.

Step 10: Cable Management

Use the provided cable ties (g) to organize and secure all cables neatly under the desk. This helps maintain a tidy workspace and prevents cables from getting caught during height adjustments.



Image: Organizing cables with cable ties.

Step 11: Install Headphone Hook

Attach the headphone hook (B12) to the underside of the desk as desired. This provides a convenient storage spot for headphones.



Image: Attaching the headphone hook.

Step 12: Insert Cable Grommet

Place the cable grommet (B13) into the pre-drilled hole on the desktop. This allows for neat routing of cables through the desk surface.



Image: Placing the cable grommet for cable organization.

4. OPERATING INSTRUCTIONS

Your JUMMICO Electric Height Adjustable Desk offers intuitive controls for a personalized workspace.

Video: Demonstration of the desk's height adjustment and features.

Control Panel Overview:



Image: Detailed view of the multi-function intelligent keypad.

- **LED Display:** Shows the current desk height in centimeters.
- **Up/Down Buttons (+/-):** Press and hold to adjust the desk height continuously. Release to stop at the desired height.
- **Memory Presets (1, 2):**
 1. Adjust the desk to your desired sitting or standing height.
 2. Press the 'M' button, then press '1' or '2' to save the current height.
 3. To recall a saved height, simply press the corresponding '1' or '2' button.
- **Timed Reminders (Clock Icon):** Activates a reminder to change posture after a set period (e.g., 50 minutes sitting, 10 minutes standing).
- **USB Charging Port:** Conveniently located on the control panel for charging mobile devices.

Anti-Collision Function:

The desk is equipped with an anti-collision system. If the desktop encounters an obstacle during height adjustment, it will automatically stop and reverse slightly to prevent damage. This feature enhances safety during operation.



Image: Smooth and quiet operation with anti-collision feature.

5. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your JUMMICO desk.

- **Cleaning:** Wipe the desktop and frame with a soft, damp cloth. Avoid abrasive cleaners or harsh chemicals that could damage the surface. The laminated surface is designed for easy cleaning.
- **Regular Checks:** Periodically check all screws and connections to ensure they remain tight. Retighten if necessary.
- **Cable Management:** Ensure cables remain organized and are not pinched or tangled, especially during height adjustments.
- **Environmental Conditions:** Avoid exposing the desk to extreme temperatures or high humidity.

6. TROUBLESHOOTING

If you encounter any issues with your desk, refer to the following common problems and solutions.

- **Desk Not Moving:**
 - Check if the power cable is securely plugged into both the desk and the wall outlet.
 - Ensure no objects are obstructing the desk's movement.
 - If an error code appears on the LED display, refer to the specific troubleshooting section in the full manual (if available) or contact customer support.
- **Uneven Movement:**
 - Verify that the drive rod (B10) is correctly installed and connected to both legs.
 - Check for any loose connections in the frame assembly.
- **Noise During Operation:**
 - A low noise level (below 55 dB) is normal. If the noise is excessive, check for loose components or obstructions.
- **USB Port Not Charging:**
 - Ensure the desk is powered on.
 - Try a different USB cable or device to rule out external issues.

If the problem persists after attempting these solutions, please contact JUMMICO customer support for assistance.

7. SPECIFICATIONS

Key technical details for your JUMMICO Electric Height Adjustable Desk.

Feature	Specification
Brand	JUMMICO
Model Number	0183
Color	White
Product Dimensions (L x W x H)	200 x 80 x 73-118 cm
Adjustable Height Range	73 cm to 118 cm
Weight Capacity	60 kg
Material	Laminate, Alloy Steel, Steel
Special Features	Electric Height Adjustment, USB Charging Port, Anti-Collision Function, Memory Presets
Noise Level	Below 55 dB
Item Weight	22 Kilograms

8. WARRANTY AND SUPPORT

JUMMICO stands behind the quality of its products. Your desk comes with a worry-free guarantee, ensuring peace of mind.

- **Warranty:** Please refer to your purchase documentation for specific warranty terms and conditions.
- **Customer Support:** For any questions, technical assistance, or warranty claims, please contact JUMMICO customer service through the retailer where you purchased the product.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0CX2WR93Z>

More documents and user manuals: <https://manuals.plus/>