Spider Farmer 6L Humidifier & SF1000D Kit

Spider Farmer 6L Grow Tent Humidifier and SF1000D Tent Kit Complete System User Manual

Model: 6L Humidifier & SF1000D Kit

1. Product Overview

The Spider Farmer 6L Grow Tent Humidifier and SF1000D Tent Kit is a comprehensive system designed for indoor plant cultivation. This kit provides an optimized environment for plant growth, combining efficient lighting, precise humidity control, and effective ventilation.

Kit Components:

- SF1000D LED Grow Light
- Grow Tent (e.g., 2x2x4.6ft)
- 6L Grow Tent Humidifier with extendable tubing and sensor probe
- Inline Fan (e.g., 4-inch)
- Carbon Filter (e.g., 4-inch)
- Ducting
- Fan Speed Control
- Clip Fan (e.g., 6-inch)
- Temperature Humidity Monitor
- Timer
- 5 Gallon Grow Bags (x3)
- Trellis Plant Netting
- YOYO Hanger (x2)
- Vent Cover (x2)
- Corner Shelves (x2)
- Hose Clamps
- Other necessary accessories for assembly



Figure 1: All components included in the Spider Farmer Grow Tent Kit, with labels for identification.

2. Setup Guide

Follow these steps to properly set up your Spider Farmer Grow Tent System.

2.1 Grow Tent Assembly

1. Unpack all tent frame components and the tent fabric.
2. Assemble the steel frame according to the included diagram, ensuring all poles are securely connected.
3. Drape the heavy-duty 1680D Oxford cloth tent fabric over the assembled frame.
4. Zip up the tent completely, ensuring the SBS zippers operate smoothly and the double stitching provides light protection.
5. Install the removable viewing mesh screen.
6. Place the bottom tray inside the tent to prevent water leakage.



Figure 2: Assembled grow tent with internal components.

2.2 Grow Light Installation (SF1000D)

1. Attach the YOYO hangers to the top bars of the grow tent.
2. Connect the SF1000D LED grow light to the hangers, ensuring it is level and securely suspended.
3. Position the light at the appropriate height above your plants, adjusting with the hangers as needed.
4. Connect the power cord to the light and route it through one of the tent's electrical cord openings.



Figure 3: SF1000D LED Grow Light with Samsung LM301B Diodes.

2.3 Humidifier Setup

1. Place the 6L humidifier outside the grow tent for optimal space utilization and ease of refilling.
2. Connect the extendable tubing to the humidifier's mist output.
3. Route the tubing into the grow tent through a designated opening, positioning the mist output near the plants.
4. Insert the sensor probe into the grow tent to accurately monitor internal humidity and temperature.
5. Fill the humidifier tank with clean water.



Figure 4: Humidifier positioned outside the grow tent with tubing.

2.4 Ventilation System Setup

1. Mount the inline fan and carbon filter within or outside the tent, connecting them with ducting and hose clamps. Ensure proper airflow direction (typically pulling air out of the tent).
2. Connect the ducting to the tent's ventilation openings.
3. Install the clip fan inside the tent to ensure air circulation around the plants.
4. Connect the fan speed control to the inline fan.

3. Operating Instructions

3.1 Humidifier Operation

The 6L humidifier features a digital control panel for precise environmental management.

- **Power On/Off:** Press the **On/Off** button to activate or deactivate the unit.

- **Humidity Adjustment:** Use the **Humidity** button to set the desired humidity level between 35% and 95% in 5% increments. The built-in hygrometer will display the current humidity.
- **Mist Levels:** Select from 1 to 4 levels of fog volume using the **Mist** button to control the mist output (max 450 ml/h).
- **Timer Setting:** Utilize the **Timer** button to set operation duration from 1 to 12 hours in 1-hour increments. The humidifier will automatically shut off after the set time.
- **Low Water Auto Shut-off:** The unit will automatically turn off when water levels are low to prevent damage.




Figure 5: Humidifier LED Digital Control Panel.

3.2 Grow Light Operation (SF1000D)

The SF1000D LED grow light provides full spectrum illumination for all stages of plant growth.

- **Power On/Off:** Connect the light to a power source. Use an external timer (included) to automate lighting cycles.
- **Spectrum:** The light provides a full spectrum suitable for vegetative and flowering stages.
- **Efficiency:** The SF1000D consumes only 100W while delivering powerful light output.

3.3 Ventilation System Operation

- **Inline Fan:** Use the fan speed control to adjust the airflow rate of the inline fan, ensuring proper air exchange and temperature regulation within the tent.
- **Carbon Filter:** The carbon filter works in conjunction with the inline fan to remove odors from the exhaust air.
- **Clip Fan:** Position the clip fan to provide gentle air movement around the plant canopy, which helps strengthen stems and prevent stagnant air pockets.

4. Maintenance

Regular maintenance ensures the longevity and optimal performance of your grow system.

4.1 Humidifier Cleaning

- **Weekly:** Empty and rinse the water tank and base. Use a soft brush or cloth to clean any mineral deposits.
- **Monthly:** For stubborn mineral buildup, use a descaling solution (e.g., white vinegar and water) to soak the tank and ultrasonic transducer. Rinse thoroughly before refilling.
- Ensure the humidifier is unplugged before any cleaning.

4.2 Grow Tent Cleaning

- **Regularly:** Wipe down the interior Mylar lining with a damp cloth to maintain reflectivity.
- **As needed:** Clean the exterior Oxford cloth with a mild detergent and water.
- Ensure the tent is dry before zipping it up for extended periods.

4.3 Grow Light Care

- **Periodically:** Gently wipe the LED board with a dry, soft cloth to remove dust and debris. Do not use liquids directly on the diodes.
- The protective coating on the LEDs helps extend lifespan; avoid scratching it.

5. Troubleshooting

Refer to this section for common issues and their solutions.

Problem	Possible Cause	Solution
Humidifier not producing mist.	Low water level; clogged transducer; power issue.	Refill water tank; clean transducer; check power connection.
Grow light not turning on.	Power cord disconnected; external timer off; faulty outlet.	Ensure power cord is fully plugged in; check timer settings; test outlet with another device.
Tent interior humidity too high/low.	Humidifier settings incorrect; ventilation inadequate.	Adjust humidifier mist level/target humidity; increase/decrease inline fan speed.
Unusual odors from tent.	Carbon filter saturation; poor air exchange.	Check carbon filter lifespan and replace if necessary; ensure inline fan is operating effectively.

6. Specifications

Key specifications for the Spider Farmer 6L Grow Tent Humidifier and SF1000D Tent Kit.

Feature	Detail
Brand	Spider Farmer
Humidifier Capacity	6 Liters
Humidifier Mist Output	Up to 450 ml/h
Humidifier Humidity Range	35%-95% (5% intervals)
Humidifier Timer	1-12 hours (1-hour increments)
Grow Light Model	SF1000D
Grow Light Diodes	Samsung LM301B
Grow Light Power Consumption	100W
Grow Tent Material	1680D Oxford cloth, 100% Reflective Mylar interior
ASIN	B0CX8XJ94

7. Warranty and Support

Spider Farmer products are designed for durability and performance. For specific warranty details, please refer to the warranty card included with your purchase or visit the official Spider Farmer website.
For technical support, troubleshooting assistance, or replacement parts, please contact Spider Farmer customer service through their official channels. Provide your product model and purchase date for faster service.
Official Website: www.spider-farmer.com

© 2024 Spider Farmer. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question