**Surtime 42IN-6666**

# Surtime 42-inch Low Profile Ceiling Fan with Light and Remote/APP Control

Model: **42IN-6666**

## 1. Product Overview

This manual provides detailed instructions for the installation, operation, and maintenance of your Surtime 42-inch Low Profile Ceiling Fan. Please read this manual thoroughly before installation and retain it for future reference.



Figure 1: Surtime 42-inch Low Profile Ceiling Fan with Light and Remote/APP Control. This image shows the complete ceiling fan unit, including the five brown blades, the central light fixture, and the black motor housing. A remote control and a smartphone displaying the control app are also visible, indicating multiple control options.

## 2. Key Features

- **Dimmable LED Lighting:** Features three color temperature options (3000K-6000K) and adjustable brightness from 10% to 100%.
- **Dual Control:** Operable via both remote control and a dedicated mobile application.
- **6-Speed Settings:** Offers six wind speed options for customized comfort.
- **Reversible DC Motor:** Supports both forward (summer) and reverse (winter) rotation for year-round air circulation.
- **Quiet Operation:** High-quality DC motor ensures silent performance, with sound levels less than 30dB.
- **Smart Memory Function:** Remembers preferred brightness and color settings.
- **Easy Installation:** Innovative snap-in blade design simplifies assembly.




Figure 2: Remote Control Features. This image highlights the remote control for the ceiling fan, detailing its functions: 6 speeds, 3000K-6500K color temperature, 2H/4H timer, and forward/reverse rotation.




Figure 3: Three Color Light Options. This image illustrates the three color temperature options for the fan's LED light: 3000K (Warm Light), 4500K (Natural Light), and 6000K (White Light).




Figure 4: Reversible Motor Function. This image demonstrates the two modes of the reversible motor: downdraft mode for cooling in summer and updraft mode for circulating warm air in winter.

## 3. Setup and Installation

Before beginning installation, ensure the power is turned off at the circuit breaker. It is recommended to have a qualified electrician perform the installation if you are unsure.

### 3.1 Unpacking and Component Check

Carefully unpack all components and verify against the packing list. Ensure all parts are present and undamaged.

Your browser does not support the video tag.

Video 1: 6669 Ceiling Fans with Lights Installation. This video provides a detailed visual guide for the installation process of the ceiling fan, including unpacking and assembly steps.

### 3.2 Blade Installation

The fan features an innovative snap-in blade design for easy installation without the need for screws. Simply align the blade with the motor assembly and push until it clicks into place.




Figure 5: Snap-in Blade Installation. This image shows the simple process of attaching the fan blades to the motor housing, highlighting the screw-less design.

### 3.3 Mounting the Fan

Secure the mounting bracket to the ceiling junction box. Connect the electrical wires according to local electrical codes (black to live, white to neutral, green/bare to ground). Carefully lift the fan assembly and attach it to the mounting bracket.

Your browser does not support the video tag.

Video 2: 36IN Ceiling Fan Installation Display Video. This video demonstrates the installation of a 36-inch ceiling fan, which shares similar mounting procedures with the 42-inch model.

## 4. Operating Instructions

### 4.1 Remote Control Operation

The included remote control allows full functionality of the fan and light. Refer to Figure 2 for button layout and functions.

- **Fan Speed:** Use buttons 1-6 to adjust fan speed. 1-2 for comfortable wind, 3-4 for natural wind, 5-6 for strong wind.
- **Light Control:** Turn light ON/OFF, adjust brightness (+/-), and change color temperature (3000K, 4500K, 6000K).
- **Timer:** Set the fan to turn off automatically after 2 or 4 hours.
- **Reverse Function:** Press the reverse button to switch between summer (downdraft) and winter (updraft) modes. The fan will stop completely and then automatically reverse.




Figure 6: Adjustable Wind Speeds. This image visually represents the six adjustable wind speeds, categorized into comfortable, natural, and strong wind settings.




Figure 7: Remote Control Layout. This image provides a detailed diagram of the remote control, labeling each button for light control, fan speed, timing, and forward/reverse functions.

### 4.2 APP Control Operation

The fan can also be controlled via the "Fan Lamp Pro" mobile application. Follow these steps to connect:

1. Scan the QR code provided in Figure 8 to download the "Fan Lamp Pro" app.
2. Ensure Bluetooth is enabled on your smartphone.
3. Turn off the main power to the fan at the wall switch.
4. Turn on the main power to the fan. Within 5 seconds, open the app and click the pairing button (usually a "+" or "connect" icon) repeatedly until the fan light blinks twice, indicating a successful connection.
5. Once connected, you can control fan speed, light settings, and reverse function directly from the app.




Figure 8: APP Control Method. This image displays the QR code for downloading the "Fan Lamp Pro" app and shows screenshots of the app interface for controlling the fan's functions.

Your browser does not support the video tag.

Video 3: APP Control Method Video. This video demonstrates how to connect and control the ceiling fan using the mobile application, including language settings, device adding, and function control.

Your browser does not support the video tag.

Video 4: 6669 Brown ceiling fans with lights APP control. This video specifically shows the APP control for the brown model of the ceiling fan, demonstrating light and fan speed adjustments.

Your browser does not support the video tag.

Video 5: 6669 White APP Controls Connection Display. This video illustrates the APP connection process for the white model, showing how to pair the fan with the application.

## 5. Maintenance

Regular maintenance ensures optimal performance and longevity of your ceiling fan.

- **Cleaning:** Use a soft, damp cloth to clean the fan blades and motor housing. Do not use abrasive cleaners or solvents.
- **Blade Balance:** If the fan wobbles, check that all blades are securely attached and balanced. A balancing kit may be used if necessary.
- **Light Source:** The LED light source is designed for long life. If replacement is needed, contact customer support.

## 6. Troubleshooting

| Problem | Possible Cause | Solution |
| --- | --- | --- |

| Problem | Possible Cause | Solution |
|---|---|---|
| Fan does not operate. | No power supply; loose wiring; remote control battery low. | Check circuit breaker; ensure all connections are secure; replace remote control batteries. |
| Light does not turn on. | Loose wiring; LED module issue. | Check wiring connections; contact customer support if LED module is faulty. |
| Fan wobbles. | Loose blades; unbalanced blades; improper mounting. | Ensure blades are securely attached; use balancing kit; re-check mounting bracket installation. |
| Remote/APP not responding. | Pairing issue; battery low (remote); Bluetooth off (APP). | Re-pair the remote/APP (refer to Section 4); replace remote batteries; ensure Bluetooth is on. |

## 7. Specifications

| Specification | Value |
|---|---|
| Brand | Surtime |
| Model Name | 42IN-6666-Brown |
| Size | 42 inches |
| Color | Brown |
| Material | Acrylic |
| Light Source Type | LED |
| Light Color Temperature | 3000K-6000K |
| Wattage | 36 watts |
| Voltage | 110 Volts |
| Control Method | App, Remote |
| Special Features | Removable Lampshade, APP Control, Timer, Dimmable Light, Light Memory Function |
| Item Weight | 6.76 pounds |
| Product Dimensions | 3.94"L x 3.94"W x 3.94"H |

## 8. Warranty and Support

Surtime ceiling fans come with a worry-free 1-year warranty on quality-related issues. If you encounter any problems or have questions, please do not hesitate to contact us.
For further assistance, you can visit the Surtime Store on Amazon.
For APP related inquiries, you can visit https://www.jasonghost.com/fanlamppro/.

© 2025 Surtime. All rights reserved.