

Torin AGPZ30112NB

Torin Garage Storage System Heavy Duty 12-Piece Metal
Organization Workbench Instruction Manual

Model: AGPZ30112NB

	Introduction	Safety Information	Package Contents	Setup &
Assembly	Operation	Maintenance	Troubleshooting	Specifications
				Support

1. INTRODUCTION

This manual provides detailed instructions for the assembly, operation, and maintenance of your Torin Heavy Duty 12-Piece Metal Garage Storage System. This comprehensive system is designed to enhance organization and functionality in garages, workshops, and other utility areas. It features a robust, fully welded steel construction, ensuring durability and security for your stored items.

Please read this manual thoroughly before beginning assembly or operation to ensure safe and correct usage. Keep this manual for future reference.



Image 1.1: The complete Torin 12-Piece Garage Storage System, showcasing its modular design and ample storage capacity.

2. SAFETY INFORMATION

Always prioritize safety during assembly and use. Failure to follow these instructions may result in injury or damage to the product.

- **Read All Instructions:** Before assembly or use, read and understand all instructions and warnings in this manual.
- **Proper Tools:** Use appropriate tools for assembly. Ensure all fasteners are tightened securely.
- **Stable Surface:** Assemble the system on a flat, level, and stable surface.
- **Wall Connection:** Utilize the back slots for wall connection to prevent tipping, especially for tall cabinets. This is crucial for stability and safety.
- **Weight Capacity:** Do not exceed the stated weight capacities for shelves (150 lbs) and drawers (100 lbs). Overloading can cause structural failure.
- **Children and Pets:** Keep children and pets away from the assembly area. Do not allow them to climb on or play with the cabinets.
- **Locking Mechanism:** Ensure all lockable cabinets are secured when not in use, especially if storing hazardous materials or valuable items.
- **Moving Cabinets:** When moving rolling cabinets, ensure casters are unlocked. Lock casters once the cabinet is in its desired position.
- **Maintenance:** Regularly inspect the system for loose fasteners, damage, or wear. Address any issues promptly.

3. PACKAGE CONTENTS

The Torin 12-Piece Garage Storage System includes the following components:

- 2x Tall Cabinets
- 2x Base Cabinets with 4 Drawers (Rolling)
- 2x Base Cabinets with 1 Drawer and 2 Doors
- 2x Wood Worktops (1" thick)
- 4x Small Top Wall Cabinets

Verify all components are present and undamaged before proceeding with assembly. Contact customer support if any parts are missing or damaged.



Image 3.1: Dimensions of individual cabinet types: Tall Cabinet (75.98" H x 29.53" W x 18.58" D), Base Cabinet (32.68" H x 23.62" W x 16.14" D), and Wall Cabinet (15.75" H x 23.62" W x 12.3" D).

PRODUCT DIMENSIONS



Image 3.2: Detailed dimensions for the 2-door base cabinet (32.67" H x 23.62" W x 16.14" D) and the 4-drawer rolling cabinet (32.67" H x 23.62" W x 16.14" D).

4. SETUP & ASSEMBLY

Assembly of the Torin Garage Storage System requires careful attention to detail. It is recommended to have at least two people for assembly due to the size and weight of the components.

4.1 General Assembly Steps

1. **Unpack Components:** Carefully remove all parts from their packaging. Lay them out on a clean, protected surface to prevent scratches.
2. **Assemble Individual Units:** Follow the specific instructions provided with each cabinet type (tall, base, wall) for individual unit assembly. Ensure all panels are correctly oriented and fasteners are tightened.
3. **Install Shelves:** For tall cabinets, install the three adjustable shelves. Shelves can be adjusted in 3-inch increments to suit your storage needs.
4. **Attach Adjustable Feet:** Screw the adjustable feet onto the bottom of the tall cabinets and stationary base cabinets. Adjust them to ensure the cabinets are level and stable on uneven floors.
5. **Attach Casters:** For the 4-drawer rolling cabinets, attach the 360-degree swivel casters to the base. Ensure they are securely fastened.
6. **Position Units:** Arrange the assembled cabinets in your desired configuration.
7. **Connect Units:** Use the side holes provided to connect adjacent cabinets together. This enhances the overall

stability and rigidity of the system.

8. **Install Worktops:** Place the 1-inch thick wood worktops onto the base cabinets. Secure them as per the specific instructions.
9. **Wall Mounting:** For enhanced stability and to prevent tipping, especially for tall cabinets and wall cabinets, utilize the back slots to connect the units to a wall. Appropriate wall anchors and fasteners (not included) should be used based on your wall type.

4.2 Leveling and Stability

The adjustable legs on the heavy-duty storage cabinets are designed to help maintain a level and balanced system. After positioning your cabinets, use a level to ensure each unit is plumb and level. Adjust the feet as necessary.



Image 4.1: The assembled system showing overall dimensions: approximately 75.98" in height and 153.6" in width, with a depth of 18.6".

5. OPERATION

Your Torin Garage Storage System is designed for efficient and secure storage. Familiarize yourself with its features for optimal use.

5.1 Lockable Cabinets and Drawers

- All garage storage cabinets are fully lockable. Use the provided keys to secure your items.
- The doors feature magnetic latches to keep them closed when unlocked.
- The 4-drawer rolling cabinets also include a locking mechanism for the drawers.

5.2 Adjustable Shelving

- Tall cabinets contain three shelves adjustable in 3-inch increments. Adjust shelf height by repositioning the shelf clips in the desired slots.
- Each shelf has a loading capacity of 150 lbs. Do not exceed this limit.

5.3 Rolling Cabinets

- The 4-drawer base cabinets are equipped with 360-degree swivel casters for mobility.
- To move a cabinet, unlock the casters. To secure it in place, engage the caster locks.
- Drawer slides have a 100 lbs loading capacity.

5.4 Wood Worktop

- The 1-inch thick wood worktop provides a durable surface for various tasks and tool operation.



Image 5.1: Key features of the system including lockable cabinets, 360-degree swivel casters for mobility, the durable pressed wood worktop, and magnetic latches for secure door closure.



Image 5.2: An example of the workbench in use, demonstrating its utility for organizing and accessing tools.

6. MAINTENANCE

Regular maintenance will ensure the longevity and optimal performance of your storage system.

- **Cleaning:** Wipe down metal surfaces with a soft, damp cloth and mild detergent. Avoid abrasive cleaners that can damage the powder-coated finish. For the wood worktop, clean spills immediately and use appropriate wood cleaning products.
- **Inspection:** Periodically check all bolts, screws, and fasteners to ensure they are tight. Re-tighten any loose hardware.
- **Caster Care:** Keep casters clean and free of debris. Lubricate swivel and axle points if movement becomes stiff.
- **Drawer Slides:** Ensure drawer slides operate smoothly. If they become stiff, clean and apply a silicone-based lubricant.
- **Damage:** Inspect for any signs of damage, such as dents or rust. Address minor rust spots with appropriate rust treatment to prevent spread.

7. TROUBLESHOOTING

This section addresses common issues you might encounter with your storage system.

Problem	Possible Cause	Solution
Cabinet is wobbly or unstable.	Uneven floor; adjustable feet not properly set; units not connected; not wall-mounted.	Adjust the leveling feet until the cabinet is stable. Ensure adjacent units are connected. Secure tall cabinets to the wall using the provided back slots.
Drawer or door does not close smoothly.	Obstruction in slide/hinge; bent component; unit not level.	Check for obstructions. Ensure the cabinet is level. Inspect slides/hinges for damage. Clean and lubricate drawer slides if necessary.
Casters do not roll freely or lock.	Debris in casters; damaged caster; lock mechanism jammed.	Clean any debris from the casters. Lubricate swivel points. If damaged, casters may need replacement.
Cabinet doors do not stay closed.	Weak magnetic latches; cabinet not level; door hinges misaligned.	Ensure the cabinet is level. Check magnetic latches for proper alignment and function. Adjust door hinges if necessary.

8. SPECIFICATIONS

Feature	Detail
Model Number	AGPZ30112NB
Brand	Torin
Overall System Dimensions (Approx.)	153.6" W x 75.98" H x 18.6" D
Material	Fully Welded Steel (cabinets), Wood (worktop)
Finish	Scratch and Stain Resistant Powder Coated
Color	Black/Grey
Tall Cabinet Shelf Capacity	150 lbs per shelf (3 adjustable shelves)
Drawer Capacity	100 lbs per drawer
Special Features	Adjustable Feet, Adjustable Shelves, Heavy Duty Construction, Lockable Doors/Drawers, Scratch Resistant Finish, Magnetic Latches, 360-degree Swivel Casters (on rolling units), Wall Connection Slots
UPC	810151422411
Item Weight (Total)	Approximately 493 lbs

9. WARRANTY AND CUSTOMER SUPPORT

For warranty information, missing parts, or technical assistance, please contact Torin customer support. Keep your purchase receipt and model number (AGPZ30112NB) readily available when contacting support. Contact information can typically be found on the manufacturer's website or on the product packaging.

© 2024 Torin. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question