Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

UGREEN CM818 P/N: 45363

UGREEN Revodok Pro 106 USB C Hub User Manual

Model: CM818 P/N: 45363

Product Overview

The UGREEN Revodok Pro 106 USB C Hub is a versatile 6-in-1 multiport adapter designed to expand the connectivity of your USB-C enabled devices. It integrates essential ports for display, data transfer, and power delivery, enhancing productivity and convenience for various computing environments.



Image: The UGREEN Revodok Pro 106 USB C Hub, a compact grey device with a short braided USB-C cable, showcasing its various ports including USB-C, USB-A, and HDMI.

Key Features

- **6-in-1 Connectivity:** Equipped with a 4K@60Hz HDMI port, two 10 Gbps USB-C data ports, two 10 Gbps USB-A data ports, and a 100W USB-C Power Delivery (PD) port.
- **Ultra-Fast Data Transfer:** Four 10 Gbps data ports (2x USB-C, 2x USB-A) enable rapid file transfers, significantly boosting workflow efficiency. *Note: The USB-C data ports do not support video output or charging.*
- **Brilliant 4K@60Hz Display:** The HDMI port supports high-resolution video output, ideal for presentations, extended displays, or multimedia consumption.
- **100W Pass-Through Charging:** Provides up to 85W power delivery to your laptop through the dedicated USB-C PD port, ensuring continuous operation.
- **Durable and Safe Design:** Features an exclusive aluminum alloy casing for efficient heat dissipation and incorporates 4-layer safety features, including overcurrent, overvoltage, overheating, and short-circuit protection. An indicator light shows operational status.
- **Universal Compatibility:** Compatible with a wide range of USB-C devices, including MacBook Pro/Air, iPad Pro, iPhone 16 Series, Chromebooks, Surface Pro, HP Envy, XPS, Steam Deck, and Switch OLED.



Image: Close-up view of the UGREEN Revodok Pro 106 hub, clearly labeling its six ports: USB-C PD (100W), two USB-A 3.2 (10Gbps), two USB-C 3.2 (10Gbps), and HDMI (4K@60Hz).

Setup Instructions

1. **Connect to Host Device:** Plug the integrated USB-C cable of the Revodok Pro 106 hub into a full-function USB-C port on your laptop, tablet, or smartphone. Ensure the USB-C port on your host device supports data, video (DisplayPort Alt Mode), and power delivery for full functionality.
2. **Power Connection (Optional but Recommended):** For stable operation and to charge your host device, connect a USB-C Power Delivery (PD) charger (up to 100W) to the USB-C PD port on the hub. This port supports up to 85W pass-through charging to your host device.
3. **Connect Peripherals:**
    - **HDMI Display:** Connect an HDMI cable from the hub's HDMI port to your monitor or TV for video output.
    - **USB Data Devices:** Plug in USB-A or USB-C peripherals such as external hard drives, USB flash drives, keyboards, or mice into the respective 10 Gbps data ports.
4. **Verify Connection:** The indicator light on the hub will illuminate when properly connected and powered, signifying

operational status. Your operating system should automatically detect and configure connected devices.



Image: A laptop being charged via the UGREEN Revodok Pro 106 hub, which is connected to a wall charger. This illustrates the 100W input and 85W output pass-through charging capability.

Operating Instructions

Once the UGREEN Revodok Pro 106 is set up, it operates as a plug-and-play device. No additional drivers are typically required for most operating systems.

- **Display Output:** After connecting an HDMI display, your operating system's display settings can be used to configure mirror mode, extended desktop, or primary display. Ensure your display is set to the correct input source.
- **Data Transfer:** Files can be transferred to and from connected USB-A and USB-C storage devices at speeds up to 10 Gbps. Drag and drop files as you normally would with directly connected devices.
- **Power Delivery:** The hub will automatically manage power delivery to your host device when a compatible PD charger is connected to the hub's PD port. The indicator light confirms power flow.
- **Peripheral Use:** Keyboards, mice, webcams, and other USB peripherals will function immediately upon connection.



Image: Two individuals collaborating, with one using a laptop connected to a large external monitor via the UGREEN Revodok Pro 106 hub, demonstrating its 4K@60Hz display capability.



Image: A close-up of the UGREEN Revodok Pro 106 hub highlighting the "10Gbps" labels on its USB-A and USB-C data ports, illustrating its ultra-fast data transfer capabilities.

Maintenance

The UGREEN Revodok Pro 106 is designed for durability and requires minimal maintenance.

- **Cleaning:** Use a soft, dry cloth to wipe the surface of the hub. Avoid using liquid cleaners, aerosols, or abrasive materials, as these can damage the device.
- **Storage:** When not in use, store the hub in a cool, dry place away from direct sunlight and extreme temperatures.
- **Handling:** Avoid dropping the device or subjecting it to strong impacts. Do not attempt to disassemble or modify the hub, as this will void the warranty and could cause damage.
- **Port Care:** Ensure that cables are inserted and removed gently to prevent damage to the ports. Keep ports free of dust and debris.



Image: An exploded view of the UGREEN Revodok Pro 106 hub, illustrating its internal components and the aluminum alloy casing designed for efficient heat dissipation, ensuring stable performance.

Troubleshooting

If you encounter issues with your UGREEN Revodok Pro 106, refer to the following common solutions:

Problem	Possible Cause	Solution
No display output via HDMI.	Host USB-C port does not support DisplayPort Alt Mode. Incorrect display input selected. Faulty HDMI cable or monitor.	Ensure your device's USB-C port is full-featured. Select the correct HDMI input on your monitor/TV. Try a different HDMI cable or monitor. Restart your host device.
USB devices not recognized or unstable.	Insufficient power. Loose connection. Driver issues on host device.	Connect a PD charger to the hub's PD port. Ensure all connections are secure. Try connecting the USB device directly to the host to rule out driver issues.

Problem	Possible Cause	Solution
Host device not charging via PD port.	PD charger not connected or insufficient wattage. Host device does not support USB-C PD charging.	Ensure a compatible USB-C PD charger (min. 65W recommended) is connected to the hub. Verify your host device supports USB-C PD charging.
Slow data transfer speeds.	Connected device is not 10Gbps compatible. Host USB-C port is not 10Gbps compatible.	Ensure both the connected device and host port support USB 3.2 Gen 2 (10Gbps). Avoid transferring very large numbers of small files simultaneously.

Specifications

Attribute	Detail
Brand	UGREEN
Model Number	CM818 P/N: 45363
Connectivity	6-in-1 (HDMI, 2x USB-A 3.2, 2x USB-C 3.2, USB-C PD)
HDMI Output	4K@60Hz
USB Data Transfer Rate	10 Gigabits Per Second (Gbps)
USB-C PD Input	Up to 100W
USB-C PD Output	Up to 85W (Pass-Through Charging)
Total USB Ports	4 (2x USB-A, 2x USB-C for data)
Material	Plastic, Aluminum Alloy
Colour	Grey
Product Dimensions	11.5 x 3.5 x 1.25 cm
Item Weight	109 g
Compatible Operating Systems	Chrome OS, Linux, Windows, macOS
Special Features	Fast Data Transfer, Lightweight, Plug and Play, Portable



Image: A diagram illustrating the universal compatibility of the UGREEN Revodok Pro 106 hub with various host devices (MacBook, Laptop, Tablet, Smartphone, Game Console) and operating systems (Windows, macOS, Linux, Android), emphasizing the requirement for a full-function USB-C port.

Warranty and Support

UGREEN products typically come with a standard manufacturer's warranty. For specific warranty details, duration, and terms, please refer to the warranty card included with your product or visit the official UGREEN website.
For technical support, troubleshooting assistance, or warranty claims, please contact UGREEN customer service through their official website or the contact information provided in your product packaging. When contacting support, please have your product model number (CM818 P/N: 45363) and purchase details ready.

Online Resources:

- UGREEN Official Website: www.ugreen.com
- Product Support Page: Check the UGREEN website for a dedicated support page for the Revodok Pro 106 (Model: CM818 P/N: 45363) for FAQs, driver downloads (if any), and further assistance.

© 2025 UGREEN. All rights reserved.
This manual is for informational purposes only. Specifications are subject to change without notice.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0D1XLNWP2

More documents and user manuals: **https://manuals.plus/**