

[Manuals.plus](#) /

› [Sarpaws](#) /

› Automatic Cat Feeder, Cat Food Dispenser Battery-Operated with 180-Day Battery Life, Timed Pet Feeder for Cats and Dogs, Desiccant Bag, Programmable Portion Control, 4 Daily Meals, 10s Voice Recorder

Sarpaws F14

Sarpaws Automatic Cat Feeder Instruction Manual

Model: F14

INTRODUCTION

Thank you for choosing the Sarpaws Automatic Cat Feeder. This device is designed to simplify your pet feeding routine, ensuring your cat or small dog receives timely and portion-controlled meals. With features like voice recording, power outage backup, and a fresh-keeping design, it offers convenience and peace of mind.



The Sarpaws Automatic Cat Feeder, ready for use with dry kibble in its bowl.

WHAT'S IN THE BOX

- Automatic Pet Feeder Base Unit
- Food Storage Container (3L capacity)
- Stainless Steel Food Bowl
- Bowl Holder
- Lid with Desiccant Box
- Food Dispensing Rotor
- USB Power Cable
- Power Adapter
- User Manual

SETUP

1. **Assemble the Bowl:** Place the stainless steel bowl into the plastic bowl holder.
2. **Attach the Bowl to the Base:** Align the bowl holder with the front opening of the feeder base unit and slide it into place.
3. **Insert Dispensing Rotor:** Place the food dispensing rotor into the designated slot inside the feeder base. Ensure it is securely seated.
4. **Attach Food Storage Container:** Place the 3L food storage container onto the feeder base, aligning it with the dispensing mechanism.
5. **Add Desiccant:** Open the desiccant box on the underside of the lid and insert the provided desiccant packet to help keep food fresh. Close the box and secure the lid onto the food storage container.
6. **Power the Feeder:** Connect the USB power cable to the feeder's power port (located at the bottom rear) and plug the adapter into a wall outlet. For backup power, install three D-size batteries (not included) in the battery compartment at the bottom of the unit.

Power Outage Backup

The feeder supports dual power modes (AC adapter and D-size batteries) to ensure continuous operation even during power outages. This feature guarantees your pet will always be fed according to schedule.

Power Outage Backup

Your pets will still be fed even if there is a power outage



The feeder can be powered via AC adapter or D-size batteries for uninterrupted feeding.

OPERATING INSTRUCTIONS

The control panel is located on the back of the feeder. It features a display and buttons for setting time, meals, portions, and voice recording.

Setting Time and Meals

1. **Unlock the Panel:** Press and hold the 'Settings' (gear icon) button for a few seconds until the lock icon on the display disappears.
2. **Set Current Time:** Use the '+' and '-' buttons to adjust the hour and minutes. Press 'Settings' to confirm each adjustment and move to the next.

3. **Program Meals:** The feeder allows up to 4 daily meals. For each meal (Meal 1, Meal 2, etc.):
- Select the meal number using the 'Settings' button.
 - Set the desired feeding time (hour and minute) using '+' and '-' buttons, confirming with 'Settings'.
 - Set the portion size (1-9 portions) using '+' and '-' buttons, confirming with 'Settings'.

Feeding Schedule & Portion Adjustment

Give small portions of dry food a few times a day



The feeder allows scheduling up to 4 meals per day with adjustable portion sizes (1-9 portions per meal).

Voice Recording

Record a 10-second voice message to call your pet at meal times. Press and hold the 'Microphone' button to start recording. Release to stop. The recorded message will play before each scheduled meal.

Leave a Personal Message For Pet

Record your own voice 10 seconds



Record a personalized 10-second voice message to call your pet for meals.

Manual Feeding

To dispense food manually, press and hold the '+' button. Each press will dispense one portion. This is useful for training or providing extra treats.

Official Product Video

An official video from Sarpaws demonstrating the automatic pet feeder's features and operation.

MAINTENANCE AND CLEANING

Regular cleaning ensures hygiene and proper functioning of your feeder. The feeder is designed for

easy disassembly for cleaning.

1. **Disassemble:** Remove the food bowl, food storage container, and dispensing rotor from the base unit.
2. **Hand Wash:** All removable parts (bowl, container, rotor, lid) can be hand washed with mild soap and water.
3. **Dry Thoroughly:** Ensure all parts are completely dry before reassembling to prevent moisture buildup and maintain food freshness.
4. **Wipe Base:** Wipe the main base unit with a damp cloth. Do not submerge the base unit in water.

Easy to Clean

Provide a clean feeding environment for your pet



The feeder's components are easily detachable for thorough hand washing, ensuring a clean feeding environment.

Food Freshness

The locking lid and desiccant box help keep the food fresh and crunchy, preventing moisture and

maintaining quality.

Locking Lid & Desiccant Box

Effective in keeping food fresh and crunchy



The lid features a desiccant box to absorb moisture and keep kibble fresh.

TROUBLESHOOTING

- **Feeder not dispensing food:**

- Check if the food storage container has enough kibble.
- Ensure the dispensing rotor is correctly installed and not jammed.
- Verify the power connection (AC adapter or batteries).
- Check for food clogs in the dispensing mechanism. The feeder has an anti-clog design, but large kibble or debris can still cause issues.

- **Incorrect time or meal schedule:**

- Unlock the control panel and re-enter the correct time and meal schedules.
- Ensure you are confirming each setting by pressing the 'Settings' button.

- **Voice message not playing:**

- Re-record your voice message, ensuring you press and hold the 'Microphone' button for the full duration.
- Check if the volume is set appropriately (if adjustable).

Anti-Clog Design

Anti-Clog Design

No more worrying about food clogs when you are out



The feeder incorporates an anti-clog design to minimize food blockages during dispensing.

SPECIFICATIONS

- **Model Name:** Automatic Pet Feeder (F14)
- **Capacity:** 3 Liters
- **Dimensions:** 11.5 x 11.5 x 7 inches
- **Weight:** 2.55 pounds
- **Material:** Stainless Steel, Plastic
- **Power:** AC Adapter (included), 3 x D-size batteries (not included)
- **Meals per Day:** Up to 4 programmable meals
- **Portions per Meal:** 1-9 adjustable portions
- **Voice Recording:** 10-second personalized message
- **Care Instructions:** Hand Wash Only (removable parts)
- **Target Species:** Cats, dogs, small animals
- **Country of Origin:** China

WARRANTY AND SUPPORT

The Sarpaws Automatic Pet Feeder comes with a 2-year manufacturer's warranty.

For further support, product information, or to explore other Sarpaws products, please visit the [Sarpaws Store on Amazon](#).