

LEDIARY 68A3BB6BA

LEDIARY 20" Caged Ceiling Fan with Light User Manual

Model: 68A3BB6BA

INTRODUCTION

This user manual provides detailed instructions for the installation, operation, and maintenance of your LEDIARY 20" Caged Ceiling Fan with Light. Designed for various indoor spaces such as kitchens, bedrooms, living rooms, and dining rooms, this low-profile fan combines stylish aesthetics with efficient air circulation and lighting.

SAFETY INFORMATION

Please read all safety instructions carefully before installation and use to prevent injury or damage. Keep this manual for future reference.

- Ensure power is disconnected at the circuit breaker before installation or maintenance.
- All electrical wiring must be performed by a qualified electrician and conform to local codes.
- Do not connect the fan to a dimmer switch.
- Ensure the mounting structure can support the weight of the fan.
- Keep hands, hair, and clothing clear of the fan blades during operation.
- Use only the recommended bulb types: E26 base, A19 ST19 T45, incandescent up to 60W, LED up to 10W.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Caged Ceiling Fan Unit
- Remote Control (Batteries included)
- Mounting Hardware (screws, wire nuts, etc.)
- User Manual
- **Note:** 4*E26 bulbs are NOT included and must be purchased separately.

SPECIFICATIONS

Feature	Detail
---------	--------

Brand	LEDIARY
Model Name	RM (Item model number: 68A3BB6BA)
Color	Black
Product Dimensions	17"D x 12"W x 8"H (20 x 20 x 20 inches; 9.63 Pounds)
Power Source	DC Motor
Voltage	120 Volts (AC)
Wattage	10W (for LED bulbs)
Control Method	App, Remote
Fan Speeds	6
Timer Settings	1/2/4/8 Hours
Special Features	Remote Controlled, Timer, 6 wind speeds, Reversible Mode, Quiet Operation
Room Type	Kitchen, Bedroom, Living Room, Home Office, Dining Room

SETUP AND INSTALLATION

The LEDIARY Caged Ceiling Fan is designed for flush mount installation, making it suitable for rooms with lower ceilings or where a compact design is preferred. Installation is straightforward, typically involving connecting two wires and a ground.

Pre-Installation Checklist:

- Turn off power at the main circuit breaker.
- Ensure you have the necessary tools (screwdriver, wire strippers, etc.).
- Prepare the E26 base bulbs (not included) as per recommendations.

Installation Steps:

1. Carefully unpack all components and verify against the package contents list.
2. Attach the mounting bracket to the ceiling junction box. Ensure it is securely fastened.
3. Connect the electrical wires (live, neutral, ground) from the fan to the corresponding wires in the ceiling.
4. Lift the fan unit and secure it to the mounting bracket. Many units include a hook to temporarily hold the fan during wiring, simplifying the process.
5. Install the 4 E26 bulbs into their sockets.
6. Attach the decorative cage or cover if it's a separate component.
7. Restore power at the circuit breaker.



Silent Operation Ceiling Fan



6 Fan Speeds



1/2/4/8H Timing



Powerful Motor



Quiet Operation



0dB
Mute



15dB
Library



30dB
Our Ceiling Fan



40-60dB
Chat



60-80dB
Meeting



Figure 1: The LEDIARY Caged Ceiling Fan installed, demonstrating its low-profile and compact design suitable for various rooms.



Figure 2: Detail of the E26 bulb socket, highlighting where to install the four required bulbs (not included).

OPERATING INSTRUCTIONS

Your LEDIARY Caged Ceiling Fan offers convenient control via both a remote control and a smartphone application.

Remote Control Functions:

The included remote control provides comprehensive command over your fan's features:

- **Power On/Off:** Turn the fan and light on or off.
- **Fan Speed:** Select from 6 adjustable fan speeds (1-6) to customize airflow.
- **Timer:** Set the fan to automatically turn off after 1, 2, 4, or 8 hours.
- **Reversible Mode (F/R):** Switch between summer mode (downward airflow for cooling) and winter mode (upward airflow for heat circulation).
- **Light Control:** Independently turn the light on or off.
- **Mute Function:** Turn off the beep sound from the fan.

APP & Remote Control

✧ Tips: APP control needs Bluetooth



Speed Control



Timer Setting



F/R Reverse Function



Turn On/Off



Fan On/Off



Figure 3: The remote control and a smartphone displaying the app interface, showing various control options for the fan and light.

App Control (Bluetooth):

For enhanced convenience, download the dedicated app to control your fan via Bluetooth. The app mirrors most remote control functions, allowing you to manage speed, timer, reversible mode, and light settings directly from your smartphone.

MAINTENANCE

Regular maintenance ensures optimal performance and longevity of your ceiling fan.

- **Cleaning:** Dust the fan and light fixture regularly with a soft, dry cloth. For stubborn dirt, use a slightly damp cloth and mild detergent, then wipe dry. Do not use abrasive cleaners.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow bulbs to cool completely. Replace with E26 base bulbs, adhering to the recommended wattage (incandescent up to 60W, LED up to 10W).
- **Tighten Screws:** Periodically check and tighten all screws on the fan and mounting bracket to ensure secure operation.

TROUBLESHOOTING

If you encounter issues with your fan, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Fan does not operate	No power; Loose wiring; Remote battery dead	Check circuit breaker; Verify wiring connections; Replace remote batteries.
Light does not turn on	Bulbs loose or burnt out; Wiring issue	Tighten or replace bulbs; Check light wiring connections.
Fan is noisy	Loose screws; Unbalanced fan blades	Tighten all mounting and motor housing screws; Ensure blades are securely attached and balanced.
Remote control not working	Dead batteries; Obstruction; Not paired	Replace batteries; Remove obstructions between remote and fan; Refer to pairing instructions in the full manual (if applicable).

WARRANTY AND SUPPORT

LEDIARY is committed to providing high-quality products and excellent customer service. Your product comes with a worry-free warranty.

- **Technical Support:** LEDIARY offers 24-hour online technical support to assist with any questions or issues you may encounter.
- **Contact Information:** For support, please visit the official LEDIARY store on Amazon or contact their customer service directly.
- [Visit the LEDIARY Amazon Store](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0D2R95JZZ>

More documents and user manuals: <https://manuals.plus/>