

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Generic](#) /

› [User Manual for Magnetic Mini Security Camera](#)

Generic B0D3BD95BV

User Manual

MAGNETIC MINI SECURITY CAMERA

Model: B0D3BD95BV

Brand: Generic

Introduction

Thank you for choosing the Magnetic Mini Security Camera. This compact and versatile camera is designed to provide reliable surveillance for your home, office, or any desired location. With its 1080p HD resolution, night vision, motion detection, and Wi-Fi connectivity, you can monitor your space anytime, anywhere via a dedicated mobile application.

Package Contents

Please verify that all items are present in your package:

- Mini Camera (Quantity varies by package: 1, 2, 3, or 4)
- Bracket (Quantity varies by package: 1, 2, 3, or 4)
- USB Charging Cable (Quantity varies by package: 1, 2, 3, or 4)
- User Manual (This document)



Image: Contents of the Magnetic Mini Security Camera package, showing two cameras, two magnetic mounts, and two USB charging cables.

Product Overview

Familiarize yourself with the camera's components:



Image: Detailed diagram of the camera highlighting the ON/OFF button, Mode button, Lens, Micro SD card slot, USB output, and IR Night lights.

- **ON/OFF Button:** Powers the camera on or off.
- **Mode Button:** Switches between different operating modes.
- **Lens:** Captures video and images. Features a 150° ultra-wide-angle view.
- **Micro SD Card Slot:** For inserting a Micro SD card (up to 32GB, not included) for local storage of recordings.
- **USB Output:** For charging the camera and connecting to a computer.
- **IR Night Lights:** Six non-luminance infrared lights for night vision up to 6 meters.

Setup

1. Charge the Camera:

Before first use, fully charge the camera using the provided USB charging cable and a 5V power adapter (not included). The charging indicator light will typically change color or turn off when fully charged.

2. Insert Micro SD Card (Optional):

If you wish to store recordings locally, insert a Micro SD card (up to 32GB, Class 10 recommended) into the Micro SD card slot. Ensure the card is inserted correctly until it clicks into place.

3. Download the App:

Scan the QR code in the included mini user manual or search for "HDWiFiCampro" in your mobile app store (iOS/Android) to download and install the camera's control application.

4. Connect to Wi-Fi:

- Power on the camera by pressing the ON/OFF button.
- Open the "HDWiFiCampro" app on your smartphone.
- Follow the in-app instructions to add a new device. This typically involves connecting your phone to the camera's temporary Wi-Fi hotspot first, then configuring the camera to connect to your home Wi-Fi network.
- Ensure your Wi-Fi network is 2.4GHz, as 5GHz networks may not be supported.



Image: Illustration of Wi-Fi connection to a smartphone and the camera's magnetic attachment feature.

5. Mounting the Camera:

The camera features a strong magnetic base, allowing it to be easily attached to any metallic surface. Use the included bracket for wall mounting or positioning on non-magnetic surfaces. The compact design allows for discreet placement in various indoor and outdoor environments.

Operating Instructions

1. Live View and Recording:

Once connected, open the "HDWiFiCampro" app to view the live feed from your camera. You can initiate manual recordings, take snapshots, and access recorded footage directly from the app. The camera records in 1080p HD resolution at 30 frames per second.

2. Night Vision:

The camera automatically switches to night vision mode in low-light conditions. Its 6 non-luminance IR lights provide clear visibility up to 6 meters without emitting visible light, ensuring discreet monitoring.



Image: Day and Night Vision comparison, illustrating the camera's ability to capture clear images in low light.

3. Motion Detection:

Enable motion detection in the app settings. When motion is detected, the camera will automatically start recording and send an alert notification to your smartphone. This feature helps conserve storage space and battery life by only recording when activity occurs.

GUARD YOUR HOME SECURITY ANYTIME ANYWHERE



HD night vision



Motion Detection



Long battery life



Wireless WiFi



Record while charging

Image: Overview of security features including HD night vision and motion detection.

4. Loop Recording:

If a Micro SD card is inserted and full, the camera will automatically overwrite the oldest video files to continue recording. Ensure this setting is enabled in the app if you require continuous recording.

5. Remote Viewing:

With the camera connected to your home Wi-Fi and your phone connected to the internet, you can access the live feed and recordings from anywhere in the world via the "HDWiFiCampro" app.

Maintenance

- Cleaning:** Use a soft, dry cloth to clean the camera lens and body. Avoid using liquid cleaners or abrasive materials.
- Battery Care:** To prolong battery life, avoid extreme temperatures and fully charge the camera before long periods of inactivity.
- Storage:** When not in use, store the camera in a cool, dry place away from direct sunlight.
- Firmware Updates:** Periodically check the "HDWiFiCampro" app for any available firmware updates to ensure optimal performance and security.

Troubleshooting

Problem	Possible Cause / Solution
Camera not turning on.	Battery is depleted. Charge the camera fully.
Cannot connect to Wi-Fi.	<ul style="list-style-type: none"> Ensure your Wi-Fi network is 2.4GHz. Check Wi-Fi password. Camera is too far from the router. Move closer. Reset the camera (refer to app or mini manual for reset procedure).
No recording or footage missing.	<ul style="list-style-type: none"> Micro SD card not inserted or full. Micro SD card corrupted. Format or replace. Motion detection not enabled or sensitivity too low.
Poor video quality.	<ul style="list-style-type: none"> Dirty lens. Clean with a soft cloth. Insufficient lighting (for day vision). Weak Wi-Fi signal.

Specifications

Feature	Detail
Model	Magnetic Mini Security Camera (ASIN: B0D3BD95BV)
Video Resolution	1080p HD
Frame Rate	30 fps
Lens Angle	150° Wide Angle
Night Vision Distance	Up to 6 meters (with 6 non-luminance IR lights)
Connectivity	Wi-Fi (2.4GHz)
Storage	Micro SD Card (up to 32GB, not included)
Power Source	Battery Powered (1 Lithium Polymer battery included)
Voltage	5 Volts
Control Method	Mobile App ("HDWiFiCampro")
Mounting Type	Magnetic, Wall Mount
Indoor/Outdoor Usage	Indoor, Outdoor
Material	Aluminum Alloy

Warranty and Support

For warranty information and technical support, please refer to the contact details provided with your purchase or visit the manufacturer's official website. Keep your purchase receipt as proof of purchase. This product is manufactured by Generic.

© 2024 Generic. All rights reserved.